

**User's Guide for New MOSES
Version 2.0
(MMode-coupling Single bunch instability
in an Electron Storage ring)***

Yong Ho Chin

Center for Beam Physics
Lawrence Berkeley Laboratory
University of California
Berkeley, CA 94720

Abstract

MOSES is a computer program which computes (complex)coherent betatron tune shifts as a function of the bunch current for a Gaussian beam and provides their graphical representation on a line printer. The new version of MOSES presented in this note is different in two respects from the old one: (1) the betatron tune may have a spread, (2) the synchrotron tune can be varied as a function of current as the user wishes. The method of calculation in the presence of betatron tune spread can be chosen to be either the author's dispersion integral method or Besnier's dispersion matrix method. The outline of these methods is explained in the Appendix. MOSES is available as source code in both the CERN-IBM VM/CMS and the MVS/Wylbur System.

* This work was supported by the Director, Office of Energy Research, Office of High Energy and Nuclear Physics, High Energy Physics Division, of the U.S. Department of Energy under Contract No. DE-AC03-76SF00098.

I. Introduction

A bunched beam in a storage ring interacts with its environment electromagnetically by exciting wake fields. These fields kick the beam, and the oscillation frequency of coherent particle motion may be changed. When the frequencies of two different transverse coherent motions coincide, one of those motions will become unstable, with a growth rate comparable to the synchrotron frequency. This is called a transverse mode-coupling instability[1, 2]. MOSES (MOde-coupling Single bunch instability in an Electron Storage ring) is a computer program which computes oscillation tunes of transverse coherent motion as a function of the bunch current for a Gaussian beam, and provides their graphical representation on a line printer. The first version of MOSES was published in 1986[3]. Since then, it has been shown in several publications that the program gives good agreement with computer simulations[4]. MOSES was installed to the program BBI by Zotter and Gygi-Hanney[5], and can be called from the inside of BBI or can be used as a stand-alone program. The new version of MOSES presented in this note has the following two differences from the old version:

1. The betatron tune may have a spread.
2. The synchrotron frequency can be varied with the bunch current as the user wishes.

The method of calculation in the presence of betatron tune spread can be chosen to be either the author's dispersion integral method[6] or Besnier's dispersion matrix method[7]. Their outline is explained in the Appendix. Details of the formalism can be found in Refs.(6-8). In the former method, solutions are obtained by finding zeros of the determinant of a certain complex matrix. This method is valid only when the zeros have non-zero imaginary parts. Stationary solutions cannot be calculated correctly. However, some users might want to guess where the tunes of stationary modes will appear, even if it is rough guess. MOSES provides such a guess, by assuming that a stationary solution may be approximated roughly by the purely real value which gives a local minimum to the absolute value of the determinant, and by searching such a point with a minimization program. Sometimes the program fails to find local minima for large tune spreads, mainly because they are not well defined or do not exist. On the contrary, solutions in the latter method are obtained as eigenvalues of the complex matrix as in the absence of tune spread, and hence are determined without uncertainty. But this requires a rather large matrix size ($\sim 100 \times 100$) for accurate solutions, and therefore is very time consuming (actually solutions converge to those obtained with the dispersion integral method in the limit of infinite matrix size). A combined use of the two methods is therefore recommended. We discuss this problem again in Sec.4.

There are some new variables related to the above differences. There is no change in the old variables, so the user can still use input data for the old version. These old variables are already explained in Ref.3. However, for the convenience of the reader, I shall try to make this note serve as a full user's guide by explaining all input variables, even if many of them may have been described in Ref.3.

The output of MOSES contains, in addition to the printout of all input parameters, complex values of the coherent tune shifts of a specified number of modes, and their graphical representation on a line printer. In the following sections, we will explain the definitions of the input variables and how to interpret the output, referring to an example for a test job.

The final section is devoted to some remarks on how to search coherent tune shifts in the presence of betatron tune spread and how to interpret the results.

II. Input variables

Two sample input data, one for LEP without betatron tune spread, and another for DCI of Orsay with betatron tune spread, are given in Figs. 1 and 2, respectively. They consist of one headline and five (four if no betatron tune spread) **NAMelist** formats. If you are a user of the CERN IBM VM/CMS, you must have access to the LEPth disk, where you will find a copy of the files: MOSES FORTRAN (source code), MOSES EXEC (EXEC file for executing MOSES), MOSES HELPCMS file and a test data file TEST MOSDATA. The content of MOSES EXEC file is shown in Fig. 3.

If you don't know about the LEPth disk ...

You need log in to CERNVM and type **GIME PMG 195** to obtain access to the disk. Then the command **LEPthDSK** will allow you to take full advantage of the software on the disk, including permanent access if you wish. This command will also guide you to the on-line HELP information which includes help for using MOSES.

In order to run the program, you must have a data file on the A-disk, called fn MOSDATA. If fn is not specified, it is assumed to be TEST. (For test purposes you could copy the TEST MOSDATA file from the LEPth disk). Then type in:

```
MOSES fn
```

The results will be on the file MOSES RESULTS on your A-disk.

If you are a user of the MVS/Wylbur, you can get the same input data with the JCL (job control card) by typing in Wylbur mode

```
EXEC FROM $IZ.ZOT.LIB#MOSESTST
```

and answering the questions. We list all input variables with brief explanations, their units or formats, and default values in what follows.

| | |
|--------------|--------------------|
| TITLE | FORMAT(A72) |
|--------------|--------------------|

The title of the program run which may be printed as header to the program. If you do not want a title, leave it blank, but never eliminate the line.

| | | |
|-----------------|-------------------|--------------------------------------|
| NAMelist | &MPARM | defines machine and beam parameters. |
|-----------------|-------------------|--------------------------------------|

| | |
|------------|---|
| NUS | Synchrotron tune. If NUS > 0, the synchrotron tune is kept constant as input while the bunch current varies. If NUS = 0, the synchrotron tune varies with the bunch current according to the user specified |
|------------|---|

| | | |
|---------------------------------------|-----------------------|---|
| | | arrays of the synchrotron tunes NUSTOC(i) and the bunch currents CTONUS(i) (see also the explanation of NUSTOC and CTONUS for more details.) If NUS < 0, the synchrotron tune varies with the bunch current according to a user defined function. The user must supply a synchrotron tune function into the source program. Copy the source file into your file, and edit the subroutine function FNUS(X) following the instruction written there. |
| ENGY | GeV | Beam energy. |
| SGMZ | cm | Bunch length. If SGMZ > 0, the bunch length kept constant as input while the bunch current varies. If SGMZ = 0, the bunch length varies with the bunch current according to the user specified arrays of the bunch lengths SGMTOC(i) and the bunch currents CTOSGM(i) (see also the explanation of SGMTOC and CTOSGM for more details.) If SGMZ < 0, the bunch length varies with the bunch current according to a user defined function. The user must supply a bunch length function into the source program. Copy the source file into your file, and edit the subroutine function FSGM(X) following the instruction written there. |
| BETAC | meter | Beta-function at the location of the impedance. |
| REVFRQ | MHz | Revolution frequency of a reference particle. |
| ALFA | | Momentum compaction factor. |
| CHROM | (default=0) | Linear chromaticity defined by $d\nu_x/dp/p$. |
| SPRD | (default=0) | Betatron tune spread at one standard deviation of bunch length. A parabolic amplitude dependence of tune spread is assumed, namely $\nu_x = \nu_{x0} - \text{SPRD} \cdot \left(\frac{r_x}{\sigma_x}\right)^2$. See also the Appendix. |
| NUSTOC(i), CTONUS(i) | mA (i ≤ 120) | When NUS = 0, these variables are used: NUSTOC(i) is the array to store the synchrotron tunes at the bunch currents CTONUS(i) . The synchrotron tune between two points CTONUS(i) and CTONUS(i+1) is calculated by linear interpolation. |
| SGMTOC(i), CTOSGM(i) | cm mA (i ≤ 120) | When SGMZ = 0, these variables are used: SGMTOC(i) is the array to store the bunch lengths at the bunch currents CTOSGM(i) . The bunch length between two points CTOSGM(i) |

and `CTOSGM(i+1)` is calculated by linear interpolation.

NAMelist **&IPARM** defines parameters of the transverse impedance.
A resonator model is assumed for the impedance.

FREQ **MHz** Resonant frequency of the impedance.
RS **MΩ/m** Impedance at the resonant frequency.
QV Quality factor.

NAMelist **&CPARM** parameters relevant to the computation of
coherent tune shifts and control card for printout.

CRNT **mA** The first bunch current with which the computation
starts. The value must be larger than zero.
STPC **mA** Step on increase in bunch current. The bunch current
varies as **CRNT**, **CRNT+STPC**, ..., **CRNT + STPC × (NCR-1)**.
Can be negative.
NCR (default=60) Number of steps on change in bunch current to
be executed. Must be less than 120.
NMODE (default=-2) The lowest azimuthal mode number to be included
in the calculation.
NMODF (default=1) The highest azimuthal mode number to be included
in the calculation.
KRAD (default=0) Number of higher longitudinal radial modes to be
used for expansion of the radial function for each
azimuthal mode. Note that zero means that each
azimuthal mode has one radial mode.
LPRINT Logical*1
(default=T) When **LPRINT = .TRUE.**, numerical values of
coherent tune shifts normalized by the synchrotron
tune are printed with the bunch length and the
synchrotron tune for each bunch current.
LPLE Logical*1
(default=F) Plot the real and imaginary parts of coherent tune
shifts in units of the synchrotron tune.

NAMelist **&HPARM** defines the window of graphical output of
coherent tune shifts on a line printer.

MMAx (default= The maximum coordinate of the figure of the real

| | | |
|-----------------|--------------------------------|---|
| | NMODF) (default= | part of coherent tune shifts. |
| MMIN | NMODE) (default=0.1) | The minimum coordinate of the figure of the real part of coherent tune shifts. |
| TAUMAX | | The maximum coordinate of the figure of the imaginary part of coherent tune shifts. |
| TAUMIN | (default=-0.1) | The minimum coordinate of the figure of the imaginary part of coherent tune shifts. |
| NSPL | (default=1) | Number of split pictures of the real part of coherent tune shifts. |
| NAMelist | &SPARM | defines parameters necessary for searching coherent tune shifts in the presence of betatron tune spread. If SPRD = 0 , this NAMelist is not read. See also remarks in Sec.4. |
| LMTRIX | Logical*1 (default=F) | When LMTRIX = .TRUE. , Besnier's dispersion matrix method is used. The user has to specify NDISP , number of higher transverse radial modes for expansion of the transverse dipole distribution. |
| LINTGL | Logical*1 (default=T) | When LINTGL = .TRUE. , the dispersion integral method is used. The user has to specify all variables from NSTPS down to CXMAX described in this NAMelist . Solutions are identified as points which give zeros or local minima of the absolute value of the determinant of the matrix A defined in the Appendix. The simplex method and the Müller method are used for minimum search. For a large tune spread, it is recommended to increase the tune spread gradually from a small value to the desired one, using NSTPS and SPRD0 parameters. |
| LMAP | Logical*1 (default=F) | When LMAP = .TRUE. , the absolute value of the determinant of the matrix A defined in the Appendix is plotted on line printer as a function of real tune shift in a interval (MMIN , MMAX) with increment 0.05 between points. The subroutine MAP in CERN GENLIB is also used for plotting. See also remarks in Sec.4. |
| NDISP | (default=9) | Number of higher transverse radial modes for expansion of the dipole particle distribution. Used only when LMTRIX = .TRUE. |
| NSTPS | (default=1) | Number of steps for changing the tune spread. Must be less than 10 on VM and 6 on MVS. |

| | | |
|--------------|------------------|--|
| | | If the starting tune spread, SPRD0 , is not zero, NSTPS has to be larger than two. The tune spread at each step is : $\text{SPRD} \times i / \text{NSTPS}$, $i = 1$ to NSTPS , when SPRD0 = 0, $\text{SPRD0} + (\text{SPRD} - \text{SPRD0}) \times (i - 1) / (\text{NSTPS} - 1)$, $i = 1$ to NSTPS , when SPRD0 > 0. |
| SPRD0 | (default=0) | Starting betatron tune spread. |
| EX | (default=0.1) | Initial search step for the real part of the tune shifts. Search is done in both directions EX and -EX . |
| EY | (default=0.01) | Initial search step for the imaginary part of the tune shifts. |
| FEPS | (default=1.D-10) | Criterion for convergence of the function value. |
| ZEPS | (default=0) | Criterion for convergence of the solution. When zero, this criterion will be ignored. |
| DXMAX | (default=0.5) | The maximum difference of the real tune shift in which the initial estimate of solutions is taken from the results for one current step smaller. See also remarks in Sec.4. |
| ESPC | (default=0.001) | The minimum distance between different solutions in the complex plane. If their distance is within this value, they are considered to be the same solution. |
| CXMAX | (default=0.5) | The maximum change in real tune shift which can be accepted as a solution for the current one step larger. If the change is larger than this value, that solution is neglected. |

III. Output of MOSES

The output for the test inputs given by Figs. 1 and 2 are shown in Figs. 4 and 5, respectively. We will briefly explain how to interpret this for the reader's convenience. The beginning of the output is signalled by the title of the program followed by the date, time and the version number of MOSES. All the input variables are printed with short explanations of their definitions and with their units. Next follows the printout of the bunch length and the synchrotron tune as a function of the bunch current if they vary with the current. When **SGMZ(NUS)** = 0, the content of the arrays **SGMTOC** and **CTOSGM** (**NUSTOC** and **CTONUS**) will be printed. If **LPRINT** = **.TRUE.**, complex values of all coherent tune shifts, normalized by the synchrotron tune, are printed for each bunch current together with the bunch length and the synchrotron tune. If **SPRD** \neq 0 and **LINTGL** = **.TRUE.**, the betatron tune spread is printed at the head of printout.

The normalized coherent tune shifts are plotted at separate pages by line printer. The window of these figures are defined in **NAMELIST \$HPARM**. The title of the job, date, time and the tune spread are printed in the header line. If **SPRD** \neq 0, the method used for finding solutions is also typed.

If **LPLE**=**.TRUE.** in **CPARM**, a TopDrawer input file for plots of the normalized coherent

tune shifts are created in a file called `fn TOPDRAW`, where `fn` is the file name of your input data. In order to view plots, you must execute a local `TopDrawer` command on this file.

IV. Some remarks

In this final chapter, we add some remarks on the computation algorithm and on the interpretation of results for the case of nonzero betatron tune spread. First, we consider the case where the dispersion integral method is used. There is no uniquely defined way to calculate coherent tune shifts for stationary modes, only when the imaginary part of tune shifts becomes nonzero, solutions can be rigorously obtained. This corresponds to the fact that there is no method of the mapping from the complex tune-shift plane to the stable region in the stability diagram. In MOSES, it is assumed that such a stationary solution may be approximated by a purely real tune which corresponds a local minimum of the absolute value of the determinant of the matrix **A** (see Appendix for its definition). This assumption is reasonable, since zeros of this determinant are true eigensolutions when the tune spread is zero. Therefore, one may expect that this function will still have well-defined local minima around solutions as long as the tune spread is small. However, it is not clear how good or bad this approximation is for large tune spreads. There is even no physical foundation for the existence of local minima. The user has to keep in mind that tunes of stationary solutions provided by MOSES have meaning only as a guide for the user's convenience. When MOSES fails to find stationary solutions, this might be due to the nature of the problem.

The parameter **DXMAX** is related to the initial estimate of solutions. There are two ways to set the initial estimate: from the result for a smaller tune spread at the same current, or from the result for a smaller current at the same tune spread. MOSES decides which value should be taken through a rather complicated algorithm: First, it takes the initial value from the solution for the tune spread one step smaller (if **NSTPS** = 1, from the solution for no tune spread) at the same current. We shall call it **X0**. If there is a solution within $\pm \mathbf{DXMAX}$ around **X0** for the current one step smaller, at the same tune spread, the program replaces **X0** by this value. In this process, any two solutions whose distance is less than **ESPC** in complex tune space are supposed be the same solution, and one of them is not therefore used as an initial estimate of the solution for the next current. If the solution from the minimization program lies further away from the initial estimate than **CXMAX**, it is rejected.

Sometimes the minimization program converges to the same local minimum or fails to find a local minimum at all. If this happens, the following recipe might be worth to try:

- Set **STPC** negative, and compute backwards from the largest current.
- Try a finer step size for changing the tune spread, using **NSTPS**.
- Change the parameters **DXMAX**, **CXMAX**, **EX,EY,FEPS**, and **ZEPS**.
- If the **m=0** mode is not found, set **NMODF** to a larger value.

If solutions cannot be found even after all these tries, and if the user is interested in finding all local minima if they exist, he should use the **LMAP** parameter. It gives a graphical picture of the function to be minimized, as function of the real tune shift in the interval (**MMIN,MMAX**) with distance 0.05 between neighboring points. The user may then find what is going on by his inspection.

Next, we consider the Besnier's dispersion matrix method. This method has the advantage that all solutions are always obtained, no matter whether solutions are stationary or unstable. It has, however, the following two drawbacks: (1) We need a large number of orthogonal polynomials to expand the transverse dipole distribution for accurate calculation. A suitable **NDISP** is around $\text{SPRD} \times 500 / \text{NUS}$. (2) There is no stability threshold. This might be explained physically as follows. In this method, a infinite set of δ functions or shell distributions, each having a different tune determined by its phase space amplitude, is approximated by a finite set of orthogonal coherent distributions. In reality, Landau damping is due to the fact that the energy of unstable coherent oscillations is absorbed by those shell distributions whose oscillation frequency resonates with the coherent one. This situation is now described by only a few orthogonal distributions. Therefore the share of each orthogonal distribution becomes relatively large, and they will always remain slightly unstable in order to suppress a strongly unstable mode. In this method, the number of eigensolutions will be quite large. It will be helpful to split the picture for the real parts of the coherent tune shift by using the **NSPL** parameter.

Acknowledgements

The author would like to thank B. Zotter for proposing the problem and for helpful discussions, and P.M.Gygi-Hanney for her support with the CERN-IBM VM/CMS System. He also would like to thank E. Keil and the LEP TH Group for its hospitality.

Appendix: The dispersion integral and Besnier's dispersion matrix methods

In this appendix, we outline the two methods used for calculation in the presence of betatron tune spread. The definition of notations follows those in Ref.1.

The equation which we want to solve has the form of an integral equation for particle distribution:

$$[\nu - m\nu_s - \nu_x(r_x)]f(r_x)g_m(r_s) = -\nu_s D \frac{df_0}{dr_x} w_s(r_s) \sum_n \int_0^\infty G_n^m(r_s, r'_s) g_n(r'_s) dr'_s, \quad (1)$$

where $f(r_x)$ and $g_m(r_s)$ are the perturbed transverse and longitudinal distributions as a function of the phase space amplitudes r_x and r_s , respectively, and ν is the coherent tune to be determined. We assume that the betatron tune ν_x is a function of r_x only and can be expressed as

$$\nu_x = \nu_{x0} - S_x(r_x). \quad (2)$$

The explicit form of the kernel $G_n^m(r_s, r'_s)$ can be derived from Eq.(2.22) of Ref.1. The transverse dipole moment D is given by

$$D = \pi \int_0^\infty f(r_x) r_x^2 dr_x. \quad (3)$$

The other notations are as follows: ν_s is the synchrotron tune, $f_0(r_x)$ is the transverse unperturbed distribution, and $w_s(r_s)$ is the longitudinal weight function. First we show how to solve Eq.(1) according to the dispersion integral method.

If we divide both sides of Eq.(1) by $(\nu - m\nu_s - \nu_x(r_x))$, multiply by r_x^2 , and integrate over r_x , we obtain

$$g_m(r_s) = F_m(\nu) w_s(r_s) \sum_n \int_0^\infty G_n^m(r_s, r'_s) g_n(r'_s) dr'_s, \quad (4)$$

where

$$F_m(\nu) = -\nu_s \pi \int_0^\infty \frac{\frac{df_0}{dr_x} r_x^2 dr_x}{\nu - m\nu_s - \nu_x(r_x)}. \quad (5)$$

We solve Eq.(4) by expanding the unknown function $g_m(r_s)$ into normalized orthogonal polynomials which satisfy the relation

$$\int_0^\infty w_s(r_s) h_k^{(m)}(r_s) h_l^{(n)}(r_s) r_s dr_s = \delta_{mn} \delta_{kl}. \quad (6)$$

The kernel can also be expanded with the same orthogonal polynomials. The results are:

$$g_m(r_s) = w_s(r_s) \sum_{k=0}^\infty a_k^{(m)} h_k^{(m)}(r_s), \quad (7)$$

$$G_n^m(r_s, r'_s) = \sum_{k,l} M_{nl}^{mk} h_k^{(m)}(r_s) h_l^{(n)}(r'_s). \quad (8)$$

The explicit form of the matrix element M_{nl}^{mk} is given by Eq.(2.44) in Ref.1. Multiplying Eq.(4) by $h_k^{(m)}(r_s) r_s$ and integrating over r_s , we obtain

$$a_k^{(m)} = F_m(\nu) \sum_{n=-\infty}^\infty \sum_{l=0}^\infty M_{nl}^{mk} a_l^{(n)}. \quad (9)$$

The set of equations has a non-trivial solution only if

$$\det \mathbf{A} = 0, \quad (10)$$

where \mathbf{A} is the matrix with elements

$$A_{nl}^{mk} = \delta_{mn} \delta_{kl} F_m^{-1}(\nu) - M_{nl}^{mk}. \quad (11)$$

The condition(10) may be called a generalized dispersion relation.

If $f_0(r_x)$ is a Gaussian distribution with a beam size σ_x :

$$f_0(r_x) = \frac{1}{2\pi\sigma_x^2} \exp\left(-\frac{r_x^2}{2\sigma_x^2}\right) \quad (12)$$

and the tune spread $S_x(r_x)$ has a parabolic dependence on r_x :

$$S_x(r_x) = S\left(\frac{r_x}{\sigma_x}\right)^2, \quad (13)$$

the integration of F_m is achieved readily, with the result

$$F_m(\nu) = \frac{\nu_s}{2S} [1 - \tau e^\tau E_1(\tau)], \quad (14)$$

where $E_1(x)$ is the exponential integral[9], and

$$\tau = \frac{\nu - m\nu_s - \nu_{x0}}{2S}. \quad (15)$$

Next, we solve Eq.(1) by Besnier's dispersion matrix method. In this method, we expand, not only the longitudinal distribution $g_m(r_s)$, but also the transverse distribution $f(r_x)$. Using the orthogonal polynomials $d_s(r_x)$ which satisfy

$$\int_0^\infty w_x(r_x) d_s(r_x) d_t(r_x) r_x dr_x = \delta_{st}, \quad (16)$$

where $w_x(r_x)$ is the transverse weight function defined by

$$w_x(r_x) = K \frac{1}{r_x} \frac{df_0(r_x)}{dr_x}, \quad (17)$$

with the normalizing factor K , $f(r_x)$ can be expanded as

$$f(r_x) = w_x(r_x) \sum_{s=0}^{\infty} c_s d_s(r_x). \quad (18)$$

We expand also the product of $S_x(r_x)$ and $f(r_x)$ in the same orthogonal polynomials:

$$S_x(r_x) f(r_x) = w_x(r_x) \sum_{s=0}^{\infty} b_s d_s(r_x), \quad (19)$$

where the coefficients b_s are related to the coefficients c_t by

$$b_s = \sum_{t=0}^{\infty} N_{st} c_t, \quad (20)$$

where

$$N_{st} = \int_0^\infty S_x(r_x) w_x(r_x) d_s(r_x) d_t(r_x) r_x dr_x \quad (21)$$

is called the dispersion matrix.

The transverse dipole moment D can now be expressed with the coefficients c_s by inserting Eq.(18) into Eq.(3), with the result

$$D = \pi \sum_s c_s \int_0^\infty w_x(r_x) d_s(r_x) r_x^2 dr_x. \quad (22)$$

If one uses the fact that the lowest polynomial is proportional to r_x :

$$d_0(r_x) = \kappa r_x, \quad (23)$$

one finds that only the lowest coefficient in the summation remains. Therefore,

$$D = \pi \frac{c_0}{\kappa}. \quad (24)$$

If we insert Eqs.(17-20) and (24) into Eq.(1) and notice that $-\pi\kappa^2/K$ is one, Eq.(1) can be rewritten as

$$\begin{aligned} & [(\nu - m\nu_s - \nu_{x0})w_x(r_x) \sum_s c_s d_s(r_x) + w_x(r_x) \sum_{s,t} N_{st} c_t d_s(r_x)] g_m(r_s) \\ &= \nu_s w_x(r_x) c_0 d_0(r_x) \times w_s(r_s) \sum_n \int_0^\infty G_n^m(r_s, r'_s) g_n(r'_s) dr'_s. \end{aligned} \quad (25)$$

By inserting Eq.(8) into Eq.(25), multiplying by $h_k^{(m)}(r_s) r_s \cdot d_s(r_x) r_x$, and integrating over r_s and r_x , we obtain

$$[(\nu - m\nu_s - \nu_{x0})c_s + \sum_{t=0}^\infty N_{st} c_t] a_k^{(m)} = \nu_s c_0 \delta_{s0} \sum_{n=-\infty}^\infty \sum_{l=0}^\infty M_{nl}^{mk} a_l^{(n)}. \quad (26)$$

If one defines new coefficients

$$e_{ks}^{(m)} = c_s a_k^{(m)}, \quad (27)$$

these coefficients have a non-trivial solution only if

$$\det(\lambda \mathbf{I} - \mathbf{B}) = 0, \quad (28)$$

where

$$\lambda = \frac{\nu - \nu_{x0}}{\nu_s} \quad (29)$$

is the normalized tune shift, \mathbf{I} is the unit matrix, and \mathbf{B} is the matrix with elements

$$B_{tnl}^{smk} = m \delta_{st} \delta_{mn} \delta_{kl} - \frac{N_{st}}{\nu_s} \delta_{mn} \delta_{kl} + M_{nl}^{mk} \delta_{s0} \delta_{t0}. \quad (30)$$

For a $f_0(r_x)$ of a Gaussian distribution, and S_x of Eq.(13), elements of the dispersion matrix are written explicitly as

$$N_{kl} = 2S[2(k+1)\delta_{kl} - \sqrt{(k+1)(l+1)}\delta_{k+1,l} - \sqrt{(k+1)(l+1)}\delta_{k-1,l}]. \quad (31)$$

References

- [1] Y. H. Chin, CERN SPS/85-2 (DI-MST), 1985.
- [2] G. Besnier, D. Brandt, and B. Zotter, CERN LEP-TH/84-11, 1984.
- [3] Y. H. Chin, CERN SPS/86-2 (DI-MST), 1986.
- [4] D. Brandt, J. P. Delahaye, and A. Hofman, CERN LEP Note 595, 1987.
- [5] P. M. Gygi, CERN LEP Theory Note 60, 1988.
- [6] Y. H. Chin, CERN SPS/85-9 (DI-MST), 1985.
- [7] G. Besnier, Nucl. Instru. and Methods, **164**, 235 (1974).
- [8] B. Zotter, CERN SPS/81-19 (DI), 1981.
- [9] M. Abramowitz and I. A. Stegun, *Handbook of Mathematical Functions*, (Dover, New York, 1965).

```

SAMPLE INPUT #1  LEP AT INJECTION WITHOUT BETATRON TUNE SPREAD
&MPARM
NUS=0.089931D0, ENGY=20.D0, SGMZ=2.500D0,  BETAC=40.7D0,
REVFRQ=0.0112455D0, ALPHA=3.867D-4, CHROM=0.D0, SPRD=0.0
&END
&CPARM
CRNT=0.00D0, STPC=0.005D0, NCR=201, NMODF=-2, NMODE=1, KRAD=2
IPRINT=.TRUE., LPLE=.TRUE.
&END
&IPARM
FREQ=2000.D0, RS=2.00D0, QV=1.00D0
&END
&HPARM
MMIN=-3, MMAX=2, TAUMIN=-0.5, TAUMAX=0.5
&END

```

Figure 1: Sample input data # 1.

```

SAMPLE INPUT #2  DCI OF ORSAY WITH BETATRON TUNE SPREAD
&MPARM
NUS=0.00792D0, ENGY=.8D0, SGMZ=-1.D0, BETAC=8.86D0
REVFRQ=3.17D0, ALFA=7.88D-2, CHROM=0.D0, SPRD=5.D-4
&END
&CPARM
CRNT=4.0D0, STPC=4.0D0, NCR=99,  NMODF=-2, NMODE=1, KRAD=0
IPRINT=.TRUE., LPLE=.TRUE.
&END
&IPARM
FREQ=1300.D0, RS=.4D0, QV=1.00D0
&END
&HPARM
MMIN=-3, MMAX=1, TAUMIN=-.1, TAUMAX=.1
&END
&SPARM
LMTRIX=.FALSE., LINTGL=.TRUE., LMAP=.FALSE., NDISP=0, NSTPS=1, SPRD0=0.,
EX=0.1, EY=0.01, FEPS=1.0D-10, ZEPS=0.0, DXMAX=0.5, ESPC=0.001,
CXMAX=0.5
&END

```

Figure 2: Sample input data # 2.

```

/* Running MOSES Version 3.3, March 1994 */
arg fn .
'EXEC CERNLIB NAGLIB GENLIB'
'FILEDEF 5 DISK' fn 'DATA A (PERM'
'FILEDEF 6 DISK' fn 'RESULTS A (PERM'
'FILEDEF 9 DISK' fn 'TOPDRAW A (PERM'
/* 'EXEC VFORT MOSES (NOSOURCE NOMAP NOPRINT GO' */
'LOAD MOSES (NOAUTO CLEAR'
'START * NOXUFLOW'
exit

```

Figure 3: MOSES EXEC file to run MOSES on CERN IBM VM/CMS system.

```

*****
*                                     *
*                               MOSES *
*                                     *
*  Mode-coupling Single bunch instability in an Electron Storage ring *
*                                     *
*  SAMPLE INPUT #1  LEP AT INJECTION WITHOUT BETATRON TUNE SPREAD *
*                                     *
*    DATE:30/ 8/ 5    TIME:13:12:10    VERSION 4.0,    AUGUST    2005 *
*                                     *
*****

```

```

$MAPRM:
SYNCHROTRON TUNE      : NUS      = 0.89931E-01
BEAM ENERGY          : ENGZ      = 20.000    (GeV)
RMS BUNCH LENGTH      : SGMZ      = 2.5000    (cm)
BETA-FUNCTION AT IMPEDANCE : BETAC   = 40.700    (m)
REVOLUTION FREQUENCY  : REVFRQ    = 0.11245E-01 (MHz)
MOMENTUM COMPACTION FACTOR : ALPHA   = 0.38670E-03
CHROMATICITY          : CHROM      = 0.0000
BETATRON TUNE SPREAD AT SIGMA : SPRD    = 0.0000

```

```

$I Parm:
RESONANT FREQUENCY    : FREQ      = 2000.0    (MHz)
IMPEDANCE              : RS        = 2.0000    (MOhm/m)
Q - VALUE              : QV        = 1.0000

```

```

$C Parm:
STARTING CURRNT        : CRNT      = 0.0000    (mA)
STEP IN CURRENT        : STPC      = 0.50000E-02 (mA)
NUMBER OF STEPS IN CURRENT : NCR      = 201
LOWEST AZIMUTHAL MODE   : NMODF    = -2
HIGHEST AZIMUTHAL MODE  : NMODE    = 1
NUMBER OF LONG. RADIAL MODES : KRAD     = 2
PRINT OF EIGENVALUES    : IPRINT   = T
USE OF A BINOMIAL DISTRIBUTION : LBIN     = F

```

```

$H Parm:
MAXIMUM AZIMUTHAL MODE IN PLOT : MMAX     = 2
MINIMUM AZIMUTHAL MODE IN PLOT : MMIN     = -3
MAXIMUM COORDINATE IN TAU PLOT : TAUMAX    = 0.50000
MINIMUM COORDINATE IN TAU PLOT : TAUMIN    = -0.50000
NUMBER OF SPLITTED PLOTS      : NSPL      = 1

```


*****>>> EIGEN VALUES (Nu-Nux)/Nus VS. BUNCH CURRENT <<<*****

BETATRON TUNE SPREAD = 0.0000

| Current (mA) / | 0.0000 | 0.0050 | 0.0100 | 0.0150 | 0.0200 |
|---------------------|----------------------|----------------------|----------------------|----------------------|--------|
| Bunch length (cm) / | 2.5000 | 2.5000 | 2.5000 | 2.5000 | 2.5000 |
| Synchrotron tune / | 0.0899 | 0.0899 | 0.0899 | 0.0899 | 0.0899 |
| (Nu-Nux)/Nus ... | (REAL : IMAGINARY) | | | | |
| -2.00 : 0.00 | -2.00 :-.557E-13 | -2.00 :-.111E-12 | -2.00 :-.167E-12 | -2.00 :-.222E-12 | |
| -2.00 : 0.00 | -2.00 :-.521E-13 | -2.00 :-.104E-12 | -2.00 :-.156E-12 | -2.00 :-.208E-12 | |
| -2.00 : 0.00 | -2.00 :0.451E-13 | -2.00 :0.892E-13 | -2.00 :0.133E-12 | -2.00 :0.176E-12 | |
| -1.00 : 0.00 | -.377E-02 :-.230E-12 | -.754E-02 :-.460E-12 | -.113E-01 :-.690E-12 | -.151E-01 :-.920E-12 | |
| -1.00 : 0.00 | 0.277E-03 :-.495E-13 | 0.554E-03 :-.987E-13 | 0.832E-03 :-.148E-12 | 0.111E-02 :-.198E-12 | |
| -1.00 : 0.00 | 1.00 :-.798E-13 | 1.00 :-.159E-12 | 1.00 :-.236E-12 | 1.00 :-.313E-12 | |
| 0.00 : 0.00 | 1.00 :-.595E-13 | 1.00 :-.118E-12 | 0.999 :-.176E-12 | 0.999 :-.232E-12 | |
| 0.00 : 0.00 | 1.00 :0.332E-13 | 1.00 :0.667E-13 | 1.00 :0.101E-12 | 1.00 :0.135E-12 | |
| 0.00 : 0.00 | -1.00 :-.807E-13 | -.999 :-.163E-12 | -.999 :-.246E-12 | -.999 :-.330E-12 | |
| 1.00 : 0.00 | -1.00 :-.603E-13 | -1.00 :-.121E-12 | -1.00 :-.182E-12 | -1.00 :-.243E-12 | |
| 1.00 : 0.00 | -1.00 :0.325E-13 | -1.00 :0.645E-13 | -1.00 :0.960E-13 | -1.00 :0.127E-12 | |
| 1.00 : 0.00 | -.248E-06 :-.948E-13 | -.496E-06 :-.190E-12 | -.744E-06 :-.284E-12 | -.991E-06 :-.379E-12 | |

| Current (mA) / | 0.0250 | 0.0300 | 0.0350 | 0.0400 | 0.0450 |
|----------------------|----------------------|----------------------|----------------------|----------------------|--------|
| Bunch length (cm) / | 2.5000 | 2.5000 | 2.5000 | 2.5000 | 2.5000 |
| Synchrotron tune / | 0.0899 | 0.0899 | 0.0899 | 0.0899 | 0.0899 |
| (Nu-Nux)/Nus ... | (REAL : IMAGINARY) | | | | |
| -2.00 :-.277E-12 | -2.00 :-.332E-12 | -2.00 :-.387E-12 | -2.00 :-.442E-12 | -2.00 :-.497E-12 | |
| -2.00 :-.260E-12 | -2.00 :-.312E-12 | -2.00 :-.364E-12 | -2.00 :-.416E-12 | -2.00 :-.467E-12 | |
| -2.00 :0.219E-12 | -2.00 :0.261E-12 | -2.00 :0.301E-12 | -2.00 :0.343E-12 | -2.00 :0.382E-12 | |
| -.189E-01 :-.115E-11 | 0.999 :-.341E-12 | 0.998 :-.393E-12 | 0.998 :-.444E-12 | 0.998 :-.494E-12 | |
| 0.139E-02 :-.247E-12 | 1.00 :-.466E-12 | 1.00 :-.541E-12 | 1.00 :-.615E-12 | 1.00 :-.689E-12 | |
| 1.00 :-.390E-12 | 1.00 :0.206E-12 | 1.00 :0.243E-12 | 1.00 :0.279E-12 | 1.00 :0.316E-12 | |
| 0.999 :-.287E-12 | -.226E-01 :-.138E-11 | -.264E-01 :-.161E-11 | -.302E-01 :-.184E-11 | -.340E-01 :-.207E-11 | |
| 1.00 :0.171E-12 | 0.166E-02 :-.297E-12 | 0.194E-02 :-.347E-12 | 0.222E-02 :-.395E-12 | 0.250E-02 :-.444E-12 | |
| -.999 :-.416E-12 | -.998 :-.504E-12 | -.998 :-.593E-12 | -.998 :-.683E-12 | -.998 :-.775E-12 | |
| -1.00 :-.304E-12 | -1.00 :-.366E-12 | -1.00 :-.427E-12 | -1.00 :-.489E-12 | -1.00 :-.550E-12 | |
| -1.00 :0.157E-12 | -1.00 :0.187E-12 | -1.00 :0.217E-12 | -1.00 :0.246E-12 | -1.00 :0.274E-12 | |
| -.124E-05 :-.474E-12 | -.149E-05 :-.569E-12 | -.173E-05 :-.663E-12 | -.198E-05 :-.758E-12 | -.223E-05 :-.853E-12 | |

| Current (mA) / | 0.0500 | 0.0550 | 0.0600 | 0.0650 | 0.0700 |
|----------------------|----------------------|----------------------|----------------------|----------------------|--------|
| Bunch length (cm) / | 2.5000 | 2.5000 | 2.5000 | 2.5000 | 2.5000 |
| Synchrotron tune / | 0.0899 | 0.0899 | 0.0899 | 0.0899 | 0.0899 |
| (Nu-Nux)/Nus ... | (REAL : IMAGINARY) | | | | |
| -2.00 :-.552E-12 | -2.00 :-.607E-12 | -2.00 :-.661E-12 | -2.00 :-.716E-12 | -2.00 :-.770E-12 | |
| -2.00 :-.519E-12 | -2.00 :-.571E-12 | -2.00 :-.622E-12 | -2.00 :-.674E-12 | -2.00 :-.725E-12 | |
| -2.00 :0.421E-12 | -2.00 :0.460E-12 | -2.00 :0.498E-12 | -2.00 :0.535E-12 | -2.00 :0.571E-12 | |
| 0.998 :-.542E-12 | 0.997 :-.589E-12 | 0.997 :-.635E-12 | 0.997 :-.679E-12 | 0.996 :-.721E-12 | |
| 1.00 :-.762E-12 | 1.00 :-.835E-12 | 1.00 :-.907E-12 | 1.00 :-.979E-12 | 1.00 :-.105E-11 | |
| 1.00 :0.353E-12 | 1.00 :0.391E-12 | 1.00 :0.431E-12 | 1.00 :0.470E-12 | 1.00 :0.509E-12 | |
| -.377E-01 :-.229E-11 | -.415E-01 :-.252E-11 | -.453E-01 :-.275E-11 | -.491E-01 :-.298E-11 | -.529E-01 :-.321E-11 | |
| 0.277E-02 :-.495E-12 | 0.305E-02 :-.543E-12 | 0.333E-02 :-.595E-12 | 0.361E-02 :-.644E-12 | 0.388E-02 :-.693E-12 | |
| -.997 :-.868E-12 | -.997 :-.963E-12 | -.997 :-.106E-11 | -.996 :-.116E-11 | -.996 :-.126E-11 | |

| | | | | | | | |
|-------------------|---|------------------------|------------------------|------------------------|------------------------|------------------------|--|
| | | | | 2 | | | |
| | | -1.00 :- 612E-12 | -1.00 :- 673E-12 | -1.00 :- 735E-12 | -1.00 :- 796E-12 | -1.00 :- 857E-12 | |
| | | -1.00 :- 0.302E-12 | -1.00 :- 0.329E-12 | -1.00 :- 0.355E-12 | -1.00 :- 0.381E-12 | -1.00 :- 0.407E-12 | |
| | | - .248E-05 :- .948E-12 | - .272E-05 :- .104E-11 | - .297E-05 :- .114E-11 | - .322E-05 :- .123E-11 | - .347E-05 :- .133E-11 | |
| Current (mA) | / | 0.0750 | 0.0800 | 0.0850 | 0.0900 | 0.0950 | |
| Bunch length (cm) | / | 2.5000 | 2.5000 | 2.5000 | 2.5000 | 2.5000 | |
| Synchrotron tune | / | 0.0899 | 0.0899 | 0.0899 | 0.0899 | 0.0899 | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | |
| | | -2.00 :- .825E-12 | -2.00 :- .879E-12 | -2.00 :- .934E-12 | -2.00 :- .988E-12 | -2.00 :- .104E-11 | |
| | | -2.00 :- .776E-12 | -2.00 :- .826E-12 | -2.00 :- .877E-12 | -2.00 :- .928E-12 | -2.00 :- .979E-12 | |
| | | -2.00 :- 0.608E-12 | -2.00 :- 0.642E-12 | -2.00 :- 0.676E-12 | -2.00 :- 0.710E-12 | -2.00 :- 0.743E-12 | |
| | | 0.996 :- .762E-12 | 0.996 :- .801E-12 | 0.996 :- .839E-12 | 0.995 :- .875E-12 | 0.995 :- .909E-12 | |
| | | 1.00 :- .112E-11 | 1.00 :- .119E-11 | 1.00 :- .126E-11 | 1.00 :- .133E-11 | 1.00 :- .140E-11 | |
| | | 1.00 :- 0.550E-12 | 1.00 :- 0.590E-12 | 1.00 :- 0.630E-12 | 1.00 :- 0.672E-12 | 1.00 :- 0.714E-12 | |
| | | - .566E-01 :- .343E-11 | - .604E-01 :- .366E-11 | - .642E-01 :- .388E-11 | - .680E-01 :- .411E-11 | - .718E-01 :- .433E-11 | |
| | | 0.416E-02 :- .744E-12 | 0.444E-02 :- .794E-12 | 0.472E-02 :- .844E-12 | 0.500E-02 :- .894E-12 | 0.528E-02 :- .945E-12 | |
| | | - .996 :- .136E-11 | - .996 :- .147E-11 | - .995 :- .157E-11 | - .995 :- .168E-11 | - .995 :- .179E-11 | |
| | | -1.00 :- .918E-12 | -1.00 :- .978E-12 | -1.00 :- .104E-11 | -1.00 :- .110E-11 | -1.00 :- .116E-11 | |
| | | -1.00 :- 0.431E-12 | -1.00 :- 0.455E-12 | -1.00 :- 0.478E-12 | -1.00 :- 0.501E-12 | -1.00 :- 0.522E-12 | |
| | | - .371E-05 :- .142E-11 | - .396E-05 :- .152E-11 | - .421E-05 :- .161E-11 | - .445E-05 :- .171E-11 | - .470E-05 :- .180E-11 | |
| Current (mA) | / | 0.1000 | 0.1050 | 0.1100 | 0.1150 | 0.1200 | |
| Bunch length (cm) | / | 2.5000 | 2.5000 | 2.5000 | 2.5000 | 2.5000 | |
| Synchrotron tune | / | 0.0899 | 0.0899 | 0.0899 | 0.0899 | 0.0899 | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | |
| | | -2.00 :- .110E-11 | -2.00 :- .115E-11 | -2.00 :- .120E-11 | -2.00 :- .126E-11 | -1.99 :- .131E-11 | |
| | | -2.00 :- .103E-11 | -2.00 :- .108E-11 | -2.00 :- .113E-11 | -2.00 :- .118E-11 | -2.00 :- .123E-11 | |
| | | -2.00 :- 0.775E-12 | -2.00 :- 0.806E-12 | -2.00 :- 0.837E-12 | -2.00 :- 0.867E-12 | -2.00 :- 0.896E-12 | |
| | | 0.995 :- .942E-12 | 0.994 :- .972E-12 | 0.994 :- .100E-11 | 0.994 :- .103E-11 | 0.993 :- .105E-11 | |
| | | 1.00 :- .147E-11 | 1.00 :- .154E-11 | 1.01 :- .161E-11 | 1.01 :- .168E-11 | 1.01 :- .175E-11 | |
| | | 1.00 :- 0.756E-12 | 1.00 :- 0.797E-12 | 1.00 :- 0.842E-12 | 1.00 :- 0.890E-12 | 1.00 :- 0.929E-12 | |
| | | - .756E-01 :- .456E-11 | - .794E-01 :- .478E-11 | - .832E-01 :- .501E-11 | - .870E-01 :- .523E-11 | - .908E-01 :- .545E-11 | |
| | | 0.555E-02 :- .995E-12 | 0.583E-02 :- .104E-11 | 0.611E-02 :- .110E-11 | 0.639E-02 :- .115E-11 | 0.667E-02 :- .120E-11 | |
| | | - .994 :- .190E-11 | - .994 :- .202E-11 | - .994 :- .213E-11 | - .994 :- .225E-11 | - .993 :- .237E-11 | |
| | | -1.00 :- .122E-11 | -1.00 :- .127E-11 | -1.00 :- .133E-11 | -1.00 :- .139E-11 | -1.00 :- .144E-11 | |
| | | -1.00 :- 0.543E-12 | -1.00 :- 0.564E-12 | -1.00 :- 0.583E-12 | -1.00 :- 0.601E-12 | -1.00 :- 0.619E-12 | |
| | | - .495E-05 :- .190E-11 | - .520E-05 :- .199E-11 | - .544E-05 :- .209E-11 | - .569E-05 :- .218E-11 | - .594E-05 :- .227E-11 | |
| Current (mA) | / | 0.1250 | 0.1300 | 0.1350 | 0.1400 | 0.1450 | |
| Bunch length (cm) | / | 2.5000 | 2.5000 | 2.5000 | 2.5000 | 2.5000 | |
| Synchrotron tune | / | 0.0899 | 0.0899 | 0.0899 | 0.0899 | 0.0899 | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | |
| | | -1.99 :- .137E-11 | -1.99 :- .142E-11 | -1.99 :- .147E-11 | -1.99 :- .153E-11 | -1.99 :- .158E-11 | |
| | | -2.00 :- .128E-11 | -2.00 :- .132E-11 | -2.00 :- .137E-11 | -2.00 :- .142E-11 | -2.00 :- .147E-11 | |
| | | -2.00 :- 0.924E-12 | -2.00 :- 0.951E-12 | -2.00 :- 0.978E-12 | -2.00 :- 0.100E-11 | -2.00 :- 0.103E-11 | |
| | | 0.993 :- .108E-11 | 0.993 :- .110E-11 | 0.992 :- .112E-11 | 0.992 :- .114E-11 | 0.992 :- .115E-11 | |
| | | 1.01 :- .182E-11 | 1.01 :- .189E-11 | 1.01 :- .196E-11 | 1.01 :- .203E-11 | 1.01 :- .210E-11 | |
| | | 1.00 :- 0.972E-12 | 1.00 :- 0.102E-11 | 1.00 :- 0.106E-11 | 1.00 :- 0.110E-11 | 1.00 :- 0.115E-11 | |
| | | - .946E-01 :- .567E-11 | - .984E-01 :- .589E-11 | - .102 :- .611E-11 | - .106 :- .633E-11 | - .110 :- .655E-11 | |
| | | 0.695E-02 :- .125E-11 | 0.723E-02 :- .130E-11 | 0.751E-02 :- .135E-11 | 0.779E-02 :- .140E-11 | 0.806E-02 :- .145E-11 | |
| | | - .993 :- .250E-11 | - .993 :- .262E-11 | - .992 :- .275E-11 | - .992 :- .288E-11 | - .992 :- .302E-11 | |

| | | | | | | | |
|-------------------|---|-----------------------|-----------------------|-----------------------|-----------------------|-----------------------|--|
| | | | | 2 | | | |
| | | -1.00 :- 150E-11 | -1.00 :- 155E-11 | -1.00 :- 160E-11 | -1.00 :- 166E-11 | -1.00 :- 171E-11 | |
| | | -1.00 :0. 636E-12 | -1.00 :0. 652E-12 | -1.00 :0. 667E-12 | -1.00 :0. 681E-12 | -1.00 :0. 694E-12 | |
| | | -. 618E-05:-. 237E-11 | -. 643E-05:-. 246E-11 | -. 668E-05:-. 256E-11 | -. 692E-05:-. 265E-11 | -. 717E-05:-. 275E-11 | |
| Current (mA) | / | 0.1500 | 0.1550 | 0.1600 | 0.1650 | 0.1700 | |
| Bunch length (cm) | / | 2.5000 | 2.5000 | 2.5000 | 2.5000 | 2.5000 | |
| Synchrotron tune | / | 0.0899 | 0.0899 | 0.0899 | 0.0899 | 0.0899 | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | |
| | | -1.99 :- 164E-11 | -1.99 :- 169E-11 | -1.99 :- 174E-11 | -1.99 :- 180E-11 | -1.99 :- 185E-11 | |
| | | -2.00 :- 152E-11 | -2.00 :- 156E-11 | -2.00 :- 161E-11 | -2.00 :- 166E-11 | -2.00 :- 171E-11 | |
| | | -2.00 :0. 105E-11 | -2.00 :0. 108E-11 | -2.00 :0. 110E-11 | -2.00 :0. 112E-11 | -2.00 :0. 114E-11 | |
| | | 0.991 :- 117E-11 | 0.991 :- 118E-11 | 0.991 :- 119E-11 | 0.990 :- 120E-11 | 0.990 :- 120E-11 | |
| | | 1.01 :- 217E-11 | 1.01 :- 223E-11 | 1.01 :- 230E-11 | 1.01 :- 237E-11 | 1.01 :- 244E-11 | |
| | | 1.00 :0. 120E-11 | 1.00 :0. 124E-11 | 1.00 :0. 129E-11 | 1.00 :0. 134E-11 | 1.00 :0. 138E-11 | |
| | | -. 114 :- 676E-11 | -. 118 :- 698E-11 | -. 121 :- 719E-11 | -. 125 :- 741E-11 | -. 129 :- 762E-11 | |
| | | 0.834E-02:-. 150E-11 | 0.862E-02:-. 155E-11 | 0.890E-02:-. 160E-11 | 0.918E-02:-. 165E-11 | 0.946E-02:-. 170E-11 | |
| | | -. 991 :- 316E-11 | -. 991 :- 330E-11 | -. 991 :- 344E-11 | -. 990 :- 358E-11 | -. 990 :- 373E-11 | |
| | | -1.01 :- 176E-11 | -1.01 :- 180E-11 | -1.01 :- 185E-11 | -1.01 :- 190E-11 | -1.01 :- 194E-11 | |
| | | -1.00 :0. 706E-12 | -1.00 :0. 717E-12 | -1.00 :0. 727E-12 | -1.00 :0. 736E-12 | -1.00 :0. 744E-12 | |
| | | -. 742E-05:-. 284E-11 | -. 766E-05:-. 294E-11 | -. 791E-05:-. 303E-11 | -. 815E-05:-. 313E-11 | -. 840E-05:-. 322E-11 | |
| Current (mA) | / | 0.1750 | 0.1800 | 0.1850 | 0.1900 | 0.1950 | |
| Bunch length (cm) | / | 2.5000 | 2.5000 | 2.5000 | 2.5000 | 2.5000 | |
| Synchrotron tune | / | 0.0899 | 0.0899 | 0.0899 | 0.0899 | 0.0899 | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | |
| | | -1.99 :- 190E-11 | -1.99 :- 196E-11 | -1.99 :- 201E-11 | -1.99 :- 207E-11 | -1.99 :- 212E-11 | |
| | | -2.00 :- 175E-11 | -2.00 :- 180E-11 | -2.00 :- 185E-11 | -2.00 :- 189E-11 | -2.00 :- 194E-11 | |
| | | -2.00 :0. 116E-11 | -2.00 :0. 118E-11 | -2.00 :0. 120E-11 | -2.00 :0. 122E-11 | -2.00 :0. 124E-11 | |
| | | 0.990 :- 121E-11 | 0.989 :- 121E-11 | 0.989 :- 121E-11 | 0.988 :- 121E-11 | 0.988 :- 120E-11 | |
| | | 1.01 :- 251E-11 | 1.01 :- 258E-11 | 1.01 :- 265E-11 | 1.01 :- 272E-11 | 1.01 :- 279E-11 | |
| | | 1.00 :0. 143E-11 | 1.00 :0. 148E-11 | 1.00 :0. 153E-11 | 1.00 :0. 157E-11 | 1.00 :0. 162E-11 | |
| | | -. 133 :- 783E-11 | -. 137 :- 804E-11 | -. 141 :- 825E-11 | -. 144 :- 846E-11 | -. 148 :- 867E-11 | |
| | | 0.974E-02:-. 175E-11 | 0.100E-01:-. 181E-11 | 0.103E-01:-. 186E-11 | 0.106E-01:-. 191E-11 | 0.109E-01:-. 196E-11 | |
| | | -. 990 :- 389E-11 | -. 989 :- 404E-11 | -. 989 :- 420E-11 | -. 989 :- 436E-11 | -. 988 :- 453E-11 | |
| | | -1.01 :- 198E-11 | -1.01 :- 202E-11 | -1.01 :- 206E-11 | -1.01 :- 209E-11 | -1.01 :- 213E-11 | |
| | | -1.00 :0. 751E-12 | -1.00 :0. 756E-12 | -1.00 :0. 760E-12 | -1.00 :0. 763E-12 | -1.00 :0. 764E-12 | |
| | | -. 865E-05:-. 332E-11 | -. 889E-05:-. 341E-11 | -. 914E-05:-. 351E-11 | -. 939E-05:-. 360E-11 | -. 963E-05:-. 370E-11 | |
| Current (mA) | / | 0.2000 | 0.2050 | 0.2100 | 0.2150 | 0.2200 | |
| Bunch length (cm) | / | 2.5000 | 2.5000 | 2.5000 | 2.5000 | 2.5000 | |
| Synchrotron tune | / | 0.0899 | 0.0899 | 0.0899 | 0.0899 | 0.0899 | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | |
| | | -1.99 :- 217E-11 | -1.99 :- 223E-11 | -1.99 :- 228E-11 | -1.99 :- 233E-11 | -1.99 :- 239E-11 | |
| | | -2.00 :- 198E-11 | -2.00 :- 203E-11 | -2.00 :- 207E-11 | -2.00 :- 212E-11 | -2.00 :- 216E-11 | |
| | | -2.00 :0. 125E-11 | -2.00 :0. 127E-11 | -2.00 :0. 128E-11 | -2.00 :0. 130E-11 | -2.00 :0. 131E-11 | |
| | | 0.988 :- 120E-11 | 0.987 :- 119E-11 | 0.987 :- 118E-11 | 0.987 :- 116E-11 | 0.986 :- 115E-11 | |
| | | 1.01 :- 286E-11 | 1.01 :- 293E-11 | 1.01 :- 300E-11 | 1.01 :- 308E-11 | 1.01 :- 315E-11 | |
| | | 1.00 :0. 167E-11 | 1.00 :0. 172E-11 | 1.00 :0. 177E-11 | 1.00 :0. 182E-11 | 1.00 :0. 187E-11 | |
| | | -. 152 :- 887E-11 | -. 156 :- 908E-11 | -. 160 :- 928E-11 | -. 164 :- 948E-11 | -. 168 :- 968E-11 | |
| | | 0.111E-01:-. 201E-11 | 0.114E-01:-. 206E-11 | 0.117E-01:-. 211E-11 | 0.120E-01:-. 216E-11 | 0.123E-01:-. 222E-11 | |
| | | -. 988 :- 470E-11 | -. 987 :- 487E-11 | -. 987 :- 505E-11 | -. 987 :- 523E-11 | -. 986 :- 542E-11 | |

| | | | | | | | | | | |
|-------------------|--------------------|-------------|------------|-------------|------------|-------------|------------|-------------|------------|-------------|
| | | | | 2 | | | | | | |
| | -1.01 | :-. 216E-11 | -1.01 | :-. 219E-11 | -1.01 | :-. 222E-11 | -1.01 | :-. 224E-11 | -1.01 | :-. 226E-11 |
| | -1.00 | :0. 764E-12 | -1.00 | :0. 763E-12 | -1.00 | :0. 760E-12 | -1.00 | :0. 756E-12 | -1.00 | :0. 750E-12 |
| | -. 988E-05 | :-. 379E-11 | -. 101E-04 | :-. 389E-11 | -. 104E-04 | :-. 398E-11 | -. 106E-04 | :-. 408E-11 | -. 109E-04 | :-. 417E-11 |
| Current (mA) | / | 0. 2250 | 0. 2300 | 0. 2350 | 0. 2400 | 0. 2450 | | | | |
| Bunch length (cm) | / | 2. 5000 | 2. 5000 | 2. 5000 | 2. 5000 | 2. 5000 | | | | |
| Synchrotron tune | / | 0. 0899 | 0. 0899 | 0. 0899 | 0. 0899 | 0. 0899 | | | | |
| (Nu-Nux)/Nus ... | (REAL : IMAGINARY) | | | | | | | | | |
| | -1.99 | :-. 244E-11 | -1.99 | :-. 250E-11 | -1.99 | :-. 255E-11 | -1.99 | :-. 260E-11 | -1.99 | :-. 266E-11 |
| | -2.00 | :-. 220E-11 | -2.00 | :-. 225E-11 | -2.00 | :-. 229E-11 | -2.00 | :-. 233E-11 | -2.00 | :-. 237E-11 |
| | -2.00 | :0. 132E-11 | -2.00 | :0. 133E-11 | -2.00 | :0. 134E-11 | -2.00 | :0. 135E-11 | -2.00 | :0. 136E-11 |
| | 0.986 | :-. 113E-11 | 0.985 | :-. 111E-11 | 0.985 | :-. 109E-11 | 0.985 | :-. 107E-11 | 0.984 | :-. 104E-11 |
| | 1.01 | :-. 322E-11 | 1.01 | :-. 329E-11 | 1.01 | :-. 336E-11 | 1.01 | :-. 344E-11 | 1.01 | :-. 351E-11 |
| | 1.00 | :0. 192E-11 | 1.00 | :0. 197E-11 | 1.00 | :0. 202E-11 | 1.00 | :0. 207E-11 | 1.00 | :0. 212E-11 |
| | -. 172 | :-. 988E-11 | -. 175 | :-. 101E-10 | -. 179 | :-. 103E-10 | -. 183 | :-. 105E-10 | -. 187 | :-. 107E-10 |
| | 0.126E-01 | :-. 227E-11 | 0.128E-01 | :-. 232E-11 | 0.131E-01 | :-. 237E-11 | 0.134E-01 | :-. 243E-11 | 0.137E-01 | :-. 248E-11 |
| | -. 986 | :-. 561E-11 | -. 986 | :-. 580E-11 | -. 985 | :-. 600E-11 | -. 985 | :-. 620E-11 | -. 984 | :-. 641E-11 |
| | -1.01 | :-. 228E-11 | -1.01 | :-. 230E-11 | -1.01 | :-. 231E-11 | -1.01 | :-. 232E-11 | -1.01 | :-. 233E-11 |
| | -1.00 | :0. 742E-12 | -1.00 | :0. 733E-12 | -1.00 | :0. 722E-12 | -1.00 | :0. 710E-12 | -1.00 | :0. 695E-12 |
| | -. 111E-04 | :-. 427E-11 | -. 114E-04 | :-. 436E-11 | -. 116E-04 | :-. 446E-11 | -. 118E-04 | :-. 455E-11 | -. 121E-04 | :-. 465E-11 |
| Current (mA) | / | 0. 2500 | 0. 2550 | 0. 2600 | 0. 2650 | 0. 2700 | | | | |
| Bunch length (cm) | / | 2. 5000 | 2. 5000 | 2. 5000 | 2. 5000 | 2. 5000 | | | | |
| Synchrotron tune | / | 0. 0899 | 0. 0899 | 0. 0899 | 0. 0899 | 0. 0899 | | | | |
| (Nu-Nux)/Nus ... | (REAL : IMAGINARY) | | | | | | | | | |
| | -1.99 | :-. 271E-11 | -1.99 | :-. 277E-11 | -1.99 | :-. 282E-11 | -1.99 | :-. 287E-11 | -1.99 | :-. 293E-11 |
| | -2.00 | :-. 242E-11 | -2.00 | :-. 246E-11 | -2.00 | :-. 250E-11 | -2.00 | :-. 254E-11 | -2.00 | :-. 258E-11 |
| | -2.00 | :0. 137E-11 | -2.00 | :0. 137E-11 | -2.00 | :0. 138E-11 | -2.00 | :0. 139E-11 | -2.00 | :0. 139E-11 |
| | 0.984 | :-. 101E-11 | 0.983 | :-. 980E-12 | 0.983 | :-. 947E-12 | 0.982 | :-. 912E-12 | 0.982 | :-. 875E-12 |
| | 1.01 | :-. 358E-11 | 1.01 | :-. 366E-11 | 1.01 | :-. 373E-11 | 1.01 | :-. 381E-11 | 1.01 | :-. 388E-11 |
| | 1.00 | :0. 217E-11 | 1.00 | :0. 222E-11 | 1.00 | :0. 227E-11 | 1.00 | :0. 233E-11 | 1.00 | :0. 238E-11 |
| | -. 191 | :-. 108E-10 | -. 195 | :-. 110E-10 | -. 199 | :-. 112E-10 | -. 203 | :-. 114E-10 | -. 207 | :-. 116E-10 |
| | 0.140E-01 | :-. 253E-11 | 0.142E-01 | :-. 258E-11 | 0.145E-01 | :-. 263E-11 | 0.148E-01 | :-. 269E-11 | 0.151E-01 | :-. 274E-11 |
| | -. 984 | :-. 662E-11 | -. 983 | :-. 684E-11 | -. 983 | :-. 706E-11 | -. 983 | :-. 729E-11 | -. 982 | :-. 752E-11 |
| | -1.01 | :-. 233E-11 | -1.01 | :-. 233E-11 | -1.01 | :-. 233E-11 | -1.01 | :-. 232E-11 | -1.01 | :-. 231E-11 |
| | -1.00 | :0. 678E-12 | -1.00 | :0. 660E-12 | -. 999 | :0. 639E-12 | -. 999 | :0. 616E-12 | -. 999 | :0. 591E-12 |
| | -. 123E-04 | :-. 474E-11 | -. 126E-04 | :-. 483E-11 | -. 128E-04 | :-. 493E-11 | -. 131E-04 | :-. 502E-11 | -. 133E-04 | :-. 512E-11 |
| Current (mA) | / | 0. 2750 | 0. 2800 | 0. 2850 | 0. 2900 | 0. 2950 | | | | |
| Bunch length (cm) | / | 2. 5000 | 2. 5000 | 2. 5000 | 2. 5000 | 2. 5000 | | | | |
| Synchrotron tune | / | 0. 0899 | 0. 0899 | 0. 0899 | 0. 0899 | 0. 0899 | | | | |
| (Nu-Nux)/Nus ... | (REAL : IMAGINARY) | | | | | | | | | |
| | -1.99 | :-. 298E-11 | -1.99 | :-. 304E-11 | -1.99 | :-. 309E-11 | -1.99 | :-. 314E-11 | -1.99 | :-. 320E-11 |
| | -2.00 | :-. 262E-11 | -2.00 | :-. 266E-11 | -2.00 | :-. 270E-11 | -2.00 | :-. 273E-11 | -2.00 | :-. 277E-11 |
| | -2.00 | :0. 139E-11 | -2.00 | :0. 140E-11 | -2.00 | :0. 140E-11 | -2.00 | :0. 140E-11 | -2.00 | :0. 140E-11 |
| | 0.982 | :-. 835E-12 | 0.981 | :-. 793E-12 | 0.981 | :-. 749E-12 | 0.980 | :-. 702E-12 | 0.980 | :-. 653E-12 |
| | 1.01 | :-. 396E-11 | 1.01 | :-. 403E-11 | 1.01 | :-. 411E-11 | 1.01 | :-. 419E-11 | 1.01 | :-. 426E-11 |
| | 1.00 | :0. 243E-11 | 1.00 | :0. 248E-11 | 1.00 | :0. 254E-11 | 1.00 | :0. 259E-11 | 1.00 | :0. 264E-11 |
| | -. 211 | :-. 118E-10 | -. 215 | :-. 119E-10 | -. 219 | :-. 121E-10 | -. 223 | :-. 123E-10 | -. 227 | :-. 125E-10 |
| | 0.154E-01 | :-. 279E-11 | 0.157E-01 | :-. 285E-11 | 0.159E-01 | :-. 290E-11 | 0.162E-01 | :-. 295E-11 | 0.165E-01 | :-. 300E-11 |
| | -. 982 | :-. 776E-11 | -. 981 | :-. 800E-11 | -. 981 | :-. 825E-11 | -. 980 | :-. 851E-11 | -. 980 | :-. 877E-11 |

| | | | | | | | | | | |
|-------------------|------------|--------------------|------------|-------------|------------|-------------|------------|-------------|------------|-------------|
| | | | | 2 | | | | | | |
| | -1.01 | :-. 230E-11 | -1.01 | :-. 228E-11 | -1.01 | :-. 226E-11 | -1.01 | :-. 223E-11 | -1.01 | :-. 219E-11 |
| | -. 999 | :0. 564E-12 | -. 999 | :0. 534E-12 | -. 999 | :0. 502E-12 | -. 999 | :0. 467E-12 | -. 999 | :0. 430E-12 |
| | -. 136E-04 | :-. 521E-11 | -. 138E-04 | :-. 531E-11 | -. 141E-04 | :-. 540E-11 | -. 143E-04 | :-. 550E-11 | -. 145E-04 | :-. 559E-11 |
| Current (mA) | / | 0. 3000 | 0. 3050 | 0. 3100 | 0. 3150 | 0. 3200 | | | | |
| Bunch length (cm) | / | 2. 5000 | 2. 5000 | 2. 5000 | 2. 5000 | 2. 5000 | | | | |
| Synchrotron tune | / | 0. 0899 | 0. 0899 | 0. 0899 | 0. 0899 | 0. 0899 | | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | |
| | -1.99 | :-. 325E-11 | -1.99 | :-. 331E-11 | -1.99 | :-. 336E-11 | -1.99 | :0. 234E-11 | -1.99 | :0. 453E-11 |
| | -2.00 | :-. 281E-11 | -2.00 | :-. 285E-11 | -2.00 | :-. 289E-11 | -2.00 | :-. 948E-10 | -2.00 | :-. 103E-09 |
| | -2.00 | :0. 140E-11 | -2.00 | :0. 140E-11 | -2.00 | :0. 140E-11 | -2.00 | :0. 124E-10 | -2.00 | :0. 171E-10 |
| | 0.979 | :-. 602E-12 | 0.979 | :-. 548E-12 | 0.978 | :-. 492E-12 | 0.978 | :0. 656E-10 | 0.978 | :0. 716E-10 |
| | 1.01 | :-. 434E-11 | 1.01 | :-. 442E-11 | 1.01 | :-. 450E-11 | 1.01 | :-. 733E-11 | 1.01 | :-. 117E-10 |
| | 1.00 | :0. 270E-11 | 1.00 | :0. 275E-11 | 1.00 | :0. 280E-11 | 1.00 | :0. 286E-11 | 1.00 | :0. 291E-11 |
| | -. 231 | :-. 126E-10 | -. 235 | :-. 128E-10 | -. 239 | :-. 130E-10 | -. 243 | :-. 131E-10 | -. 247 | :-. 133E-10 |
| | 0.168E-01 | :-. 306E-11 | 0.171E-01 | :-. 311E-11 | 0.174E-01 | :-. 317E-11 | 0.176E-01 | :-. 322E-11 | 0.179E-01 | :-. 327E-11 |
| | -. 979 | :-. 903E-11 | -. 979 | :-. 930E-11 | -. 978 | :-. 958E-11 | -. 978 | :-. 987E-11 | -. 977 | :-. 102E-10 |
| | -1.01 | :-. 216E-11 | -1.01 | :-. 211E-11 | -1.01 | :-. 207E-11 | -1.01 | :-. 201E-11 | -1.01 | :-. 196E-11 |
| | -. 999 | :0. 390E-12 | -. 999 | :0. 346E-12 | -. 999 | :0. 301E-12 | -. 999 | :0. 251E-12 | -. 999 | :0. 199E-12 |
| | -. 148E-04 | :-. 569E-11 | -. 150E-04 | :-. 578E-11 | -. 153E-04 | :-. 588E-11 | -. 155E-04 | :-. 597E-11 | -. 158E-04 | :-. 607E-11 |
| Current (mA) | / | 0. 3250 | 0. 3300 | 0. 3350 | 0. 3400 | 0. 3450 | | | | |
| Bunch length (cm) | / | 2. 5000 | 2. 5000 | 2. 5000 | 2. 5000 | 2. 5000 | | | | |
| Synchrotron tune | / | 0. 0899 | 0. 0899 | 0. 0899 | 0. 0899 | 0. 0899 | | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | |
| | -1.99 | :0. 651E-11 | -1.99 | :-. 357E-11 | -1.98 | :-. 363E-11 | -1.98 | :-. 368E-11 | -1.98 | :-. 374E-11 |
| | -2.00 | :-. 110E-09 | -2.00 | :-. 304E-11 | -2.00 | :-. 307E-11 | -2.00 | :-. 311E-11 | -2.00 | :-. 314E-11 |
| | -2.00 | :0. 147E-10 | -2.00 | :0. 138E-11 | -2.00 | :0. 138E-11 | -2.00 | :0. 137E-11 | -2.00 | :0. 136E-11 |
| | 0.977 | :0. 722E-10 | 0.977 | :-. 244E-12 | 0.976 | :-. 177E-12 | 0.976 | :-. 106E-12 | 0.975 | :-. 337E-13 |
| | 1.01 | :-. 543E-11 | 1.01 | :-. 482E-11 | 1.01 | :-. 490E-11 | 1.01 | :-. 498E-11 | 1.01 | :-. 506E-11 |
| | 1.00 | :0. 297E-11 | 1.00 | :0. 302E-11 | 1.00 | :0. 308E-11 | 1.00 | :0. 314E-11 | 1.00 | :0. 318E-11 |
| | -. 251 | :-. 134E-10 | 0.185E-01 | :-. 338E-11 | 0.188E-01 | :-. 344E-11 | 0.191E-01 | :-. 349E-11 | 0.193E-01 | :-. 354E-11 |
| | 0.182E-01 | :-. 333E-11 | -. 255 | :-. 136E-10 | -. 259 | :-. 138E-10 | -. 263 | :-. 139E-10 | -. 267 | :-. 140E-10 |
| | -. 977 | :-. 105E-10 | -. 976 | :-. 108E-10 | -. 976 | :-. 111E-10 | -. 975 | :-. 114E-10 | -. 975 | :-. 117E-10 |
| | -1.01 | :-. 189E-11 | -1.01 | :-. 182E-11 | -1.01 | :-. 174E-11 | -1.01 | :-. 166E-11 | -1.01 | :-. 157E-11 |
| | -. 999 | :0. 143E-12 | -. 999 | :0. 842E-13 | -. 999 | :0. 215E-13 | -. 999 | :-. 450E-13 | -. 999 | :-. 115E-12 |
| | -. 160E-04 | :-. 616E-11 | -. 163E-04 | :-. 626E-11 | -. 165E-04 | :-. 635E-11 | -. 167E-04 | :-. 645E-11 | -. 170E-04 | :-. 654E-11 |
| Current (mA) | / | 0. 3500 | 0. 3550 | 0. 3600 | 0. 3650 | 0. 3700 | | | | |
| Bunch length (cm) | / | 2. 5000 | 2. 5000 | 2. 5000 | 2. 5000 | 2. 5000 | | | | |
| Synchrotron tune | / | 0. 0899 | 0. 0899 | 0. 0899 | 0. 0899 | 0. 0899 | | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | |
| | -1.98 | :-. 379E-11 | -1.98 | :-. 384E-11 | -1.98 | :-. 390E-11 | -1.98 | :-. 395E-11 | -1.98 | :-. 401E-11 |
| | -2.00 | :-. 318E-11 | -2.00 | :-. 321E-11 | -2.00 | :-. 325E-11 | -2.00 | :-. 328E-11 | -2.00 | :-. 331E-11 |
| | -2.00 | :0. 135E-11 | -2.00 | :0. 134E-11 | -2.00 | :0. 133E-11 | -2.00 | :0. 132E-11 | -2.00 | :0. 131E-11 |
| | 0.975 | :0. 412E-13 | 0.974 | :0. 119E-12 | 0.974 | :0. 199E-12 | 0.973 | :0. 281E-12 | 0.973 | :0. 366E-12 |
| | 1.01 | :-. 514E-11 | 1.01 | :-. 523E-11 | 1.01 | :-. 531E-11 | 1.01 | :-. 540E-11 | 1.02 | :-. 548E-11 |
| | 1.00 | :0. 324E-11 | 1.00 | :0. 330E-11 | 1.00 | :0. 335E-11 | 1.00 | :0. 341E-11 | 1.00 | :0. 346E-11 |
| | 0.196E-01 | :-. 360E-11 | 0.199E-01 | :-. 365E-11 | 0.202E-01 | :-. 370E-11 | 0.205E-01 | :-. 376E-11 | 0.208E-01 | :-. 381E-11 |
| | -. 271 | :-. 142E-10 | -. 275 | :-. 143E-10 | -. 280 | :-. 145E-10 | -. 284 | :-. 146E-10 | -. 288 | :-. 147E-10 |
| | -. 974 | :-. 120E-10 | -. 973 | :-. 124E-10 | -. 973 | :-. 127E-10 | -. 972 | :-. 131E-10 | -. 972 | :-. 135E-10 |

| | | | | | | | | | | | |
|-------------------|---|--------------------|------------|-----------|------------|-----------|------------|-----------|------------|-----------|------------|
| | | | | 2 | | | | | | | |
| | | -1.01 | :-.148E-11 | -1.01 | :-.138E-11 | -1.01 | :-.127E-11 | -1.01 | :-.115E-11 | -1.01 | :-.103E-11 |
| | | -.999 | :-.189E-12 | -.999 | :-.268E-12 | -.999 | :-.350E-12 | -.999 | :-.437E-12 | -.999 | :-.529E-12 |
| | | -.172E-04 | :-.664E-11 | -.175E-04 | :-.673E-11 | -.177E-04 | :-.683E-11 | -.180E-04 | :-.692E-11 | -.182E-04 | :-.702E-11 |
| Current (mA) | / | 0.3750 | 0.3800 | 0.3850 | 0.3900 | 0.3950 | | | | | |
| Bunch length (cm) | / | 2.5000 | 2.5000 | 2.5000 | 2.5000 | 2.5000 | | | | | |
| Synchrotron tune | / | 0.0899 | 0.0899 | 0.0899 | 0.0899 | 0.0899 | | | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | | |
| | | -1.98 | :-.406E-11 | -1.98 | :-.412E-11 | -1.98 | :-.417E-11 | -1.98 | :-.423E-11 | -1.98 | :-.428E-11 |
| | | -2.00 | :-.335E-11 | -2.00 | :-.338E-11 | -2.00 | :-.341E-11 | -2.00 | :-.344E-11 | -2.00 | :-.348E-11 |
| | | -2.00 | :-.130E-11 | -2.00 | :-.129E-11 | -2.00 | :-.127E-11 | -2.00 | :-.126E-11 | -2.00 | :-.124E-11 |
| | | 0.972 | :-.453E-12 | 0.972 | :-.542E-12 | 0.971 | :-.634E-12 | 0.971 | :-.729E-12 | 0.970 | :-.826E-12 |
| | | 1.02 | :-.557E-11 | 1.02 | :-.565E-11 | 1.02 | :-.574E-11 | 1.02 | :-.583E-11 | 1.02 | :-.592E-11 |
| | | 1.00 | :-.352E-11 | 1.00 | :-.358E-11 | 1.00 | :-.363E-11 | 1.00 | :-.369E-11 | 1.00 | :-.374E-11 |
| | | 0.211E-01 | :-.387E-11 | 0.213E-01 | :-.393E-11 | 0.216E-01 | :-.398E-11 | 0.219E-01 | :-.404E-11 | 0.222E-01 | :-.409E-11 |
| | | -.292 | :-.148E-10 | -.296 | :-.150E-10 | -.300 | :-.151E-10 | -.305 | :-.152E-10 | -.309 | :-.153E-10 |
| | | -.971 | :-.138E-10 | -.970 | :-.142E-10 | -.970 | :-.146E-10 | -.969 | :-.150E-10 | -.968 | :-.154E-10 |
| | | -1.01 | :-.894E-12 | -1.01 | :-.755E-12 | -1.01 | :-.608E-12 | -1.01 | :-.453E-12 | -1.01 | :-.289E-12 |
| | | -.999 | :-.626E-12 | -.999 | :-.727E-12 | -.999 | :-.833E-12 | -.999 | :-.945E-12 | -.999 | :-.106E-11 |
| | | -.185E-04 | :-.711E-11 | -.187E-04 | :-.721E-11 | -.190E-04 | :-.730E-11 | -.192E-04 | :-.740E-11 | -.194E-04 | :-.749E-11 |
| Current (mA) | / | 0.4000 | 0.4050 | 0.4100 | 0.4150 | 0.4200 | | | | | |
| Bunch length (cm) | / | 2.5000 | 2.5000 | 2.5000 | 2.5000 | 2.5000 | | | | | |
| Synchrotron tune | / | 0.0899 | 0.0899 | 0.0899 | 0.0899 | 0.0899 | | | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | | |
| | | -1.98 | :-.434E-11 | -1.98 | :-.439E-11 | -1.98 | :-.445E-11 | -1.98 | :-.450E-11 | -1.98 | :-.455E-11 |
| | | -2.00 | :-.122E-11 | -2.00 | :-.121E-11 | -2.00 | :-.119E-11 | -2.00 | :-.117E-11 | -2.00 | :-.115E-11 |
| | | -2.00 | :-.351E-11 | -2.00 | :-.354E-11 | -2.00 | :-.357E-11 | -2.00 | :-.360E-11 | -2.00 | :-.362E-11 |
| | | 0.970 | :-.925E-12 | 0.969 | :-.103E-11 | 0.969 | :-.113E-11 | 0.968 | :-.124E-11 | 0.968 | :-.135E-11 |
| | | 1.02 | :-.600E-11 | 1.02 | :-.609E-11 | 1.02 | :-.618E-11 | 1.02 | :-.627E-11 | 1.02 | :-.636E-11 |
| | | 1.00 | :-.380E-11 | 1.00 | :-.386E-11 | 1.00 | :-.392E-11 | 1.00 | :-.398E-11 | 1.00 | :-.404E-11 |
| | | 0.225E-01 | :-.415E-11 | 0.228E-01 | :-.420E-11 | 0.231E-01 | :-.426E-11 | 0.234E-01 | :-.432E-11 | 0.236E-01 | :-.438E-11 |
| | | -.313 | :-.154E-10 | -.317 | :-.155E-10 | -.321 | :-.156E-10 | -.326 | :-.157E-10 | -.330 | :-.158E-10 |
| | | -.968 | :-.158E-10 | -.967 | :-.162E-10 | -.966 | :-.167E-10 | -.965 | :-.171E-10 | -.965 | :-.176E-10 |
| | | -1.01 | :-.116E-12 | -1.01 | :-.647E-13 | -1.01 | :-.255E-12 | -1.01 | :-.453E-12 | -1.01 | :-.662E-12 |
| | | -.999 | :-.118E-11 | -.999 | :-.131E-11 | -.999 | :-.145E-11 | -.999 | :-.159E-11 | -.999 | :-.173E-11 |
| | | -.197E-04 | :-.759E-11 | -.199E-04 | :-.768E-11 | -.202E-04 | :-.778E-11 | -.204E-04 | :-.787E-11 | -.207E-04 | :-.797E-11 |
| Current (mA) | / | 0.4250 | 0.4300 | 0.4350 | 0.4400 | 0.4450 | | | | | |
| Bunch length (cm) | / | 2.5000 | 2.5000 | 2.5000 | 2.5000 | 2.5000 | | | | | |
| Synchrotron tune | / | 0.0899 | 0.0899 | 0.0899 | 0.0899 | 0.0899 | | | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | | |
| | | -1.98 | :-.116E-10 | -1.98 | :-.265E-10 | -1.98 | :-.253E-11 | -1.98 | :-.478E-11 | -1.98 | :-.483E-11 |
| | | -2.00 | :-.166E-10 | -2.00 | :-.870E-12 | -2.00 | :-.211E-11 | -2.00 | :-.106E-11 | -2.00 | :-.377E-11 |
| | | -2.00 | :-.252E-10 | -2.00 | :-.278E-10 | -2.00 | :-.841E-11 | -2.00 | :-.375E-11 | -2.00 | :-.104E-11 |
| | | 0.967 | :-.214E-10 | 0.966 | :-.184E-10 | 0.966 | :-.115E-10 | 0.965 | :-.181E-11 | 0.965 | :-.193E-11 |
| | | 1.02 | :-.256E-10 | 1.02 | :-.259E-10 | 1.02 | :-.163E-10 | 1.02 | :-.673E-11 | 1.02 | :-.683E-11 |
| | | 1.00 | :-.143E-10 | 1.00 | :-.303E-10 | 1.00 | :-.174E-10 | 1.00 | :-.427E-11 | 1.00 | :-.432E-11 |
| | | 0.239E-01 | :-.145E-10 | 0.242E-01 | :-.220E-10 | 0.245E-01 | :-.253E-11 | 0.248E-01 | :-.460E-11 | 0.251E-01 | :-.466E-11 |
| | | -.334 | :-.490E-11 | -.339 | :-.728E-11 | -.343 | :-.219E-10 | -.347 | :-.160E-10 | -.352 | :-.161E-10 |
| | | -.964 | :-.180E-10 | -.963 | :-.185E-10 | -.962 | :-.190E-10 | -.961 | :-.195E-10 | -.961 | :-.200E-10 |

| | | | | | | | | | | | |
|-------------------|---|--------------------|------------|-----------|------------|-----------|------------|-----------|------------|-----------|------------|
| | | | | 2 | | | | | | | |
| | | -1.01 | :0.879E-12 | -1.01 | :0.111E-11 | -1.01 | :0.134E-11 | -1.01 | :0.159E-11 | -1.00 | :0.184E-11 |
| | | -.999 | :-.188E-11 | -.999 | :-.204E-11 | -.999 | :-.221E-11 | -.999 | :-.238E-11 | -.999 | :-.256E-11 |
| | | -.209E-04 | :-.806E-11 | -.211E-04 | :-.816E-11 | -.214E-04 | :-.825E-11 | -.216E-04 | :-.835E-11 | -.219E-04 | :-.844E-11 |
| Current (mA) | / | 0.4500 | 0.4550 | 0.4600 | 0.4650 | 0.4700 | | | | | |
| Bunch length (cm) | / | 2.5000 | 2.5000 | 2.5000 | 2.5000 | 2.5000 | | | | | |
| Synchrotron tune | / | 0.0899 | 0.0899 | 0.0899 | 0.0899 | 0.0899 | | | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | | |
| | | -1.98 | :-.489E-11 | -1.98 | :-.218E-11 | -1.98 | :-.750E-11 | -1.98 | :-.506E-11 | -1.98 | :-.511E-11 |
| | | -2.00 | :-.380E-11 | -2.00 | :0.112E-10 | -2.00 | :0.608E-11 | -2.00 | :-.388E-11 | -2.00 | :-.391E-11 |
| | | -2.00 | :0.102E-11 | -2.00 | :0.141E-11 | -2.00 | :0.111E-10 | -2.00 | :0.941E-12 | -2.00 | :0.913E-12 |
| | | 0.964 | :0.205E-11 | 0.964 | :-.160E-10 | 0.963 | :-.471E-11 | 0.963 | :0.244E-11 | 0.962 | :0.258E-11 |
| | | 1.02 | :-.692E-11 | 1.02 | :0.372E-11 | 1.02 | :-.327E-11 | 1.02 | :-.721E-11 | 1.02 | :-.731E-11 |
| | | 1.00 | :0.438E-11 | 1.00 | :0.511E-10 | 1.00 | :0.466E-10 | 1.00 | :0.456E-11 | 1.00 | :0.462E-11 |
| | | 0.254E-01 | :-.471E-11 | 0.257E-01 | :-.402E-10 | 0.260E-01 | :-.697E-10 | 0.262E-01 | :-.488E-11 | 0.265E-01 | :-.494E-11 |
| | | -.356 | :-.161E-10 | -.361 | :0.727E-11 | -.365 | :0.271E-10 | -.369 | :-.162E-10 | -.374 | :-.162E-10 |
| | | -.960 | :-.205E-10 | -.959 | :-.210E-10 | -.958 | :-.216E-10 | -.957 | :-.221E-10 | -.956 | :-.227E-10 |
| | | -1.00 | :0.211E-11 | -1.00 | :0.238E-11 | -1.00 | :0.267E-11 | -1.00 | :0.296E-11 | -1.00 | :0.326E-11 |
| | | -.999 | :-.274E-11 | -.999 | :-.293E-11 | -.999 | :-.313E-11 | -.998 | :-.333E-11 | -.998 | :-.354E-11 |
| | | -.221E-04 | :-.854E-11 | -.224E-04 | :-.863E-11 | -.226E-04 | :-.873E-11 | -.229E-04 | :-.882E-11 | -.231E-04 | :-.892E-11 |
| Current (mA) | / | 0.4750 | 0.4800 | 0.4850 | 0.4900 | 0.4950 | | | | | |
| Bunch length (cm) | / | 2.5000 | 2.5000 | 2.5000 | 2.5000 | 2.5000 | | | | | |
| Synchrotron tune | / | 0.0899 | 0.0899 | 0.0899 | 0.0899 | 0.0899 | | | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | | |
| | | -1.98 | :-.213E-10 | -1.98 | :-.522E-11 | -1.98 | :-.528E-11 | -1.98 | :-.533E-11 | -1.98 | :-.903E-11 |
| | | -2.00 | :0.677E-10 | -2.00 | :-.396E-11 | -2.00 | :0.832E-12 | -2.00 | :0.800E-12 | -2.00 | :-.303E-10 |
| | | -2.00 | :-.967E-11 | -2.00 | :0.859E-12 | -2.00 | :-.399E-11 | -2.00 | :-.401E-11 | -2.00 | :-.692E-10 |
| | | 0.962 | :-.420E-11 | 0.961 | :0.285E-11 | 0.960 | :0.299E-11 | 0.960 | :0.314E-11 | 0.959 | :0.492E-11 |
| | | 1.02 | :-.270E-10 | 1.02 | :-.751E-11 | 1.02 | :-.761E-11 | 1.02 | :-.771E-11 | 1.02 | :0.119E-10 |
| | | 1.00 | :-.523E-10 | 1.00 | :0.474E-11 | 1.00 | :0.480E-11 | 1.00 | :0.486E-11 | 1.00 | :0.128E-09 |
| | | 0.268E-01 | :0.761E-10 | 0.271E-01 | :-.506E-11 | 0.274E-01 | :-.512E-11 | 0.277E-01 | :-.518E-11 | 0.280E-01 | :-.180E-09 |
| | | -.378 | :-.106E-09 | -.383 | :-.162E-10 | -.388 | :-.162E-10 | -.392 | :-.162E-10 | -.397 | :0.792E-10 |
| | | -.955 | :-.232E-10 | -.954 | :-.238E-10 | -.953 | :-.244E-10 | -.952 | :-.250E-10 | -.951 | :-.257E-10 |
| | | -1.00 | :0.357E-11 | -1.00 | :0.389E-11 | -1.00 | :0.422E-11 | -1.00 | :0.455E-11 | -1.00 | :0.489E-11 |
| | | -.998 | :-.375E-11 | -.998 | :-.398E-11 | -.998 | :-.420E-11 | -.998 | :-.443E-11 | -.998 | :-.467E-11 |
| | | -.233E-04 | :-.901E-11 | -.236E-04 | :-.911E-11 | -.238E-04 | :-.920E-11 | -.241E-04 | :-.930E-11 | -.243E-04 | :-.939E-11 |
| Current (mA) | / | 0.5000 | 0.5050 | 0.5100 | 0.5150 | 0.5200 | | | | | |
| Bunch length (cm) | / | 2.5000 | 2.5000 | 2.5000 | 2.5000 | 2.5000 | | | | | |
| Synchrotron tune | / | 0.0899 | 0.0899 | 0.0899 | 0.0899 | 0.0899 | | | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | | |
| | | -1.98 | :-.545E-11 | -1.98 | :-.550E-11 | -1.98 | :-.556E-11 | 0.957 | :0.389E-11 | 0.956 | :0.405E-11 |
| | | -2.00 | :0.738E-12 | -2.00 | :0.708E-12 | -2.00 | :0.674E-12 | 1.02 | :-.822E-11 | 1.02 | :-.832E-11 |
| | | -2.00 | :-.406E-11 | -2.00 | :-.409E-11 | -2.00 | :-.411E-11 | 1.00 | :0.516E-11 | 1.00 | :0.522E-11 |
| | | 0.959 | :0.343E-11 | 0.958 | :0.358E-11 | 0.958 | :0.374E-11 | -1.98 | :-.561E-11 | -1.98 | :-.567E-11 |
| | | 1.02 | :-.791E-11 | 1.02 | :-.801E-11 | 1.02 | :-.811E-11 | -2.00 | :-.414E-11 | -2.00 | :-.416E-11 |
| | | 1.00 | :0.498E-11 | 1.00 | :0.504E-11 | 1.00 | :0.510E-11 | -2.00 | :0.641E-12 | -2.00 | :0.608E-12 |
| | | 0.283E-01 | :-.529E-11 | 0.286E-01 | :-.535E-11 | 0.289E-01 | :-.541E-11 | 0.292E-01 | :-.547E-11 | 0.295E-01 | :-.553E-11 |
| | | -.401 | :-.161E-10 | -.406 | :-.161E-10 | -.411 | :-.160E-10 | -.415 | :-.160E-10 | -.420 | :-.159E-10 |
| | | -.950 | :-.263E-10 | -.949 | :-.270E-10 | -.948 | :-.276E-10 | -.947 | :-.283E-10 | -.945 | :-.290E-10 |

| | | | | | | | | | | |
|-------------------|-----------|--------------------|-----------|------------|-----------|------------|-----------|------------|-----------|------------|
| | | | | 2 | | | | | | |
| | -1.00 | :0.524E-11 | -1.00 | :0.560E-11 | -1.00 | :0.595E-11 | -1.00 | :0.632E-11 | -1.00 | :0.668E-11 |
| | -.998 | :-.490E-11 | -.998 | :-.514E-11 | -.998 | :-.539E-11 | -.998 | :-.563E-11 | -.998 | :-.588E-11 |
| | -.246E-04 | :-.949E-11 | -.248E-04 | :-.958E-11 | -.251E-04 | :-.968E-11 | -.253E-04 | :-.977E-11 | -.255E-04 | :-.987E-11 |
| Current (mA) | / | 0.5250 | 0.5300 | 0.5350 | 0.5400 | 0.5450 | | | | |
| Bunch length (cm) | / | 2.5000 | 2.5000 | 2.5000 | 2.5000 | 2.5000 | | | | |
| Synchrotron tune | / | 0.0899 | 0.0899 | 0.0899 | 0.0899 | 0.0899 | | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | |
| | 0.956 | :0.683E-11 | 0.955 | :0.740E-11 | 0.955 | :-.359E-12 | 0.954 | :-.250E-11 | 0.953 | :0.109E-10 |
| | 1.02 | :0.632E-13 | 1.02 | :-.194E-10 | 1.02 | :-.139E-10 | 1.02 | :-.637E-11 | 1.02 | :-.892E-11 |
| | 1.00 | :0.144E-10 | 1.00 | :0.176E-10 | 1.00 | :0.389E-11 | 1.00 | :0.644E-11 | 1.00 | :0.360E-12 |
| | -1.98 | :-.119E-10 | -1.97 | :0.303E-11 | -1.97 | :-.695E-11 | -1.97 | :0.535E-11 | -1.97 | :-.107E-10 |
| | -2.00 | :-.681E-11 | -2.00 | :-.462E-11 | -2.00 | :-.799E-11 | -2.00 | :0.722E-12 | -2.00 | :-.113E-10 |
| | -2.00 | :0.577E-11 | -2.00 | :-.623E-11 | -2.00 | :-.246E-11 | -2.00 | :0.157E-11 | -2.00 | :-.592E-11 |
| | 0.297E-01 | :-.355E-11 | 0.300E-01 | :-.249E-10 | 0.303E-01 | :-.920E-11 | 0.306E-01 | :-.218E-10 | 0.309E-01 | :-.171E-10 |
| | -.425 | :-.169E-10 | -.430 | :-.910E-11 | -.435 | :-.169E-10 | -.439 | :-.308E-11 | -.444 | :-.154E-10 |
| | -.944 | :-.297E-10 | -.943 | :-.305E-10 | -.941 | :-.312E-10 | -.940 | :-.320E-10 | -.939 | :-.328E-10 |
| | -1.00 | :0.705E-11 | -1.00 | :0.742E-11 | -1.00 | :0.779E-11 | -1.00 | :0.816E-11 | -1.00 | :0.852E-11 |
| | -.998 | :-.612E-11 | -.998 | :-.637E-11 | -.998 | :-.661E-11 | -.998 | :-.684E-11 | -.997 | :-.707E-11 |
| | -.258E-04 | :-.996E-11 | -.260E-04 | :-.101E-10 | -.263E-04 | :-.102E-10 | -.265E-04 | :-.102E-10 | -.268E-04 | :-.103E-10 |
| Current (mA) | / | 0.5500 | 0.5550 | 0.5600 | 0.5650 | 0.5700 | | | | |
| Bunch length (cm) | / | 2.5000 | 2.5000 | 2.5000 | 2.5000 | 2.5000 | | | | |
| Synchrotron tune | / | 0.0899 | 0.0899 | 0.0899 | 0.0899 | 0.0899 | | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | |
| | 0.953 | :0.484E-11 | 0.952 | :0.524E-11 | 0.952 | :0.542E-11 | 0.951 | :0.560E-11 | 0.950 | :0.579E-11 |
| | 1.02 | :-.726E-11 | 1.02 | :-.907E-11 | 1.02 | :-.918E-11 | 1.02 | :-.929E-11 | 1.02 | :-.940E-11 |
| | 1.00 | :0.705E-11 | 1.00 | :0.565E-11 | 1.00 | :0.571E-11 | 1.00 | :0.577E-11 | 1.00 | :0.583E-11 |
| | -1.97 | :-.673E-11 | -1.97 | :-.607E-11 | -1.97 | :-.612E-11 | -1.97 | :-.618E-11 | -1.97 | :-.624E-11 |
| | -2.00 | :-.512E-11 | -2.00 | :-.431E-11 | -2.00 | :-.434E-11 | -2.00 | :-.436E-11 | -2.00 | :-.438E-11 |
| | -2.00 | :0.142E-11 | -2.00 | :0.352E-12 | -2.00 | :0.315E-12 | -2.00 | :0.273E-12 | -2.00 | :0.233E-12 |
| | 0.312E-01 | :0.196E-12 | 0.315E-01 | :-.595E-11 | 0.318E-01 | :-.601E-11 | 0.321E-01 | :-.607E-11 | 0.324E-01 | :-.613E-11 |
| | -.449 | :-.141E-10 | -.454 | :-.149E-10 | -.459 | :-.147E-10 | -.464 | :-.145E-10 | -.470 | :-.142E-10 |
| | -.937 | :-.336E-10 | -.936 | :-.344E-10 | -.934 | :-.353E-10 | -.933 | :-.362E-10 | -.931 | :-.371E-10 |
| | -1.00 | :0.888E-11 | -1.00 | :0.924E-11 | -1.00 | :0.958E-11 | -1.00 | :0.993E-11 | -1.00 | :0.103E-10 |
| | -.997 | :-.730E-11 | -.997 | :-.752E-11 | -.997 | :-.773E-11 | -.997 | :-.793E-11 | -.997 | :-.812E-11 |
| | -.270E-04 | :-.104E-10 | -.272E-04 | :-.105E-10 | -.275E-04 | :-.106E-10 | -.277E-04 | :-.107E-10 | -.280E-04 | :-.108E-10 |
| Current (mA) | / | 0.5750 | 0.5800 | 0.5850 | 0.5900 | 0.5950 | | | | |
| Bunch length (cm) | / | 2.5000 | 2.5000 | 2.5000 | 2.5000 | 2.5000 | | | | |
| Synchrotron tune | / | 0.0899 | 0.0899 | 0.0899 | 0.0899 | 0.0899 | | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | |
| | 0.950 | :0.597E-11 | 0.949 | :0.616E-11 | 0.948 | :0.635E-11 | 0.948 | :0.655E-11 | 0.947 | :0.675E-11 |
| | 1.02 | :-.951E-11 | 1.02 | :-.963E-11 | 1.02 | :-.974E-11 | 1.02 | :-.986E-11 | 1.02 | :-.997E-11 |
| | 1.00 | :0.590E-11 | 1.00 | :0.596E-11 | 1.00 | :0.602E-11 | 1.00 | :0.605E-11 | 1.00 | :0.611E-11 |
| | -1.97 | :-.629E-11 | -1.97 | :-.635E-11 | -1.97 | :-.641E-11 | -1.97 | :-.648E-11 | -1.97 | :-.654E-11 |
| | -2.00 | :-.440E-11 | -2.00 | :-.442E-11 | -2.00 | :-.444E-11 | -2.00 | :-.443E-11 | -2.00 | :-.445E-11 |
| | -2.00 | :0.192E-12 | -2.00 | :0.151E-12 | -2.00 | :0.109E-12 | -2.00 | :0.953E-13 | -2.00 | :0.456E-13 |
| | 0.327E-01 | :-.619E-11 | 0.330E-01 | :-.626E-11 | 0.333E-01 | :-.632E-11 | 0.336E-01 | :-.638E-11 | 0.339E-01 | :-.644E-11 |
| | -.475 | :-.140E-10 | -.480 | :-.137E-10 | -.485 | :-.134E-10 | -.491 | :-.130E-10 | -.496 | :-.126E-10 |
| | -.930 | :-.380E-10 | -.928 | :-.389E-10 | -.926 | :-.399E-10 | -.924 | :-.409E-10 | -.923 | :-.420E-10 |

| | | | | | | | | | | | |
|-------------------|---|--------------------|------------|-----------|------------|-----------|------------|-----------|------------|-----------|------------|
| | | | | 2 | | | | | | | |
| | | -1.00 | :0.106E-10 | -1.00 | :0.109E-10 | -1.00 | :0.112E-10 | -1.00 | :0.115E-10 | -1.00 | :0.118E-10 |
| | | -.997 | :-.830E-11 | -.997 | :-.846E-11 | -.997 | :-.862E-11 | -.996 | :-.876E-11 | -.996 | :-.888E-11 |
| | | -.282E-04 | :-.109E-10 | -.285E-04 | :-.110E-10 | -.287E-04 | :-.111E-10 | -.289E-04 | :-.112E-10 | -.292E-04 | :-.113E-10 |
| Current (mA) | / | 0.6000 | | 0.6050 | | 0.6100 | | 0.6150 | | 0.6200 | |
| Bunch length (cm) | / | 2.5000 | | 2.5000 | | 2.5000 | | 2.5000 | | 2.5000 | |
| Synchrotron tune | / | 0.0899 | | 0.0899 | | 0.0899 | | 0.0899 | | 0.0899 | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | | |
| | | 0.947 | :0.695E-11 | 0.946 | :0.715E-11 | 0.945 | :0.735E-11 | 0.945 | :0.756E-11 | 0.944 | :0.777E-11 |
| | | 1.02 | :-.101E-10 | 1.02 | :-.102E-10 | 1.02 | :-.103E-10 | 1.02 | :-.104E-10 | 1.02 | :-.106E-10 |
| | | 1.00 | :0.618E-11 | 1.00 | :0.624E-11 | 1.00 | :0.630E-11 | 1.00 | :0.637E-11 | 1.00 | :0.643E-11 |
| | | -1.97 | :-.660E-11 | -1.97 | :-.666E-11 | -1.97 | :-.671E-11 | -1.97 | :-.677E-11 | -1.97 | :-.683E-11 |
| | | -2.00 | :-.447E-11 | -2.00 | :-.448E-11 | -2.00 | :-.450E-11 | -2.00 | :-.452E-11 | -2.00 | :-.454E-11 |
| | | -2.00 | :0.105E-14 | -2.00 | :-.449E-13 | -2.00 | :-.914E-13 | -2.00 | :-.137E-12 | -2.00 | :-.185E-12 |
| | | 0.342E-01 | :-.651E-11 | 0.345E-01 | :-.657E-11 | 0.348E-01 | :-.663E-11 | 0.351E-01 | :-.670E-11 | 0.354E-01 | :-.676E-11 |
| | | -.501 | :-.122E-10 | -.507 | :-.118E-10 | -.513 | :-.113E-10 | -.518 | :-.108E-10 | -.524 | :-.102E-10 |
| | | -.921 | :-.431E-10 | -.919 | :-.442E-10 | -.917 | :-.454E-10 | -.914 | :-.466E-10 | -.912 | :-.478E-10 |
| | | -1.00 | :0.120E-10 | -1.00 | :0.123E-10 | -1.00 | :0.125E-10 | -1.00 | :0.127E-10 | -1.00 | :0.130E-10 |
| | | -.996 | :-.900E-11 | -.996 | :-.909E-11 | -.996 | :-.918E-11 | -.996 | :-.924E-11 | -.996 | :-.930E-11 |
| | | -.294E-04 | :-.114E-10 | -.297E-04 | :-.115E-10 | -.299E-04 | :-.116E-10 | -.302E-04 | :-.117E-10 | -.304E-04 | :-.118E-10 |
| Current (mA) | / | 0.6250 | | 0.6300 | | 0.6350 | | 0.6400 | | 0.6450 | |
| Bunch length (cm) | / | 2.5000 | | 2.5000 | | 2.5000 | | 2.5000 | | 2.5000 | |
| Synchrotron tune | / | 0.0899 | | 0.0899 | | 0.0899 | | 0.0899 | | 0.0899 | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | | |
| | | 0.943 | :0.799E-11 | 0.943 | :0.820E-11 | 0.942 | :0.842E-11 | 0.941 | :0.864E-11 | 0.941 | :0.886E-11 |
| | | 1.02 | :-.107E-10 | 1.02 | :-.108E-10 | 1.02 | :-.109E-10 | 1.02 | :-.110E-10 | 1.02 | :-.112E-10 |
| | | 1.00 | :0.650E-11 | 1.00 | :0.656E-11 | 1.00 | :0.663E-11 | 1.00 | :0.669E-11 | 1.00 | :0.679E-11 |
| | | -1.97 | :-.688E-11 | -1.97 | :-.694E-11 | -1.97 | :-.700E-11 | -1.97 | :-.705E-11 | -1.97 | :-.711E-11 |
| | | -2.00 | :-.456E-11 | -2.00 | :-.458E-11 | -2.00 | :-.459E-11 | -2.00 | :-.461E-11 | -2.00 | :-.465E-11 |
| | | -2.00 | :-.233E-12 | -2.00 | :-.281E-12 | -2.00 | :-.331E-12 | -2.00 | :-.379E-12 | -2.00 | :-.459E-12 |
| | | 0.357E-01 | :-.682E-11 | 0.360E-01 | :-.688E-11 | 0.363E-01 | :-.695E-11 | 0.366E-01 | :-.702E-11 | 0.369E-01 | :-.708E-11 |
| | | -.530 | :-.957E-11 | -.536 | :-.889E-11 | -.542 | :-.815E-11 | -.548 | :-.734E-11 | -.554 | :-.645E-11 |
| | | -.910 | :-.491E-10 | -.908 | :-.505E-10 | -.905 | :-.519E-10 | -.903 | :-.534E-10 | -.900 | :-.550E-10 |
| | | -1.00 | :0.132E-10 | -1.00 | :0.133E-10 | -1.00 | :0.135E-10 | -1.00 | :0.137E-10 | -1.00 | :0.138E-10 |
| | | -.996 | :-.934E-11 | -.995 | :-.936E-11 | -.995 | :-.937E-11 | -.995 | :-.937E-11 | -.995 | :-.936E-11 |
| | | -.306E-04 | :-.119E-10 | -.309E-04 | :-.120E-10 | -.311E-04 | :-.121E-10 | -.314E-04 | :-.122E-10 | -.316E-04 | :-.122E-10 |
| Current (mA) | / | 0.6500 | | 0.6550 | | 0.6600 | | 0.6650 | | 0.6700 | |
| Bunch length (cm) | / | 2.5000 | | 2.5000 | | 2.5000 | | 2.5000 | | 2.5000 | |
| Synchrotron tune | / | 0.0899 | | 0.0899 | | 0.0899 | | 0.0899 | | 0.0899 | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | | |
| | | 0.940 | :0.909E-11 | 0.939 | :0.932E-11 | 0.939 | :0.955E-11 | 0.938 | :-.227E-10 | 0.937 | :0.371E-11 |
| | | 1.02 | :-.113E-10 | 1.02 | :-.114E-10 | 1.02 | :-.115E-10 | 1.02 | :-.585E-10 | 1.02 | :0.335E-10 |
| | | 1.00 | :0.686E-11 | 1.00 | :0.692E-11 | 1.00 | :0.698E-11 | 1.00 | :-.359E-11 | 1.00 | :0.799E-10 |
| | | -1.97 | :-.716E-11 | -1.97 | :-.722E-11 | -1.97 | :-.728E-11 | -1.97 | :-.232E-10 | -1.97 | :-.232E-10 |
| | | -2.00 | :-.466E-11 | -2.00 | :-.468E-11 | -2.00 | :-.470E-11 | -2.00 | :0.935E-11 | -2.00 | :-.463E-10 |
| | | -2.00 | :-.508E-12 | -2.00 | :-.557E-12 | -2.00 | :-.609E-12 | -2.00 | :0.617E-11 | -2.00 | :0.317E-10 |
| | | 0.372E-01 | :-.715E-11 | 0.375E-01 | :-.721E-11 | 0.378E-01 | :-.727E-11 | 0.381E-01 | :0.904E-10 | 0.384E-01 | :-.156E-09 |
| | | -.560 | :-.548E-11 | -.567 | :-.440E-11 | -.573 | :-.321E-11 | -.580 | :-.503E-10 | -.587 | :0.290E-10 |
| | | -.897 | :-.567E-10 | -.894 | :-.585E-10 | -.891 | :-.604E-10 | -.888 | :-.722E-10 | -.885 | :-.642E-10 |


| | | | | | | | |
|---------------------|-----------------------|-----------------------|-----------------------|-----------------------|-----------------------|--|--|
| | | | | 2 | | | |
| | -1.00 : 0.140E-10 | -1.00 : 0.141E-10 | -1.00 : 0.142E-10 | -1.00 : 0.143E-10 | -1.00 : 0.144E-10 | | |
| | -.995 : -.934E-11 | -.995 : -.930E-11 | -.995 : -.925E-11 | -.994 : -.920E-11 | -.994 : -.913E-11 | | |
| | -.319E-04 : -.123E-10 | -.321E-04 : -.124E-10 | -.323E-04 : -.125E-10 | -.326E-04 : -.126E-10 | -.328E-04 : -.127E-10 | | |
| Current (mA) / | 0.6750 | 0.6800 | 0.6850 | 0.6900 | 0.6950 | | |
| Bunch length (cm) / | 2.5000 | 2.5000 | 2.5000 | 2.5000 | 2.5000 | | |
| Synchrotron tune / | 0.0899 | 0.0899 | 0.0899 | 0.0899 | 0.0899 | | |
| (Nu-Nux)/Nus ... | (REAL : IMAGINARY) | | | | | | |
| | 0.937 : 0.335E-10 | 0.936 : -.741E-11 | 0.935 : -.234E-11 | 0.935 : 0.177E-10 | 0.934 : -.700E-11 | | |
| | 1.02 : -.246E-10 | 1.02 : -.119E-10 | 1.02 : -.529E-11 | 1.02 : 0.473E-11 | 1.02 : -.540E-11 | | |
| | 1.00 : 0.228E-10 | 1.00 : -.821E-10 | 1.00 : -.425E-10 | 1.00 : -.239E-10 | 1.00 : -.237E-10 | | |
| | -1.97 : -.340E-10 | -1.97 : -.160E-10 | -1.97 : -.162E-10 | -1.97 : -.348E-10 | -1.97 : -.105E-10 | | |
| | -2.00 : -.275E-10 | -2.00 : 0.192E-10 | -2.00 : 0.191E-11 | -2.00 : 0.164E-11 | -2.00 : 0.183E-10 | | |
| | -2.00 : -.131E-11 | -2.00 : -.618E-11 | -2.00 : 0.196E-10 | -2.00 : 0.362E-10 | -2.00 : 0.392E-10 | | |
| | 0.387E-01 : 0.710E-10 | 0.390E-01 : 0.546E-10 | 0.393E-01 : 0.236E-10 | 0.396E-01 : -.266E-10 | 0.399E-01 : -.712E-10 | | |
| | -.594 : -.446E-10 | -.601 : 0.134E-10 | -.609 : 0.260E-10 | -.616 : 0.733E-11 | -.624 : 0.251E-10 | | |
| | -.881 : -.739E-10 | -.877 : -.753E-10 | -.873 : -.841E-10 | -.869 : -.692E-10 | -.865 : -.811E-10 | | |
| | -1.00 : 0.145E-10 | -1.00 : 0.146E-10 | -1.00 : 0.147E-10 | -1.00 : 0.147E-10 | -1.00 : 0.148E-10 | | |
| | -.994 : -.906E-11 | -.994 : -.898E-11 | -.994 : -.889E-11 | -.994 : -.879E-11 | -.993 : -.869E-11 | | |
| | -.331E-04 : -.128E-10 | -.333E-04 : -.129E-10 | -.336E-04 : -.130E-10 | -.338E-04 : -.131E-10 | -.340E-04 : -.132E-10 | | |
| Current (mA) / | 0.7000 | 0.7050 | 0.7100 | 0.7150 | 0.7200 | | |
| Bunch length (cm) / | 2.5000 | 2.5000 | 2.5000 | 2.5000 | 2.5000 | | |
| Synchrotron tune / | 0.0899 | 0.0899 | 0.0899 | 0.0899 | 0.0899 | | |
| (Nu-Nux)/Nus ... | (REAL : IMAGINARY) | | | | | | |
| | 0.933 : 0.367E-11 | 0.933 : -.936E-11 | 0.932 : -.191E-10 | 0.931 : 0.346E-10 | 0.931 : 0.929E-11 | | |
| | 1.03 : -.142E-10 | 1.03 : -.271E-10 | 1.03 : -.227E-11 | 1.03 : -.150E-10 | 1.03 : -.934E-11 | | |
| | 1.00 : -.296E-10 | 1.00 : -.324E-10 | 1.00 : 0.991E-12 | 1.00 : 0.751E-11 | 1.00 : 0.178E-10 | | |
| | -1.97 : -.572E-11 | -1.96 : -.470E-11 | -1.96 : -.532E-11 | -1.96 : -.171E-10 | -1.96 : -.663E-11 | | |
| | -2.00 : 0.107E-10 | -2.00 : 0.200E-10 | -2.00 : -.918E-11 | -2.00 : -.138E-10 | -2.00 : -.548E-11 | | |
| | -2.00 : 0.443E-10 | -2.00 : 0.257E-10 | -2.00 : 0.246E-11 | -2.00 : -.160E-10 | -2.00 : -.358E-11 | | |
| | 0.402E-01 : -.583E-11 | 0.405E-01 : -.438E-10 | 0.408E-01 : -.200E-10 | 0.411E-01 : -.206E-10 | 0.414E-01 : -.200E-10 | | |
| | -.633 : -.117E-10 | -.642 : 0.964E-11 | -.651 : 0.363E-10 | -.661 : 0.452E-10 | -.672 : 0.428E-10 | | |
| | -.860 : -.657E-10 | -.854 : -.623E-10 | -.848 : -.978E-10 | -.842 : -.998E-10 | -.835 : -.111E-09 | | |
| | -1.00 : 0.149E-10 | -1.00 : 0.149E-10 | -1.00 : 0.150E-10 | -1.00 : 0.150E-10 | -1.00 : 0.151E-10 | | |
| | -.993 : -.859E-11 | -.993 : -.847E-11 | -.993 : -.836E-11 | -.993 : -.824E-11 | -.992 : -.811E-11 | | |
| | -.343E-04 : -.133E-10 | -.345E-04 : -.134E-10 | -.348E-04 : -.135E-10 | -.350E-04 : -.136E-10 | -.352E-04 : -.137E-10 | | |
| Current (mA) / | 0.7250 | 0.7300 | 0.7350 | 0.7400 | 0.7450 | | |
| Bunch length (cm) / | 2.5000 | 2.5000 | 2.5000 | 2.5000 | 2.5000 | | |
| Synchrotron tune / | 0.0899 | 0.0899 | 0.0899 | 0.0899 | 0.0899 | | |
| (Nu-Nux)/Nus ... | (REAL : IMAGINARY) | | | | | | |
| | 0.930 : 0.128E-10 | 0.929 : 0.131E-10 | 0.928 : 0.133E-10 | 0.928 : -.281E-09 | 0.927 : 0.424E-10 | | |
| | 1.03 : -.132E-10 | 1.03 : -.134E-10 | 1.03 : -.135E-10 | 1.03 : 0.144E-08 | 1.03 : 0.649E-10 | | |
| | 1.00 : 0.780E-11 | 1.00 : 0.786E-11 | 1.00 : 0.793E-11 | 1.00 : 0.246E-09 | 1.00 : 0.730E-08 | | |
| | -1.96 : -.802E-11 | -1.96 : -.807E-11 | -1.96 : -.813E-11 | -1.96 : 0.700E-11 | -1.96 : 0.165E-09 | | |
| | -2.00 : -.488E-11 | -2.00 : -.489E-11 | -2.00 : -.490E-11 | -2.00 : -.125E-08 | -2.00 : 0.233E-09 | | |
| | -2.00 : -.131E-11 | -2.00 : -.137E-11 | -2.00 : -.142E-11 | -2.00 : 0.117E-08 | -2.00 : 0.375E-08 | | |
| | 0.417E-01 : -.815E-11 | 0.420E-01 : -.822E-11 | 0.423E-01 : -.829E-11 | 0.426E-01 : -.445E-09 | 0.429E-01 : -.662E-08 | | |
| | -.684 : 0.494E-10 | -.697 : 0.683E-10 | -.714 : 0.106E-09 | -.740 : -.268E-09 | -.762 : 0.337E-01 | | |
| | -.826 : -.122E-09 | -.816 : -.142E-09 | -.803 : -.181E-09 | -.781 : 0.601E-09 | -.762 : -.337E-01 | | |

| | | | | | | | | | | |
|-------------------|-----------|--------------------|-----------|------------|-----------|------------|-----------|------------|-----------|------------|
| | | | | 2 | | | | | | |
| | -1.00 | :0.151E-10 | -1.00 | :0.151E-10 | -.992 | :-.772E-11 | -.992 | :-.758E-11 | -.992 | :-.745E-11 |
| | -.992 | :-.798E-11 | -.992 | :-.785E-11 | -1.00 | :0.152E-10 | -1.00 | :0.152E-10 | -1.00 | :0.152E-10 |
| | -.355E-04 | :-.138E-10 | -.357E-04 | :-.139E-10 | -.360E-04 | :-.140E-10 | -.362E-04 | :-.141E-10 | -.365E-04 | :-.142E-10 |
| Current (mA) | / | 0.7500 | 0.7550 | 0.7600 | 0.7650 | 0.7700 | | | | |
| Bunch length (cm) | / | 2.5000 | 2.5000 | 2.5000 | 2.5000 | 2.5000 | | | | |
| Synchrotron tune | / | 0.0899 | 0.0899 | 0.0899 | 0.0899 | 0.0899 | | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | |
| | 0.926 | :0.881E-08 | -1.96 | :-.578E-08 | -1.96 | :-.308E-08 | -1.96 | :0.870E-08 | -1.96 | :-.219E-07 |
| | 1.03 | :-.105E-08 | -2.00 | :0.311E-07 | -2.00 | :0.149E-07 | -2.00 | :-.531E-08 | -2.00 | :-.133E-07 |
| | 1.00 | :0.866E-08 | -2.00 | :0.421E-07 | -2.00 | :0.114E-07 | -2.00 | :0.698E-08 | -2.00 | :0.510E-07 |
| | -1.96 | :0.550E-08 | 0.926 | :-.396E-08 | 0.925 | :-.492E-08 | 0.924 | :0.164E-07 | 0.923 | :-.547E-09 |
| | -2.00 | :-.184E-07 | 1.03 | :-.512E-08 | 1.03 | :-.718E-08 | 1.03 | :0.209E-08 | 1.03 | :0.474E-08 |
| | -2.00 | :-.282E-07 | 1.00 | :-.389E-07 | 1.00 | :0.623E-07 | 1.00 | :0.146E-07 | 1.00 | :0.794E-08 |
| | 0.432E-01 | :0.229E-07 | 0.436E-01 | :0.571E-07 | 0.439E-01 | :-.197E-07 | 0.442E-01 | :0.315E-07 | 0.445E-01 | :-.162E-07 |
| | -.764 | :0.519E-01 | -.765 | :0.652E-01 | -.767 | :0.762E-01 | -.769 | :0.858E-01 | -.771 | :0.944E-01 |
| | -.764 | :-.519E-01 | -.765 | :-.652E-01 | -.767 | :-.762E-01 | -.769 | :-.858E-01 | -.771 | :-.944E-01 |
| | -.991 | :-.731E-11 | -.991 | :-.717E-11 | -.991 | :-.702E-11 | -.991 | :-.688E-11 | -.991 | :-.674E-11 |
| | -1.00 | :0.153E-10 | -1.00 | :0.153E-10 | -1.00 | :0.153E-10 | -1.00 | :0.153E-10 | -1.00 | :0.154E-10 |
| | -.367E-04 | :-.142E-10 | -.369E-04 | :-.143E-10 | -.372E-04 | :-.144E-10 | -.374E-04 | :-.145E-10 | -.377E-04 | :-.146E-10 |
| Current (mA) | / | 0.7750 | 0.7800 | 0.7850 | 0.7900 | 0.7950 | | | | |
| Bunch length (cm) | / | 2.5000 | 2.5000 | 2.5000 | 2.5000 | 2.5000 | | | | |
| Synchrotron tune | / | 0.0899 | 0.0899 | 0.0899 | 0.0899 | 0.0899 | | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | |
| | -1.96 | :-.301E-07 | -1.96 | :0.280E-08 | -1.96 | :0.332E-07 | 0.921 | :0.264E-07 | 0.920 | :-.167E-07 |
| | -2.00 | :-.341E-07 | -2.00 | :-.112E-07 | -2.00 | :0.302E-07 | 1.03 | :0.115E-07 | 1.03 | :0.169E-07 |
| | -2.00 | :-.154E-07 | -2.00 | :-.916E-08 | -2.00 | :-.300E-07 | 1.00 | :0.211E-07 | 1.00 | :0.802E-07 |
| | 0.923 | :0.129E-07 | 0.922 | :0.283E-07 | 0.921 | :0.112E-07 | -1.96 | :-.119E-07 | -1.96 | :0.643E-08 |
| | 1.03 | :0.690E-08 | 1.03 | :-.187E-07 | 1.03 | :-.252E-07 | -2.00 | :-.482E-08 | -2.00 | :-.184E-07 |
| | 1.00 | :0.477E-08 | 1.00 | :-.516E-07 | 1.00 | :-.729E-07 | -2.00 | :0.559E-08 | -2.00 | :-.317E-07 |
| | 0.448E-01 | :0.114E-07 | 0.451E-01 | :-.180E-08 | 0.454E-01 | :-.357E-07 | 0.457E-01 | :0.889E-08 | 0.460E-01 | :-.338E-07 |
| | -.772 | :0.102 | -.774 | :0.110 | -.776 | :0.117 | -.778 | :0.123 | -.779 | :0.129 |
| | -.772 | :-.102 | -.774 | :-.110 | -.776 | :-.117 | -.778 | :-.123 | -.779 | :-.129 |
| | -.990 | :-.659E-11 | -.990 | :-.645E-11 | -.990 | :-.630E-11 | -.990 | :-.616E-11 | -.990 | :-.601E-11 |
| | -1.00 | :0.154E-10 | -1.00 | :0.154E-10 | -1.00 | :0.154E-10 | -1.00 | :0.154E-10 | -1.00 | :0.155E-10 |
| | -.379E-04 | :-.147E-10 | -.382E-04 | :-.148E-10 | -.384E-04 | :-.149E-10 | -.386E-04 | :-.150E-10 | -.389E-04 | :-.151E-10 |
| Current (mA) | / | 0.8000 | 0.8050 | 0.8100 | 0.8150 | 0.8200 | | | | |
| Bunch length (cm) | / | 2.5000 | 2.5000 | 2.5000 | 2.5000 | 2.5000 | | | | |
| Synchrotron tune | / | 0.0899 | 0.0899 | 0.0899 | 0.0899 | 0.0899 | | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | |
| | 0.919 | :0.154E-07 | 0.918 | :0.613E-08 | 0.918 | :-.116E-07 | 0.917 | :0.259E-08 | 0.916 | :-.228E-08 |
| | 1.03 | :-.594E-08 | 1.03 | :0.166E-07 | 1.03 | :-.787E-08 | 1.03 | :-.144E-07 | 1.03 | :0.327E-07 |
| | 1.00 | :0.258E-07 | 1.00 | :0.754E-07 | 1.00 | :0.657E-07 | 1.00 | :0.364E-07 | 1.00 | :0.141E-06 |
| | -1.96 | :0.725E-09 | -1.96 | :-.707E-09 | -1.96 | :-.171E-07 | -1.96 | :0.187E-07 | -1.96 | :0.285E-07 |
| | -2.00 | :-.300E-09 | -2.00 | :0.636E-08 | -2.00 | :-.300E-08 | -2.00 | :0.157E-08 | -2.00 | :0.352E-07 |
| | -2.00 | :-.586E-08 | -2.00 | :-.191E-07 | -2.00 | :-.308E-08 | -2.00 | :0.623E-08 | -2.00 | :0.416E-07 |
| | 0.463E-01 | :-.116E-07 | 0.466E-01 | :-.764E-07 | 0.470E-01 | :-.604E-07 | 0.473E-01 | :-.107E-06 | 0.476E-01 | :-.147E-06 |
| | -.781 | :0.135 | -.783 | :0.141 | -.785 | :0.146 | -.786 | :0.152 | -.788 | :0.157 |
| | -.781 | :-.135 | -.783 | :-.141 | -.785 | :-.146 | -.786 | :-.152 | -.788 | :-.157 |

| | | | | | | | | | | |
|-------------------|------------|--------------------|------------|-------------|------------|-------------|------------|-------------|------------|-------------|
| | | | | 2 | | | | | | |
| | - .989 | :-. 586E-11 | - .989 | :-. 572E-11 | - .989 | :-. 557E-11 | - .989 | :-. 543E-11 | - .989 | :-. 528E-11 |
| | -1.00 | :0. 155E-10 | -1.00 | :0. 155E-10 | -1.00 | :0. 155E-10 | -1.00 | :0. 155E-10 | -1.00 | :0. 156E-10 |
| | - .391E-04 | :-. 152E-10 | - .394E-04 | :-. 153E-10 | - .396E-04 | :-. 154E-10 | - .398E-04 | :-. 155E-10 | - .401E-04 | :-. 156E-10 |
| Current (mA) | / | 0. 8250 | 0. 8300 | 0. 8350 | 0. 8400 | 0. 8450 | | | | |
| Bunch length (cm) | / | 2. 5000 | 2. 5000 | 2. 5000 | 2. 5000 | 2. 5000 | | | | |
| Synchrotron tune | / | 0. 0899 | 0. 0899 | 0. 0899 | 0. 0899 | 0. 0899 | | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | |
| | 0. 915 | :0. 277E-07 | 0. 915 | :0. 135E-07 | 0. 914 | :0. 516E-07 | 0. 913 | :-. 640E-08 | 0. 912 | :0. 140E-07 |
| | 1. 03 | :-. 236E-07 | 1. 03 | :0. 523E-07 | 1. 03 | :-. 662E-08 | 1. 03 | :0. 137E-07 | 1. 03 | :0. 236E-07 |
| | 1. 00 | :0. 209E-07 | 1. 00 | :0. 138E-06 | 1. 00 | :0. 175E-08 | 1. 00 | :-. 213E-07 | 1. 00 | :-. 859E-08 |
| | -1. 96 | :-. 363E-07 | -1. 96 | :0. 215E-07 | -1. 96 | :0. 206E-07 | -1. 96 | :0. 153E-07 | -1. 96 | :0. 257E-07 |
| | -2. 00 | :-. 103E-07 | -2. 00 | :0. 230E-07 | -2. 00 | :0. 950E-08 | -2. 00 | :-. 654E-07 | -2. 00 | :-. 303E-07 |
| | -2. 00 | :-. 231E-07 | -2. 00 | :0. 187E-07 | -2. 00 | :0. 195E-07 | -2. 00 | :0. 549E-07 | -2. 00 | :0. 817E-07 |
| | 0. 479E-01 | :-. 243E-07 | 0. 482E-01 | :-. 175E-06 | 0. 485E-01 | :0. 109E-06 | 0. 488E-01 | :0. 229E-06 | 0. 492E-01 | :0. 497E-07 |
| | - .790 | :0. 162 | - .792 | :0. 166 | - .793 | :-. 171 | - .795 | :0. 175 | - .797 | :0. 180 |
| | - .790 | :-. 162 | - .792 | :-. 166 | - .793 | :0. 171 | - .795 | :-. 175 | - .797 | :-. 180 |
| | - .988 | :-. 514E-11 | - .988 | :-. 499E-11 | - .988 | :-. 485E-11 | - .988 | :-. 471E-11 | - .988 | :-. 457E-11 |
| | -1. 00 | :0. 156E-10 | -1. 00 | :0. 156E-10 | -1. 00 | :0. 156E-10 | -1. 00 | :0. 156E-10 | -1. 00 | :0. 156E-10 |
| | - .403E-04 | :-. 157E-10 | - .406E-04 | :-. 158E-10 | - .408E-04 | :-. 159E-10 | - .410E-04 | :-. 160E-10 | - .413E-04 | :-. 161E-10 |
| Current (mA) | / | 0. 8500 | 0. 8550 | 0. 8600 | 0. 8650 | 0. 8700 | | | | |
| Bunch length (cm) | / | 2. 5000 | 2. 5000 | 2. 5000 | 2. 5000 | 2. 5000 | | | | |
| Synchrotron tune | / | 0. 0899 | 0. 0899 | 0. 0899 | 0. 0899 | 0. 0899 | | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | |
| | 0. 912 | :-. 306E-07 | 0. 911 | :0. 399E-07 | 0. 910 | :0. 964E-08 | 0. 909 | :0. 259E-07 | 0. 908 | :-. 330E-07 |
| | 1. 03 | :-. 876E-08 | 1. 03 | :0. 269E-08 | 1. 03 | :0. 859E-08 | 1. 03 | :0. 579E-08 | 1. 03 | :-. 704E-07 |
| | 1. 00 | :-. 444E-07 | 1. 00 | :0. 819E-08 | 1. 00 | :-. 150E-07 | 1. 00 | :-. 959E-07 | 1. 00 | :0. 496E-07 |
| | -1. 96 | :-. 161E-07 | -1. 96 | :0. 256E-07 | -1. 96 | :-. 153E-07 | -1. 96 | :0. 957E-08 | -1. 95 | :0. 206E-07 |
| | -2. 00 | :0. 609E-09 | -2. 00 | :0. 686E-07 | -2. 00 | :0. 550E-08 | -2. 00 | :0. 495E-07 | -2. 00 | :-. 551E-07 |
| | -2. 00 | :-. 713E-08 | -2. 00 | :0. 902E-07 | -2. 00 | :0. 125E-07 | -2. 00 | :0. 166E-07 | -2. 00 | :-. 856E-08 |
| | 0. 495E-01 | :-. 454E-07 | 0. 498E-01 | :-. 111E-06 | 0. 501E-01 | :0. 216E-07 | 0. 504E-01 | :0. 129E-06 | 0. 507E-01 | :-. 875E-07 |
| | - .798 | :0. 184 | - .800 | :0. 188 | - .802 | :0. 193 | - .804 | :0. 197 | - .805 | :-. 201 |
| | - .798 | :-. 184 | - .800 | :-. 188 | - .802 | :-. 193 | - .804 | :-. 197 | - .805 | :0. 201 |
| | - .987 | :-. 442E-11 | - .987 | :-. 428E-11 | - .987 | :-. 414E-11 | - .987 | :-. 400E-11 | - .987 | :-. 386E-11 |
| | -1. 00 | :0. 157E-10 | -1. 00 | :0. 157E-10 | -1. 00 | :0. 157E-10 | -1. 00 | :0. 157E-10 | -1. 00 | :0. 157E-10 |
| | - .415E-04 | :-. 162E-10 | - .418E-04 | :-. 162E-10 | - .420E-04 | :-. 163E-10 | - .423E-04 | :-. 164E-10 | - .425E-04 | :-. 165E-10 |
| Current (mA) | / | 0. 8750 | 0. 8800 | 0. 8850 | 0. 8900 | 0. 8950 | | | | |
| Bunch length (cm) | / | 2. 5000 | 2. 5000 | 2. 5000 | 2. 5000 | 2. 5000 | | | | |
| Synchrotron tune | / | 0. 0899 | 0. 0899 | 0. 0899 | 0. 0899 | 0. 0899 | | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | |
| | 0. 908 | :-. 743E-08 | 0. 907 | :-. 327E-07 | 0. 906 | :0. 201E-07 | 0. 905 | :0. 465E-07 | 0. 905 | :-. 266E-07 |
| | 1. 03 | :0. 329E-07 | 1. 03 | :-. 324E-07 | 1. 03 | :-. 115E-07 | 1. 03 | :0. 227E-07 | 1. 03 | :-. 495E-07 |
| | 1. 00 | :0. 235E-07 | 1. 00 | :-. 139E-07 | 1. 00 | :0. 100E-06 | 1. 00 | :-. 606E-07 | 1. 00 | :0. 210E-07 |
| | -1. 95 | :0. 549E-07 | -1. 95 | :-. 681E-08 | -1. 95 | :0. 197E-08 | -1. 95 | :-. 594E-07 | -1. 95 | :0. 329E-07 |
| | -2. 00 | :-. 161E-08 | -2. 00 | :-. 617E-07 | -2. 00 | :-. 805E-07 | -2. 00 | :0. 175E-07 | -2. 00 | :-. 636E-07 |
| | -2. 00 | :0. 460E-07 | -2. 00 | :-. 466E-07 | -2. 00 | :-. 590E-07 | -2. 00 | :-. 600E-08 | -2. 00 | :-. 289E-07 |
| | 0. 511E-01 | :-. 647E-07 | 0. 514E-01 | :-. 837E-08 | 0. 517E-01 | :-. 100E-06 | 0. 520E-01 | :0. 236E-07 | 0. 523E-01 | :-. 104E-06 |
| | - .807 | :-. 204 | - .809 | :-. 208 | - .811 | :-. 212 | - .812 | :0. 216 | - .814 | :-. 219 |
| | - .807 | :0. 204 | - .809 | :0. 208 | - .811 | :0. 212 | - .812 | :-. 216 | - .814 | :0. 219 |


| | | | | | | | | | | | |
|-------------------|---|--------------------|-------------|------------|-------------|------------|-------------|------------|-------------|------------|-------------|
| | | | | 2 | | | | | | | |
| | | - .986 | :- .373E-11 | - .986 | :- .359E-11 | - .986 | :- .345E-11 | - .986 | :- .331E-11 | - .986 | :- .317E-11 |
| | | -1.00 | :0.158E-10 | -1.00 | :0.158E-10 | -1.00 | :0.158E-10 | -1.00 | :0.158E-10 | -1.00 | :0.158E-10 |
| | | - .427E-04 | :- .166E-10 | - .430E-04 | :- .167E-10 | - .432E-04 | :- .168E-10 | - .435E-04 | :- .169E-10 | - .437E-04 | :- .170E-10 |
| Current (mA) | / | 0.9000 | 0.9050 | 0.9100 | 0.9150 | 0.9200 | | | | | |
| Bunch length (cm) | / | 2.5000 | 2.5000 | 2.5000 | 2.5000 | 2.5000 | | | | | |
| Synchrotron tune | / | 0.0899 | 0.0899 | 0.0899 | 0.0899 | 0.0899 | | | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | | |
| | | 0.904 | :0.501E-07 | 0.903 | :- .357E-07 | 0.902 | :- .137E-07 | 0.901 | :- .125E-08 | 0.901 | :0.332E-08 |
| | | 1.03 | :0.334E-07 | 1.03 | :- .203E-07 | 1.03 | :- .174E-07 | 1.03 | :0.232E-07 | 1.03 | :- .146E-06 |
| | | 1.00 | :0.813E-07 | 1.00 | :0.386E-07 | 1.00 | :- .174E-07 | 1.00 | :- .239E-07 | 1.00 | :- .389E-07 |
| | | -1.95 | :0.953E-08 | -1.95 | :0.367E-07 | -1.95 | :0.194E-08 | -1.95 | :- .598E-09 | -1.95 | :0.477E-09 |
| | | -2.00 | :- .391E-07 | -2.00 | :- .728E-07 | -2.00 | :- .353E-07 | -2.00 | :0.207E-07 | -2.00 | :0.255E-08 |
| | | -2.00 | :- .104E-07 | -2.00 | :- .217E-07 | -2.00 | :- .388E-07 | -2.00 | :0.368E-07 | -2.00 | :- .237E-07 |
| | | 0.527E-01 | :- .655E-07 | 0.530E-01 | :- .608E-07 | 0.533E-01 | :0.317E-07 | 0.536E-01 | :- .869E-08 | 0.539E-01 | :- .278E-08 |
| | | - .816 | :- .223 | - .817 | :- .226 | - .819 | :0.230 | - .821 | :0.233 | - .823 | :- .237 |
| | | - .816 | :0.223 | - .817 | :0.226 | - .819 | :- .230 | - .821 | :- .233 | - .823 | :0.237 |
| | | - .985 | :- .304E-11 | - .985 | :- .291E-11 | - .444E-04 | :- .173E-10 | - .446E-04 | :- .174E-10 | - .450E-04 | :- .175E-10 |
| | | -1.00 | :0.158E-10 | -1.00 | :0.159E-10 | - .985 | :- .278E-11 | - .985 | :- .265E-11 | - .985 | :- .252E-11 |
| | | - .439E-04 | :- .171E-10 | - .442E-04 | :- .172E-10 | -1.00 | :0.159E-10 | -1.00 | :0.159E-10 | -1.00 | :0.159E-10 |
| Current (mA) | / | 0.9250 | 0.9300 | 0.9350 | 0.9400 | 0.9450 | | | | | |
| Bunch length (cm) | / | 2.5000 | 2.5000 | 2.5000 | 2.5000 | 2.5000 | | | | | |
| Synchrotron tune | / | 0.0899 | 0.0899 | 0.0899 | 0.0899 | 0.0899 | | | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | | |
| | | 0.900 | :- .304E-07 | 0.899 | :0.382E-08 | 0.898 | :- .310E-07 | -1.95 | :0.160E-06 | 0.897 | :0.503E-08 |
| | | 1.03 | :- .381E-08 | 1.03 | :- .594E-07 | 1.03 | :0.283E-06 | -2.00 | :- .213E-07 | 1.03 | :0.693E-07 |
| | | 1.00 | :0.216E-07 | 1.00 | :- .182E-07 | 1.00 | :0.567E-07 | -2.00 | :0.946E-07 | 1.00 | :- .526E-07 |
| | | -1.95 | :- .465E-07 | -1.95 | :0.109E-07 | -1.95 | :- .119E-06 | 0.897 | :0.397E-07 | -1.95 | :- .113E-06 |
| | | -2.00 | :- .402E-08 | -2.00 | :0.251E-07 | -2.00 | :- .535E-07 | 1.03 | :- .262E-07 | -2.00 | :- .457E-07 |
| | | -2.00 | :0.105E-08 | -2.00 | :0.191E-08 | -2.00 | :0.820E-08 | 1.00 | :0.152E-06 | -2.00 | :0.163E-07 |
| | | 0.543E-01 | :0.252E-09 | 0.546E-01 | :0.320E-07 | 0.549E-01 | :0.176E-07 | 0.552E-01 | :- .645E-08 | - .831 | :- .253 |
| | | - .824 | :- .240 | - .826 | :- .243 | - .828 | :- .246 | - .829 | :- .250 | - .831 | :0.253 |
| | | - .824 | :0.240 | - .826 | :0.243 | - .828 | :0.246 | - .829 | :0.250 | 0.556E-01 | :- .115E-10 |
| | | - .450E-04 | :- .176E-10 | - .453E-04 | :- .177E-10 | - .455E-04 | :- .178E-10 | - .458E-04 | :- .179E-10 | - .984 | :- .187E-11 |
| | | - .984 | :- .238E-11 | - .984 | :- .225E-11 | - .984 | :- .212E-11 | - .984 | :- .200E-11 | -1.00 | :0.161E-10 |
| | | -1.00 | :0.160E-10 | -1.00 | :0.160E-10 | -1.00 | :0.160E-10 | -1.00 | :0.160E-10 | - .461E-04 | :- .180E-10 |
| Current (mA) | / | 0.9500 | 0.9550 | 0.9600 | 0.9650 | 0.9700 | | | | | |
| Bunch length (cm) | / | 2.5000 | 2.5000 | 2.5000 | 2.5000 | 2.5000 | | | | | |
| Synchrotron tune | / | 0.0899 | 0.0899 | 0.0899 | 0.0899 | 0.0899 | | | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | | |
| | | 0.896 | :0.657E-07 | 0.895 | :- .888E-06 | -1.95 | :0.276E-06 | -1.95 | :- .906E-07 | 0.893 | :- .847E-08 |
| | | 1.03 | :- .620E-08 | 1.03 | :0.882E-06 | -2.00 | :- .261E-06 | -2.00 | :- .217E-08 | 1.03 | :- .232E-07 |
| | | 1.00 | :- .176E-07 | 1.00 | :0.168E-06 | -2.00 | :0.448E-06 | -2.00 | :- .155E-07 | 1.00 | :- .477E-07 |
| | | -1.95 | :0.163E-07 | -1.95 | :- .126E-06 | 0.894 | :0.288E-07 | 0.893 | :- .242E-07 | -1.95 | :- .707E-08 |
| | | -2.00 | :0.394E-07 | -2.00 | :- .240E-07 | 1.03 | :- .215E-06 | 1.03 | :0.609E-07 | -2.00 | :0.413E-07 |
| | | -2.00 | :- .450E-07 | -2.00 | :0.446E-07 | 1.00 | :- .263E-07 | 1.00 | :- .729E-07 | -2.00 | :0.518E-07 |
| | | - .833 | :- .256 | - .835 | :0.259 | 0.565E-01 | :0.217E-07 | 0.569E-01 | :0.199E-07 | 0.572E-01 | :- .928E-08 |
| | | - .833 | :0.256 | - .835 | :- .259 | - .836 | :- .262 | - .838 | :- .265 | - .840 | :0.268 |
| | | 0.559E-01 | :- .116E-10 | 0.562E-01 | :- .120E-10 | - .836 | :0.262 | - .838 | :0.265 | - .840 | :- .268 |

| | | | | | | | | | |
|-------------------|-----------------------|-----------------------|-----------------------|-----------------------|-----------------------|-----------------------|-------------|--------|-------------|
| | | | | 2 | | | | | |
| | - .983 | :-. 174E-11 | - .465E-04:-. 182E-10 | - .469E-04:-. 183E-10 | - .471E-04:-. 184E-10 | - .472E-04:-. 185E-10 | | | |
| | -1. 00 | :0. 161E-10 | -1. 00 :0. 161E-10 | -1. 00 :0. 161E-10 | -1. 00 :0. 161E-10 | -1. 00 :0. 162E-10 | | | |
| | - .463E-04:-. 181E-10 | - .983 | :-. 161E-11 | - .983 | :-. 149E-11 | - .983 | :-. 136E-11 | - .983 | :-. 124E-11 |
| Current (mA) | / | 0. 9750 | 0. 9800 | 0. 9850 | 0. 9900 | 0. 9950 | | | |
| Bunch length (cm) | / | 2. 5000 | 2. 5000 | 2. 5000 | 2. 5000 | 2. 5000 | | | |
| Synchrotron tune | / | 0. 0899 | 0. 0899 | 0. 0899 | 0. 0899 | 0. 0899 | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | |
| | 0. 892 | :-. 251E-07 | 0. 891 :0. 169E-08 | -1. 95 :- .521E-07 | 0. 889 :- .236E-07 | 0. 888 :- .734E-07 | | | |
| | 1. 03 | :0. 623E-07 | 1. 03 :0. 124E-06 | -2. 00 :- .124E-07 | 1. 03 :0. 279E-06 | 1. 03 :0. 848E-07 | | | |
| | 1. 00 | :-. 242E-07 | 1. 00 :0. 321E-07 | -2. 00 :0. 648E-08 | 1. 00 :0. 771E-07 | 1. 00 :0. 350E-07 | | | |
| | -1. 95 | :-. 679E-07 | -1. 95 :- .102E-06 | 0. 890 :- .107E-06 | -1. 95 :- .679E-07 | -1. 95 :- .435E-08 | | | |
| | -2. 00 | :-. 348E-07 | -2. 00 :- .693E-07 | 1. 03 :0. 907E-08 | -2. 00 :0. 135E-07 | -2. 00 :0. 800E-07 | | | |
| | -2. 00 | :-. 574E-08 | -2. 00 :- .430E-07 | 1. 00 :- .122E-07 | -2. 00 :- .717E-07 | -2. 00 :0. 597E-07 | | | |
| | - .841 | :-. 271 | - .843 :- .274 | - .845 :- .277 | - .846 :- .280 | - .848 :- .283 | | | |
| | - .841 | :0. 271 | - .843 :0. 274 | - .845 :0. 277 | - .846 :0. 280 | - .848 :0. 283 | | | |
| | 0. 575E-01:-. 120E-10 | 0. 578E-01:-. 121E-10 | 0. 582E-01:-. 122E-10 | 0. 585E-01:-. 123E-10 | 0. 588E-01:-. 124E-10 | | | | |
| | -1. 00 :0. 162E-10 | -1. 00 :0. 162E-10 | -1. 00 :0. 163E-10 | -1. 00 :0. 163E-10 | -1. 00 :0. 163E-10 | - .982 :- .630E-12 | | | |
| | - .982 :- .112E-11 | - .982 :- .995E-12 | - .982 :- .872E-12 | - .982 :- .750E-12 | - .982 :- .750E-12 | -1. 00 :0. 163E-10 | | | |
| | - .475E-04:-. 185E-10 | - .478E-04:-. 186E-10 | - .480E-04:-. 187E-10 | - .483E-04:-. 188E-10 | - .485E-04:-. 189E-10 | | | | |
| Current (mA) | / | 1. 0000 | 1. 0050 | 1. 0100 | 1. 0150 | 1. 0200 | | | |
| Bunch length (cm) | / | 2. 5000 | 2. 5000 | 2. 5000 | 2. 5000 | 2. 5000 | | | |
| Synchrotron tune | / | 0. 0899 | 0. 0899 | 0. 0899 | 0. 0899 | 0. 0899 | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | |
| | 0. 888 | :-. 189E-07 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | | | |
| | 1. 03 | :0. 775E-07 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | | | |
| | 1. 00 | :0. 223E-07 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | | | |
| | -1. 95 | :-. 108E-07 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | | | |
| | -2. 00 | :-. 491E-08 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | | | |
| | -2. 00 | :0. 191E-07 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | | | |
| | - .850 | :-. 285 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | | | |
| | - .850 | :0. 285 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | | | |
| | 0. 592E-01:-. 124E-10 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | | | |
| | - .981 :- .508E-12 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | | | |
| | -1. 00 :0. 163E-10 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | | | |
| | - .488E-04:-. 190E-10 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | 0. 00 : 0. 00 | | | |



4
 PROBLEM = SAMPLE INPUT #1 LEP AT INJECTION WITHOUT BETATRON TUNE SPREAD
 30/ 8/ 5 13:12:10
 (*) = Imaginary part of $(\text{Nu}-\text{Nux})/\text{Nus}$ vs. the bunch current (mA)

| | | |
|------------------------|------------------|---------------|
| NUS= 0.899E-01 | ENG/GeV= 20.0 | SPRD= 0.00 |
| REVFREQ/MHz= 0.112E-01 | SGMZ/cm= 2.50 | BETAC/m= 40.7 |
| FREQ/MHz= 0.200E+04 | ALPHA= 0.387E-03 | CHROM= 0.00 |
| LZOT=F | RS/MOhm/m= 2.00 | QV= 1.00 |
| | LBIN=F | MU= 0 |




TOTAL CPU TIME USED: 1.97 (S)

– Real Part of $(\nu - \nu_x)/\nu_s$ –

MOSES -- SAMPLE INPUT #1 LEP AT INJECTION WITHOUT BETATRON TUNE SPREAD

30/ 8/ 5 13:12:10 VERSION 4.0 CPU TIME USED: 1.97 (s)




SPRD = 0.00
 NUS = 0.899E-01
 ENGY = 20.0 (GeV)
 SGMZ = 2.50 (cm)
 BETAC = 40.7 (m)
 REVFRQ= 0.112E-01 (MHz)
 ALPHA = 0.387E-03
 CHORM = 0.00
 FREQ = 0.200E+04 (MHz)
 RS = 2.00 (MΩm/m)
 QV = 1.00
 LBIN = F
 MU = 0

– Imaginary Part of $(\nu - \nu_x)/\nu_s$ –

MOSES -- SAMPLE INPUT #1 LEP AT INJECTION WITHOUT BETATRON TUNE SPREAD

30/ 8/ 5 13:12:10 VERSION 4.0 CPU TIME USED: 1.97 (s)



```

*****
*                                     *
*                               MOSES *
*                                     *
*   Mode-coupling Single bunch instability in an Electron Storage ring *
*                                     *
*   SAMPLE INPUT #2  DCI OF ORSAY WITH BETATRON TUNE SPREAD *
*                                     *
*   DATE:30/ 8/ 5    TIME:14:27:59    VERSION 4.0,    AUGUST    2005 *
*                                     *
*****

```

```

$MAPRM:
SYNCHROTRON TUNE      : NUS      = 0.79200E-02
BEAM ENERGY          : ENGZ      = 0.80000    (GeV)
RMS BUNCH LENGTH      : SGMZ      = -1.0000    (cm)
BETA-FUNCTION AT IMPEDANCE : BETAC    = 8.8600    (m)
REVOLUTION FREQUENCY  : REVFRQ    = 3.1700    (MHz)
MOMENTUM COMPACTION FACTOR : ALPHA    = 0.78800E-01
CHROMATICITY          : CHROM      = 0.0000
BETATRON TUNE SPREAD AT SIGMA : SPRD    = 0.50000E-03

```

<< BUNCH LENGTH VARIES WITH CURRENT >>

<< BETATRON TUNE HAS SPREAD >>

```

$IAPRM:
RESONANT FREQUENCY    : FREQ      = 1300.0    (MHz)
IMPEDANCE              : RS        = 0.40000    (MOhm/m)
Q - VALUE              : QV        = 1.0000

```

```

$CPARM:
STARTING CURRNT       : CRNT      = 4.0000    (mA)
STEP IN CURRENT       : STPC      = 4.0000    (mA)
NUMBER OF STEPS IN CURRENT : NCR      = 99
LOWEST AZIMUTHAL MODE : NMODF    = -2
HIGHEST AZIMUTHAL MODE : NMODE    = 1
NUMBER OF LONG. RADIAL MODES : KRAD    = 0
PRINT OF EIGENVALUES  : IPRINT   = T
USE OF A BINOMIAL DISTRIBUTION : LBIN    = F

```

```

$HPARM:
MAXIMUM AZIMUTHAL MODE IN PLOT : MMAX    = 1
MINIMUM AZIMUTHAL MODE IN PLOT : MMIN    = -3
MAXIMUM COORDINATE IN TAU PLOT : TAUMAX   = 0.10000
MINIMUM COORDINATE IN TAU PLOT : TAUMIN   = -0.10000
NUMBER OF SPLITTED PLOTS      : NSPL     = 1

```

```

$SPARM:
DISPERSION MATRIX METHOD : LMTRIX   = F

```

```
DISPERSION INTEGRAL METHOD : LINTGL = T
PLOT OF ABS(DETERMINANT) : LMAP = F
NUMBER OF TRANS. RADIAL MODES : NDISP = 0
NUMBER OF STEPS IN SPREAD : NSTPS = 1
STARTING TUNE SPREAD : SPRDO = 0.0000
STEP IN REAL TUNE(=X) SEARCH : EX = 0.10000
STEP IN IMAG TUNE(=Y) SEARCH : EY = 0.10000E-01
CRITERION FOR CONVERGENCE OF F : FEPS = 0.10000E-09
CRITERION FOR CONVERGENCE OF Z : ZEPS = 0.0000
MAXIMUM DIFFERENCE OF X : DXMAX = 0.50000
MINIMUM DISTANCE BETWEEN TUNES : ESPC = 0.10000E-02
MAXIMUM CHANGE IN X : CXMAX = 0.50000
```

*****>>> BUNCH LENGTH VARIES WITH BUNCH CURRENT AS FOLLOWS <<<*****

| | | | | | | | | | | | |
|-------------------|---|---------|---------|---------|---------|---------|---------|---------|---------|---------|---------|
| Current (mA) | / | 4.000 | 8.000 | 12.000 | 16.000 | 20.000 | 24.000 | 28.000 | 32.000 | 36.000 | 40.000 |
| Bunch Length (cm) | / | 4.964 | 6.254 | 7.159 | 7.880 | 8.488 | 9.020 | 9.495 | 9.928 | 10.325 | 10.694 |
| Current (mA) | / | 44.000 | 48.000 | 52.000 | 56.000 | 60.000 | 64.000 | 68.000 | 72.000 | 76.000 | 80.000 |
| Bunch Length (cm) | / | 11.039 | 11.364 | 11.672 | 11.963 | 12.242 | 12.508 | 12.763 | 13.009 | 13.245 | 13.474 |
| Current (mA) | / | 84.000 | 88.000 | 92.000 | 96.000 | 100.000 | 104.000 | 108.000 | 112.000 | 116.000 | 120.000 |
| Bunch Length (cm) | / | 13.695 | 13.909 | 14.116 | 14.318 | 14.514 | 14.705 | 14.891 | 15.073 | 15.250 | 15.424 |
| Current (mA) | / | 124.000 | 128.000 | 132.000 | 136.000 | 140.000 | 144.000 | 148.000 | 152.000 | 156.000 | 160.000 |
| Bunch Length (cm) | / | 15.593 | 15.759 | 15.922 | 16.081 | 16.237 | 16.390 | 16.540 | 16.688 | 16.833 | 16.976 |
| Current (mA) | / | 164.000 | 168.000 | 172.000 | 176.000 | 180.000 | 184.000 | 188.000 | 192.000 | 196.000 | 200.000 |
| Bunch Length (cm) | / | 17.116 | 17.254 | 17.390 | 17.524 | 17.656 | 17.786 | 17.914 | 18.040 | 18.164 | 18.287 |
| Current (mA) | / | 204.000 | 208.000 | 212.000 | 216.000 | 220.000 | 224.000 | 228.000 | 232.000 | 236.000 | 240.000 |
| Bunch Length (cm) | / | 18.408 | 18.527 | 18.645 | 18.762 | 18.877 | 18.991 | 19.103 | 19.214 | 19.324 | 19.433 |
| Current (mA) | / | 244.000 | 248.000 | 252.000 | 256.000 | 260.000 | 264.000 | 268.000 | 272.000 | 276.000 | 280.000 |
| Bunch Length (cm) | / | 19.540 | 19.646 | 19.751 | 19.855 | 19.958 | 20.060 | 20.161 | 20.261 | 20.359 | 20.457 |
| Current (mA) | / | 284.000 | 288.000 | 292.000 | 296.000 | 300.000 | 304.000 | 308.000 | 312.000 | 316.000 | 320.000 |
| Bunch Length (cm) | / | 20.554 | 20.650 | 20.745 | 20.840 | 20.933 | 21.026 | 21.118 | 21.209 | 21.299 | 21.388 |
| Current (mA) | / | 324.000 | 328.000 | 332.000 | 336.000 | 340.000 | 344.000 | 348.000 | 352.000 | 356.000 | 360.000 |
| Bunch Length (cm) | / | 21.477 | 21.565 | 21.652 | 21.739 | 21.825 | 21.910 | 21.995 | 22.079 | 22.162 | 22.245 |
| Current (mA) | / | 364.000 | 368.000 | 372.000 | 376.000 | 380.000 | 384.000 | 388.000 | 392.000 | 396.000 | 0.000 |
| Bunch Length (cm) | / | 22.327 | 22.408 | 22.489 | 22.570 | 22.649 | 22.729 | 22.807 | 22.885 | 22.963 | 0.000 |

1

*****>>> EIGEN VALUES (Nu-Nux)/Nus VS. BUNCH CURRENT <<<*****

BETATRON TUNE SPREAD = 0.0000

| | | | | | | |
|-------------------|-----------------------|-------------------|-------------------|-------------------|-------------------|---------|
| Current (mA) | / | 4.0000 | 8.0000 | 12.0000 | 16.0000 | 20.0000 |
| Bunch length (cm) | / | 4.9638 | 6.2540 | 7.1590 | 7.8795 | 8.4880 |
| Synchrotron tune | / | 0.0079 | 0.0079 | 0.0079 | 0.0079 | 0.0079 |
| (Nu-Nux)/Nus ... | (REAL : IMAGINARY) | | | | | |
| | -2.00 : 0.158E-12 | -2.00 : 0.181E-11 | -2.01 : -.134E-11 | -2.01 : -.383E-11 | -2.02 : 0.377E-12 | |
| | 0.990 : -.872E-12 | 0.976 : 0.137E-10 | -1.04 : 0.836E-11 | 0.951 : 0.419E-11 | 0.940 : 0.114E-09 | |
| | -1.01 : -.192E-11 | -1.02 : 0.122E-10 | -.188 : 0.874E-11 | -.231 : -.245E-11 | -.271 : -.239E-10 | |
| | -.788E-01 : -.113E-10 | -.138 : 0.717E-11 | 0.962 : 0.103E-10 | -1.05 : 0.125E-10 | -1.06 : 0.138E-09 | |
| Current (mA) | / | 24.0000 | 28.0000 | 32.0000 | 36.0000 | 40.0000 |
| Bunch length (cm) | / | 9.0198 | 9.4954 | 9.9276 | 10.3251 | 10.6942 |
| Synchrotron tune | / | 0.0079 | 0.0079 | 0.0079 | 0.0079 | 0.0079 |
| (Nu-Nux)/Nus ... | (REAL : IMAGINARY) | | | | | |

| | | | | | | | | | | |
|-------------------|--------------------|------------|----------|------------|----------|------------|-------|------------|-------|------------|
| | | | | | 2 | | | | | |
| | -2.02 | :0.926E-12 | -2.03 | :0.183E-11 | -2.03 | :-.519E-11 | -2.03 | :-.926E-11 | -2.04 | :0.141E-11 |
| | 0.931 | :0.123E-09 | 0.922 | :0.145E-09 | 0.914 | :-.145E-10 | 0.906 | :-.144E-10 | 0.899 | :0.534E-10 |
| | -.308 | :-.406E-10 | -.343 | :-.716E-10 | -.377 | :-.363E-10 | -.408 | :-.374E-10 | -.439 | :-.421E-10 |
| | -1.07 | :0.151E-09 | -1.08 | :0.139E-09 | -1.09 | :-.549E-10 | -1.10 | :-.527E-10 | -1.10 | :0.278E-10 |
| Current (mA) | / | 44.0000 | 48.0000 | 52.0000 | 56.0000 | 60.0000 | | | | |
| Bunch length (cm) | / | 11.0394 | 11.3643 | 11.6716 | 11.9635 | 12.2418 | | | | |
| Synchrotron tune | / | 0.0079 | 0.0079 | 0.0079 | 0.0079 | 0.0079 | | | | |
| (Nu-Nux)/Nus ... | (REAL : IMAGINARY) | | | | | | | | | |
| | -2.04 | :0.764E-11 | -2.04 | :0.819E-11 | -2.05 | :0.548E-10 | -2.05 | :0.562E-10 | -2.05 | :0.575E-10 |
| | 0.892 | :0.532E-10 | 0.885 | :0.538E-10 | 0.879 | :0.545E-10 | 0.872 | :0.551E-10 | 0.867 | :0.556E-10 |
| | -.468 | :-.415E-10 | -.497 | :-.408E-10 | -.524 | :-.396E-10 | -.551 | :-.382E-10 | -.577 | :-.365E-10 |
| | -1.11 | :0.203E-10 | -1.12 | :0.175E-10 | -1.13 | :0.143E-10 | -1.14 | :0.110E-10 | -1.14 | :0.749E-11 |
| Current (mA) | / | 64.0000 | 68.0000 | 72.0000 | 76.0000 | 80.0000 | | | | |
| Bunch length (cm) | / | 12.5080 | 12.7633 | 13.0088 | 13.2454 | 13.4738 | | | | |
| Synchrotron tune | / | 0.0079 | 0.0079 | 0.0079 | 0.0079 | 0.0079 | | | | |
| (Nu-Nux)/Nus ... | (REAL : IMAGINARY) | | | | | | | | | |
| | -2.06 | :0.588E-10 | -2.06 | :0.601E-10 | -2.06 | :0.614E-10 | -2.07 | :0.626E-10 | -2.07 | :0.638E-10 |
| | 0.861 | :0.562E-10 | 0.855 | :0.567E-10 | 0.850 | :0.572E-10 | 0.845 | :0.576E-10 | 0.839 | :0.581E-10 |
| | -.603 | :-.345E-10 | -.628 | :-.321E-10 | -.653 | :-.294E-10 | -.677 | :-.262E-10 | -.700 | :-.227E-10 |
| | -1.15 | :0.368E-11 | -1.16 | :-.407E-12 | -1.16 | :-.479E-11 | -1.17 | :-.950E-11 | -1.18 | :-.145E-10 |
| Current (mA) | / | 84.0000 | 88.0000 | 92.0000 | 96.0000 | 100.0000 | | | | |
| Bunch length (cm) | / | 13.6948 | 13.9088 | 14.1164 | 14.3181 | 14.5142 | | | | |
| Synchrotron tune | / | 0.0079 | 0.0079 | 0.0079 | 0.0079 | 0.0079 | | | | |
| (Nu-Nux)/Nus ... | (REAL : IMAGINARY) | | | | | | | | | |
| | -2.07 | :0.650E-10 | -2.08 | :0.662E-10 | -2.08 | :0.673E-10 | -2.08 | :0.685E-10 | 0.816 | :0.599E-10 |
| | 0.834 | :0.585E-10 | 0.830 | :0.589E-10 | 0.825 | :0.592E-10 | 0.820 | :0.596E-10 | -2.08 | :0.696E-10 |
| | -.724 | :-.188E-10 | -.746 | :-.144E-10 | -.769 | :-.950E-11 | -.791 | :-.411E-11 | -.813 | :0.184E-11 |
| | -1.18 | :-.200E-10 | -1.19 | :-.258E-10 | -1.20 | :-.320E-10 | -1.20 | :-.387E-10 | -1.21 | :-.459E-10 |
| Current (mA) | / | 104.0000 | 108.0000 | 112.0000 | 116.0000 | 120.0000 | | | | |
| Bunch length (cm) | / | 14.7052 | 14.8914 | 15.0730 | 15.2504 | 15.4237 | | | | |
| Synchrotron tune | / | 0.0079 | 0.0079 | 0.0079 | 0.0079 | 0.0079 | | | | |
| (Nu-Nux)/Nus ... | (REAL : IMAGINARY) | | | | | | | | | |
| | 0.811 | :0.603E-10 | 0.807 | :0.606E-10 | 0.803 | :0.609E-10 | 0.798 | :0.611E-10 | 0.794 | :0.614E-10 |
| | -2.09 | :0.706E-10 | -2.09 | :0.717E-10 | -2.09 | :0.727E-10 | -2.10 | :0.737E-10 | -2.10 | :0.747E-10 |
| | -.834 | :0.840E-11 | -.856 | :0.156E-10 | -.877 | :0.236E-10 | -.898 | :0.324E-10 | -.918 | :0.422E-10 |
| | -1.21 | :-.537E-10 | -1.22 | :-.621E-10 | -1.23 | :-.712E-10 | -1.23 | :-.811E-10 | -1.24 | :-.919E-10 |
| Current (mA) | / | 124.0000 | 128.0000 | 132.0000 | 136.0000 | 140.0000 | | | | |
| Bunch length (cm) | / | 15.5932 | 15.7591 | 15.9216 | 16.0808 | 16.2369 | | | | |
| Synchrotron tune | / | 0.0079 | 0.0079 | 0.0079 | 0.0079 | 0.0079 | | | | |
| (Nu-Nux)/Nus ... | (REAL : IMAGINARY) | | | | | | | | | |
| | 0.790 | :0.616E-10 | 0.786 | :0.619E-10 | 0.782 | :0.621E-10 | 0.779 | :0.623E-10 | 0.775 | :0.625E-10 |
| | -2.10 | :0.757E-10 | -2.11 | :0.766E-10 | -2.11 | :0.775E-10 | -2.11 | :0.784E-10 | -2.12 | :0.792E-10 |
| | -.939 | :0.530E-10 | -.959 | :0.650E-10 | -.979 | :0.785E-10 | -.999 | :0.936E-10 | -1.02 | :0.111E-09 |
| | -1.24 | :-.104E-09 | -1.25 | :-.117E-09 | -1.25 | :-.131E-09 | -1.26 | :-.147E-09 | -1.26 | :-.165E-09 |
| Current (mA) | / | 144.0000 | 148.0000 | 152.0000 | 156.0000 | 160.0000 | | | | |

| | | | | | | |
|-------------------|---|--------------------|------------------|----------------------|------------------|------------------|
| Bunch length (cm) | / | 16.3901 | 16.5405 | 16.6882 ² | 16.8333 | 16.9760 |
| Synchrotron tune | / | 0.0079 | 0.0079 | 0.0079 | 0.0079 | 0.0079 |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | |
| | | 0.771 :0.627E-10 | 0.767 :0.629E-10 | 0.764 :0.631E-10 | 0.760 :0.632E-10 | 0.757 :0.634E-10 |
| | | -2.12 :0.800E-10 | -2.12 :0.808E-10 | -2.13 :0.815E-10 | -2.13 :0.822E-10 | -2.13 :0.828E-10 |
| | | -1.04 :0.130E-09 | -1.06 :0.153E-09 | -1.08 :0.179E-09 | -1.10 :0.211E-09 | -1.12 :0.249E-09 |
| | | -1.27 :-.185E-09 | -1.27 :-.209E-09 | -1.27 :-.236E-09 | -1.28 :-.268E-09 | -1.28 :-.307E-09 |
| Current (mA) | / | 164.0000 | 168.0000 | 172.0000 | 176.0000 | 180.0000 |
| Bunch length (cm) | / | 17.1163 | 17.2543 | 17.3902 | 17.5240 | 17.6557 |
| Synchrotron tune | / | 0.0079 | 0.0079 | 0.0079 | 0.0079 | 0.0079 |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | |
| | | 0.753 :0.635E-10 | 0.750 :0.637E-10 | 0.747 :0.638E-10 | 0.743 :-.767E-09 | 0.740 :-.464E-08 |
| | | -2.14 :0.834E-10 | -2.14 :0.839E-10 | -2.14 :0.844E-10 | -2.15 :-.167E-08 | -2.15 :-.257E-09 |
| | | -1.14 :0.298E-09 | -1.16 :0.363E-09 | -1.18 :0.457E-09 | -1.20 :-.419E-08 | -1.23 :-.146E-07 |
| | | -1.28 :-.356E-09 | -1.29 :-.422E-09 | -1.29 :-.516E-09 | -1.29 :0.491E-08 | -1.28 :0.162E-07 |
| Current (mA) | / | 184.0000 | 188.0000 | 192.0000 | 196.0000 | 200.0000 |
| Bunch length (cm) | / | 17.7855 | 17.9135 | 18.0397 | 18.1641 | 18.2868 |
| Synchrotron tune | / | 0.0079 | 0.0079 | 0.0079 | 0.0079 | 0.0079 |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | |
| | | 0.737 :0.886E-08 | 0.734 :-.180E-07 | 0.731 :0.227E-08 | 0.728 :-.177E-07 | 0.725 :-.507E-08 |
| | | -2.15 :0.458E-09 | -2.16 :0.105E-07 | -2.16 :-.972E-08 | -2.16 :0.102E-07 | -2.17 :-.983E-08 |
| | | -1.27 :0.123E-01 | -1.28 :0.323E-01 | -1.29 :0.432E-01 | -1.30 :0.513E-01 | -1.31 :0.577E-01 |
| | | -1.27 :-.123E-01 | -1.28 :-.323E-01 | -1.29 :-.432E-01 | -1.30 :-.513E-01 | -1.31 :-.577E-01 |
| Current (mA) | / | 204.0000 | 208.0000 | 212.0000 | 216.0000 | 220.0000 |
| Bunch length (cm) | / | 18.4079 | 18.5275 | 18.6455 | 18.7620 | 18.8771 |
| Synchrotron tune | / | 0.0079 | 0.0079 | 0.0079 | 0.0079 | 0.0079 |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | |
| | | 0.722 :-.540E-08 | 0.719 :0.142E-07 | 0.716 :0.177E-07 | 0.713 :-.116E-07 | 0.710 :-.421E-08 |
| | | -2.17 :-.950E-08 | -2.18 :0.156E-07 | -2.18 :-.177E-07 | -2.18 :-.335E-08 | -2.19 :0.421E-08 |
| | | -1.32 :0.631E-01 | -1.33 :0.676E-01 | -1.34 :0.715E-01 | -1.35 :0.748E-01 | -1.36 :0.777E-01 |
| | | -1.32 :-.631E-01 | -1.33 :-.676E-01 | -1.34 :-.715E-01 | -1.35 :-.748E-01 | -1.36 :-.777E-01 |
| Current (mA) | / | 224.0000 | 228.0000 | 232.0000 | 236.0000 | 240.0000 |
| Bunch length (cm) | / | 18.9908 | 19.1032 | 19.2143 | 19.3241 | 19.4326 |
| Synchrotron tune | / | 0.0079 | 0.0079 | 0.0079 | 0.0079 | 0.0079 |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | |
| | | 0.707 :-.198E-07 | 0.704 :-.294E-08 | 0.701 :-.133E-07 | 0.699 :0.380E-07 | 0.696 :0.171E-07 |
| | | -2.19 :0.198E-07 | -2.20 :-.418E-07 | -2.20 :-.157E-08 | -2.20 :-.819E-08 | -2.21 :-.320E-07 |
| | | -1.37 :0.801E-01 | -1.38 :0.823E-01 | -1.39 :0.841E-01 | -1.40 :0.856E-01 | -1.41 :0.869E-01 |
| | | -1.37 :-.801E-01 | -1.38 :-.823E-01 | -1.39 :-.841E-01 | -1.40 :-.856E-01 | -1.41 :-.869E-01 |
| Current (mA) | / | 244.0000 | 248.0000 | 252.0000 | 256.0000 | 260.0000 |
| Bunch length (cm) | / | 19.5400 | 19.6462 | 19.7513 | 19.8552 | 19.9581 |
| Synchrotron tune | / | 0.0079 | 0.0079 | 0.0079 | 0.0079 | 0.0079 |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | |
| | | 0.693 :-.156E-08 | 0.691 :-.158E-07 | 0.688 :0.562E-08 | 0.686 :0.121E-07 | 0.683 :-.663E-08 |
| | | -2.21 :0.156E-08 | -2.22 :-.140E-07 | -2.22 :0.242E-07 | -2.23 :-.419E-07 | -2.23 :0.663E-08 |
| | | -1.42 :0.880E-01 | -1.43 :0.888E-01 | -1.44 :0.895E-01 | -1.45 :0.899E-01 | -1.45 :0.902E-01 |

| | | | | | | | | | | | |
|-------------------|---|--------------------|------------|----------|------------|----------|----------------------------|----------|------------|----------|------------|
| | | -1.42 | :-.880E-01 | -1.43 | :-.888E-01 | -1.44 | ² :-.895E-01 | -1.45 | :-.899E-01 | -1.45 | :-.902E-01 |
| Current (mA) | / | 264.0000 | | 268.0000 | | 272.0000 | | 276.0000 | | 280.0000 | |
| Bunch length (cm) | / | 20.0599 | | 20.1607 | | 20.2605 | | 20.3594 | | 20.4572 | |
| Synchrotron tune | / | 0.0079 | | 0.0079 | | 0.0079 | | 0.0079 | | 0.0079 | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | | |
| | | 0.680 | :-.978E-09 | 0.678 | :-.509E-09 | 0.675 | :-.509E-07 | 0.673 | :-.173E-07 | 0.671 | :0.108E-07 |
| | | -2.24 | :0.159E-07 | -2.24 | :0.154E-07 | -2.25 | :0.211E-07 | -2.25 | :0.173E-07 | -2.26 | :0.190E-07 |
| | | -1.46 | :0.904E-01 | -1.47 | :0.904E-01 | -1.48 | :-.902E-01 | -1.49 | :-.899E-01 | -1.50 | :-.895E-01 |
| | | -1.46 | :-.904E-01 | -1.47 | :-.904E-01 | -1.48 | :0.902E-01 | -1.49 | :0.899E-01 | -1.50 | :0.895E-01 |
| Current (mA) | / | 284.0000 | | 288.0000 | | 292.0000 | | 296.0000 | | 300.0000 | |
| Bunch length (cm) | / | 20.5542 | | 20.6503 | | 20.7454 | | 20.8397 | | 20.9332 | |
| Synchrotron tune | / | 0.0079 | | 0.0079 | | 0.0079 | | 0.0079 | | 0.0079 | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | | |
| | | 0.668 | :0.178E-07 | 0.666 | :0.363E-07 | 0.663 | :0.347E-07 | 0.661 | :0.218E-07 | 0.659 | :0.139E-07 |
| | | -2.26 | :-.327E-07 | -2.27 | :-.214E-07 | -2.27 | :-.490E-08 | -2.28 | :-.688E-08 | -2.29 | :-.139E-07 |
| | | -1.51 | :-.890E-01 | -1.52 | :-.884E-01 | -1.52 | :-.876E-01 | -1.53 | :-.868E-01 | -1.54 | :-.858E-01 |
| | | -1.51 | :0.890E-01 | -1.52 | :0.884E-01 | -1.52 | :0.876E-01 | -1.53 | :0.868E-01 | -1.54 | :0.858E-01 |
| Current (mA) | / | 304.0000 | | 308.0000 | | 312.0000 | | 316.0000 | | 320.0000 | |
| Bunch length (cm) | / | 21.0258 | | 21.1176 | | 21.2086 | | 21.2989 | | 21.3884 | |
| Synchrotron tune | / | 0.0079 | | 0.0079 | | 0.0079 | | 0.0079 | | 0.0079 | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | | |
| | | 0.656 | :0.109E-07 | 0.654 | :0.516E-08 | 0.652 | :-.107E-08 | 0.650 | :-.131E-07 | 0.647 | :-.379E-08 |
| | | -2.29 | :-.109E-07 | -2.30 | :-.201E-07 | -2.30 | :0.107E-08 | -2.31 | :-.180E-08 | -2.32 | :0.112E-07 |
| | | -1.55 | :-.848E-01 | -1.56 | :-.837E-01 | -1.56 | :-.825E-01 | -1.57 | :-.813E-01 | -1.58 | :-.800E-01 |
| | | -1.55 | :0.848E-01 | -1.56 | :0.837E-01 | -1.56 | :0.825E-01 | -1.57 | :0.813E-01 | -1.58 | :0.800E-01 |
| Current (mA) | / | 324.0000 | | 328.0000 | | 332.0000 | | 336.0000 | | 340.0000 | |
| Bunch length (cm) | / | 21.4771 | | 21.5652 | | 21.6525 | | 21.7391 | | 21.8250 | |
| Synchrotron tune | / | 0.0079 | | 0.0079 | | 0.0079 | | 0.0079 | | 0.0079 | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | | |
| | | 0.645 | :-.748E-08 | 0.643 | :-.263E-07 | 0.641 | :0.108E-07 | 0.639 | :0.188E-07 | 0.637 | :-.604E-08 |
| | | -2.32 | :-.149E-07 | -2.33 | :0.393E-08 | -2.34 | :-.108E-07 | -2.34 | :0.351E-08 | -2.35 | :-.141E-08 |
| | | -1.59 | :-.786E-01 | -1.59 | :-.771E-01 | -1.60 | :-.756E-01 | -1.61 | :-.740E-01 | -1.62 | :-.724E-01 |
| | | -1.59 | :0.786E-01 | -1.59 | :0.771E-01 | -1.60 | :0.756E-01 | -1.61 | :0.740E-01 | -1.62 | :0.724E-01 |
| Current (mA) | / | 344.0000 | | 348.0000 | | 352.0000 | | 356.0000 | | 360.0000 | |
| Bunch length (cm) | / | 21.9103 | | 21.9948 | | 22.0788 | | 22.1621 | | 22.2448 | |
| Synchrotron tune | / | 0.0079 | | 0.0079 | | 0.0079 | | 0.0079 | | 0.0079 | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | | |
| | | 0.635 | :-.110E-07 | 0.632 | :0.148E-07 | 0.630 | :-.810E-08 | 0.628 | :0.248E-07 | 0.626 | :-.205E-08 |
| | | -2.36 | :0.353E-08 | -2.36 | :-.730E-08 | -2.37 | :-.143E-07 | -2.38 | :-.986E-08 | -2.38 | :0.205E-08 |
| | | -1.62 | :-.707E-01 | -1.63 | :-.690E-01 | -1.64 | :-.673E-01 | -1.64 | :-.655E-01 | -1.65 | :-.636E-01 |
| | | -1.62 | :0.707E-01 | -1.63 | :0.690E-01 | -1.64 | :0.673E-01 | -1.64 | :0.655E-01 | -1.65 | :0.636E-01 |
| Current (mA) | / | 364.0000 | | 368.0000 | | 372.0000 | | 376.0000 | | 380.0000 | |
| Bunch length (cm) | / | 22.3269 | | 22.4084 | | 22.4893 | | 22.5696 | | 22.6494 | |
| Synchrotron tune | / | 0.0079 | | 0.0079 | | 0.0079 | | 0.0079 | | 0.0079 | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | | |

| | | | | | | | | | | |
|-------------------|-------|--------------------|----------|------------|----------|------------|-------|------------|-------|------------|
| | | | | | 2 | | | | | |
| | 0.624 | :0.201E-08 | 0.622 | :0.155E-08 | 0.620 | :-.802E-08 | 0.618 | :0.372E-08 | 0.616 | :-.927E-08 |
| | -2.39 | :0.315E-07 | -2.40 | :0.208E-07 | -2.41 | :0.567E-09 | -2.42 | :-.744E-08 | -2.42 | :0.554E-08 |
| | -1.66 | :-.618E-01 | -1.66 | :-.599E-01 | -1.67 | :-.579E-01 | -1.68 | :-.560E-01 | -1.68 | :-.540E-01 |
| | -1.66 | :0.618E-01 | -1.66 | :0.599E-01 | -1.67 | :0.579E-01 | -1.68 | :0.560E-01 | -1.68 | :0.540E-01 |
| Current (mA) | / | 384.0000 | 388.0000 | 392.0000 | 396.0000 | 400.0000 | | | | |
| Bunch length (cm) | / | 22.7285 | 22.8072 | 22.8853 | 22.9629 | 23.0399 | | | | |
| Synchrotron tune | / | 0.0079 | 0.0079 | 0.0079 | 0.0079 | 0.0079 | | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | |
| | 0.614 | :0.483E-08 | 0.613 | :-.170E-07 | 0.611 | :0.547E-08 | 0.609 | :-.650E-08 | 0.00 | : 0.00 |
| | -2.43 | :0.263E-08 | -2.44 | :0.958E-08 | -2.45 | :0.199E-08 | -2.46 | :-.468E-08 | 0.00 | : 0.00 |
| | -1.69 | :-.520E-01 | -1.69 | :-.499E-01 | -1.70 | :-.479E-01 | -1.71 | :-.458E-01 | 0.00 | : 0.00 |
| | -1.69 | :0.520E-01 | -1.69 | :0.499E-01 | -1.70 | :0.479E-01 | -1.71 | :0.458E-01 | 0.00 | : 0.00 |

1
 *****>>> EIGEN VALUES (Nu-Nux)/Nus VS. BUNCH CURRENT <<<*****

BETATRON TUNE SPREAD = 0.50000E-03

| | | | | | | |
|-------------------|--------|--------------------|--------|------------|---------|------------|
| Current (mA) | / | 4.0000 | 8.0000 | 12.0000 | 16.0000 | 20.0000 |
| Bunch length (cm) | / | 4.9638 | 6.2540 | 7.1590 | 7.8795 | 8.4880 |
| Synchrotron tune | / | 0.0079 | 0.0079 | 0.0079 | 0.0079 | 0.0079 |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | |
| | -2.03 | :-.996E-10 | -2.03 | :0.389E-10 | -2.03 | :-.449E-10 |
| | 0.812 | :-.584E-10 | 0.740 | :0.547E-10 | -1.05 | :0.220E-09 |
| | -1.04 | :0.912E-10 | -1.05 | :0.134E-09 | -1.514 | :0.187E-09 |
| | -1.312 | :-.209E-09 | -1.439 | :0.143E-09 | 0.697 | :-.272E-10 |

| | | | | | | |
|-------------------|--------|--------------------|---------|------------|---------|------------|
| Current (mA) | / | 24.0000 | 28.0000 | 32.0000 | 36.0000 | 40.0000 |
| Bunch length (cm) | / | 9.0198 | 9.4954 | 9.9276 | 10.3251 | 10.6942 |
| Synchrotron tune | / | 0.0079 | 0.0079 | 0.0079 | 0.0079 | 0.0079 |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | |
| | -2.03 | :0.243E-10 | -2.03 | :0.808E-10 | -2.03 | :-.320E-10 |
| | 0.628 | :0.295E-10 | 0.613 | :0.294E-10 | 0.600 | :-.517E-10 |
| | -1.655 | :0.176E-09 | -1.691 | :0.566E-10 | -1.725 | :0.861E-10 |
| | -1.04 | :0.207E-10 | -1.03 | :0.206E-09 | -1.02 | :0.599E-10 |

| | | | | | | |
|-------------------|--------|--------------------|---------|------------|---------|------------|
| Current (mA) | / | 44.0000 | 48.0000 | 52.0000 | 56.0000 | 60.0000 |
| Bunch length (cm) | / | 11.0394 | 11.3643 | 11.6716 | 11.9635 | 12.2418 |
| Synchrotron tune | / | 0.0079 | 0.0079 | 0.0079 | 0.0079 | 0.0079 |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | |
| | -2.03 | :-.281E-10 | -2.03 | :-.672E-10 | -2.03 | :-.118E-09 |
| | 0.569 | :0.248E-10 | 0.560 | :0.383E-10 | 0.552 | :0.116E-09 |
| | -1.813 | :0.406E-09 | -1.839 | :0.831E-09 | -1.865 | :0.898E-09 |
| | -1.01 | :-.311E-09 | -1.839 | :-.343E-09 | -1.865 | :-.371E-09 |

| | | | | | | |
|-------------------|---|--------------------|---------|---------|---------|---------|
| Current (mA) | / | 64.0000 | 68.0000 | 72.0000 | 76.0000 | 80.0000 |
| Bunch length (cm) | / | 12.5080 | 12.7633 | 13.0088 | 13.2454 | 13.4738 |
| Synchrotron tune | / | 0.0079 | 0.0079 | 0.0079 | 0.0079 | 0.0079 |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | |

| | | | | | | | | | | |
|-------------------|-------|--------------------|----------|------------|----------|------------|-------|------------|-------|------------|
| | | | | | 2 | | | | | |
| | -2.02 | :0.562E-10 | -2.02 | :-.782E-10 | -2.02 | :-.109E-09 | -2.02 | :-.370E-10 | -2.02 | :0.134E-09 |
| | 0.530 | :0.217E-11 | 0.523 | :0.144E-10 | 0.517 | :0.959E-11 | 0.511 | :0.114E-10 | 0.505 | :0.681E-11 |
| | -.940 | :-.381E-09 | -.964 | :0.984E-10 | -1.00 | :0.295E-09 | -1.01 | :-.108E-09 | -1.03 | :-.395E-09 |
| | -.940 | :-.125E-09 | -.964 | :-.346E-09 | -1.00 | :-.121E-09 | -1.01 | :-.248E-09 | -1.03 | :0.125E-09 |
| Current (mA) | / | 84.0000 | 88.0000 | 92.0000 | 96.0000 | 100.0000 | | | | |
| Bunch length (cm) | / | 13.6948 | 13.9088 | 14.1164 | 14.3181 | 14.5142 | | | | |
| Synchrotron tune | / | 0.0079 | 0.0079 | 0.0079 | 0.0079 | 0.0079 | | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | |
| | -2.02 | :-.510E-10 | -2.02 | :0.606E-10 | -2.02 | :0.749E-10 | -2.02 | :-.698E-10 | 0.479 | :0.167E-10 |
| | 0.499 | :0.359E-10 | 0.494 | :0.158E-10 | 0.489 | :0.198E-10 | 0.484 | :0.305E-11 | -2.02 | :0.660E-10 |
| | -1.05 | :0.382E-09 | -1.07 | :-.390E-09 | -1.09 | :-.245E-09 | -1.11 | :0.241E-09 | -1.13 | :0.904E-10 |
| | -1.05 | :-.650E-10 | -1.07 | :-.292E-09 | -1.09 | :0.229E-09 | -1.11 | :0.171E-09 | -1.13 | :-.162E-09 |
| Current (mA) | / | 104.0000 | 108.0000 | 112.0000 | 116.0000 | 120.0000 | | | | |
| Bunch length (cm) | / | 14.7052 | 14.8914 | 15.0730 | 15.2504 | 15.4237 | | | | |
| Synchrotron tune | / | 0.0079 | 0.0079 | 0.0079 | 0.0079 | 0.0079 | | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | |
| | 0.474 | :0.146E-10 | 0.469 | :0.170E-10 | 0.465 | :0.252E-12 | 0.460 | :0.693E-11 | 0.456 | :0.454E-11 |
| | -2.02 | :0.102E-09 | -2.02 | :-.119E-09 | -2.02 | :-.130E-09 | -2.02 | :0.808E-10 | -2.01 | :0.808E-10 |
| | -1.15 | :0.393E-09 | -1.17 | :0.415E-09 | -1.19 | :-.639E-09 | -1.21 | :-.141E-09 | -1.22 | :0.161E-02 |
| | -1.15 | :0.276E-09 | -1.17 | :-.243E-09 | -1.19 | :-.131E-09 | -1.21 | :0.261E-09 | -1.22 | :-.161E-02 |
| Current (mA) | / | 124.0000 | 128.0000 | 132.0000 | 136.0000 | 140.0000 | | | | |
| Bunch length (cm) | / | 15.5932 | 15.7591 | 15.9216 | 16.0808 | 16.2369 | | | | |
| Synchrotron tune | / | 0.0079 | 0.0079 | 0.0079 | 0.0079 | 0.0079 | | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | |
| | 0.452 | :0.209E-10 | 0.447 | :0.306E-10 | 0.443 | :0.660E-11 | 0.439 | :0.357E-10 | 0.436 | :0.190E-10 |
| | -2.01 | :0.976E-10 | -2.01 | :0.911E-10 | -2.01 | :0.117E-09 | -2.01 | :-.224E-10 | -2.01 | :0.992E-10 |
| | -1.24 | :0.340E-02 | -1.26 | :-.511E-02 | -1.28 | :0.154E-01 | -1.29 | :-.163E-01 | -1.31 | :0.171E-01 |
| | -1.24 | :-.340E-02 | -1.26 | :0.511E-02 | -1.28 | :-.154E-01 | -1.29 | :0.163E-01 | -1.31 | :-.171E-01 |
| Current (mA) | / | 144.0000 | 148.0000 | 152.0000 | 156.0000 | 160.0000 | | | | |
| Bunch length (cm) | / | 16.3901 | 16.5405 | 16.6882 | 16.8333 | 16.9760 | | | | |
| Synchrotron tune | / | 0.0079 | 0.0079 | 0.0079 | 0.0079 | 0.0079 | | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | |
| | 0.432 | :0.151E-10 | 0.428 | :0.439E-11 | 0.424 | :0.122E-10 | 0.421 | :0.143E-10 | 0.417 | :0.109E-11 |
| | -2.01 | :0.122E-10 | -2.01 | :0.453E-10 | -2.01 | :0.101E-09 | -2.01 | :-.883E-10 | -2.01 | :-.883E-10 |
| | -1.33 | :-.180E-01 | -1.35 | :0.189E-01 | -1.36 | :-.198E-01 | -1.38 | :0.208E-01 | -1.39 | :-.218E-01 |
| | -1.33 | :0.180E-01 | -1.35 | :-.189E-01 | -1.36 | :0.198E-01 | -1.38 | :-.208E-01 | -1.39 | :0.218E-01 |
| Current (mA) | / | 164.0000 | 168.0000 | 172.0000 | 176.0000 | 180.0000 | | | | |
| Bunch length (cm) | / | 17.1163 | 17.2543 | 17.3902 | 17.5240 | 17.6557 | | | | |
| Synchrotron tune | / | 0.0079 | 0.0079 | 0.0079 | 0.0079 | 0.0079 | | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | |
| | 0.414 | :0.114E-10 | 0.410 | :0.101E-10 | 0.407 | :0.120E-10 | 0.404 | :0.285E-11 | 0.400 | :0.440E-12 |
| | -2.01 | :-.883E-10 | -2.01 | :-.883E-10 | -2.01 | :-.883E-10 | -2.01 | :-.883E-10 | -2.01 | :-.883E-10 |
| | -1.41 | :0.228E-01 | -1.43 | :-.238E-01 | -1.44 | :0.249E-01 | -1.46 | :-.261E-01 | -1.47 | :0.272E-01 |
| | -1.41 | :-.228E-01 | -1.43 | :0.238E-01 | -1.44 | :-.249E-01 | -1.46 | :0.261E-01 | -1.47 | :-.272E-01 |
| Current (mA) | / | 184.0000 | 188.0000 | 192.0000 | 196.0000 | 200.0000 | | | | |

| | | | | | | | | | | |
|-------------------|---|--------------------|------------------|------------------|------------------|------------------|--|--|--|--|
| | | | | | | | | | | |
| | | | | | | | | | | |
| | | | | | | | | | | |
| Bunch length (cm) | / | 17.7855 | 17.9135 | 18.0397 | 18.1641 | 18.2868 | | | | |
| Synchrotron tune | / | 0.0079 | 0.0079 | 0.0079 | 0.0079 | 0.0079 | | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | |
| | | 0.397 :0.175E-12 | 0.394 :0.720E-11 | 0.391 :0.290E-10 | 0.388 :0.356E-11 | 0.385 :0.203E-10 | | | | |
| | | -2.01 :-883E-10 | -2.01 :-883E-10 | -1.52 :0.310E-01 | -2.29 :0.102E-07 | -2.29 :0.102E-07 | | | | |
| | | -1.49 :-285E-01 | -1.50 :0.297E-01 | -1.52 :-310E-01 | -1.53 :0.324E-01 | -1.55 :-337E-01 | | | | |
| | | -1.49 :0.285E-01 | -1.50 :-297E-01 | -1.52 :0.310E-01 | -1.53 :-324E-01 | -1.55 :0.337E-01 | | | | |
| | | | | | | | | | | |
| Current (mA) | / | 204.0000 | 208.0000 | 212.0000 | 216.0000 | 220.0000 | | | | |
| Bunch length (cm) | / | 18.4079 | 18.5275 | 18.6455 | 18.7620 | 18.8771 | | | | |
| Synchrotron tune | / | 0.0079 | 0.0079 | 0.0079 | 0.0079 | 0.0079 | | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | |
| | | 0.382 :0.171E-10 | 0.379 :0.340E-12 | 0.376 :0.115E-10 | 0.373 :0.210E-10 | 0.371 :0.406E-11 | | | | |
| | | -2.29 :0.102E-07 | -2.29 :0.102E-07 | -2.29 :0.102E-07 | -2.29 :0.102E-07 | -2.29 :0.102E-07 | | | | |
| | | -1.56 :0.351E-01 | -1.57 :-365E-01 | -1.59 :0.380E-01 | -1.60 :-394E-01 | -1.61 :0.408E-01 | | | | |
| | | -1.56 :-351E-01 | -1.57 :0.365E-01 | -1.59 :-380E-01 | -1.60 :0.394E-01 | -1.61 :-408E-01 | | | | |
| | | | | | | | | | | |
| Current (mA) | / | 224.0000 | 228.0000 | 232.0000 | 236.0000 | 240.0000 | | | | |
| Bunch length (cm) | / | 18.9908 | 19.1032 | 19.2143 | 19.3241 | 19.4326 | | | | |
| Synchrotron tune | / | 0.0079 | 0.0079 | 0.0079 | 0.0079 | 0.0079 | | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | |
| | | 0.368 :0.108E-10 | 0.365 :0.543E-11 | 0.362 :0.145E-11 | 0.360 :0.208E-11 | 0.357 :0.292E-10 | | | | |
| | | -2.29 :0.102E-07 | -2.29 :0.102E-07 | -2.29 :0.102E-07 | -2.29 :0.102E-07 | -2.29 :0.102E-07 | | | | |
| | | -1.63 :-421E-01 | -1.64 :0.435E-01 | -1.65 :-448E-01 | -1.66 :0.460E-01 | -1.67 :-471E-01 | | | | |
| | | -1.63 :0.421E-01 | -1.64 :-435E-01 | -1.65 :0.448E-01 | -1.66 :-460E-01 | -1.67 :0.471E-01 | | | | |
| | | | | | | | | | | |
| Current (mA) | / | 244.0000 | 248.0000 | 252.0000 | 256.0000 | 260.0000 | | | | |
| Bunch length (cm) | / | 19.5400 | 19.6462 | 19.7513 | 19.8552 | 19.9581 | | | | |
| Synchrotron tune | / | 0.0079 | 0.0079 | 0.0079 | 0.0079 | 0.0079 | | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | |
| | | 0.355 :0.138E-10 | 0.352 :0.197E-10 | 0.350 :0.278E-11 | 0.347 :0.575E-11 | 0.345 :0.674E-11 | | | | |
| | | -2.29 :0.102E-07 | -2.29 :0.102E-07 | -2.29 :0.102E-07 | -2.29 :0.102E-07 | -2.29 :0.102E-07 | | | | |
| | | -1.69 :0.482E-01 | -1.70 :-492E-01 | -1.71 :0.501E-01 | -1.72 :-509E-01 | -1.73 :0.517E-01 | | | | |
| | | -1.69 :-482E-01 | -1.70 :0.492E-01 | -1.71 :-501E-01 | -1.72 :0.509E-01 | -1.73 :-517E-01 | | | | |
| | | | | | | | | | | |
| Current (mA) | / | 264.0000 | 268.0000 | 272.0000 | 276.0000 | 280.0000 | | | | |
| Bunch length (cm) | / | 20.0599 | 20.1607 | 20.2605 | 20.3594 | 20.4572 | | | | |
| Synchrotron tune | / | 0.0079 | 0.0079 | 0.0079 | 0.0079 | 0.0079 | | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | |
| | | 0.342 :0.143E-10 | 0.340 :0.116E-10 | 0.337 :0.534E-12 | 0.335 :0.838E-11 | 0.333 :-513E-10 | | | | |
| | | -2.29 :0.102E-07 | -2.29 :0.102E-07 | -2.29 :0.102E-07 | -2.29 :0.102E-07 | -2.29 :0.102E-07 | | | | |
| | | -1.74 :-523E-01 | -1.75 :0.528E-01 | -1.76 :-533E-01 | -1.77 :0.536E-01 | -1.78 :-538E-01 | | | | |
| | | -1.74 :0.523E-01 | -1.75 :-528E-01 | -1.76 :0.533E-01 | -1.77 :-536E-01 | -1.78 :0.538E-01 | | | | |
| | | | | | | | | | | |
| Current (mA) | / | 284.0000 | 288.0000 | 292.0000 | 296.0000 | 300.0000 | | | | |
| Bunch length (cm) | / | 20.5542 | 20.6503 | 20.7454 | 20.8397 | 20.9332 | | | | |
| Synchrotron tune | / | 0.0079 | 0.0079 | 0.0079 | 0.0079 | 0.0079 | | | | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | |
| | | 0.330 :0.259E-10 | 0.328 :0.160E-11 | 0.326 :0.114E-10 | 0.324 :0.139E-11 | 0.321 :0.564E-11 | | | | |
| | | -2.29 :0.102E-07 | -1.80 :0.540E-01 | -2.53 :-896E-10 | -2.54 :0.461E-11 | -2.55 :0.137E-09 | | | | |
| | | -1.79 :0.540E-01 | -1.80 :-540E-01 | -1.80 :-540E-01 | -1.81 :0.539E-01 | -1.82 :-536E-01 | | | | |

| | | | | | | | | | | | |
|-------------------|---|--------------------|------------|----------|------------|----------|----------------------------|----------|------------|----------|------------|
| | | -1.79 | :-.540E-01 | -1.80 | :0.540E-01 | -1.80 | ² :0.540E-01 | -1.81 | :-.539E-01 | -1.82 | :0.536E-01 |
| Current (mA) | / | 304.0000 | | 308.0000 | | 312.0000 | | 316.0000 | | 320.0000 | |
| Bunch length (cm) | / | 21.0258 | | 21.1176 | | 21.2086 | | 21.2989 | | 21.3884 | |
| Synchrotron tune | / | 0.0079 | | 0.0079 | | 0.0079 | | 0.0079 | | 0.0079 | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | | |
| | | 0.319 | :0.702E-11 | 0.317 | :0.508E-11 | 0.315 | :0.644E-11 | 0.313 | :0.566E-11 | 0.311 | :0.365E-11 |
| | | -2.56 | :0.320E-09 | -2.57 | :-.386E-10 | -2.57 | :-.469E-10 | -2.58 | :-.136E-10 | -2.59 | :0.116E-09 |
| | | -1.83 | :0.533E-01 | -1.84 | :-.530E-01 | -1.85 | :0.525E-01 | -1.85 | :-.520E-01 | -1.86 | :0.514E-01 |
| | | -1.83 | :-.533E-01 | -1.84 | :0.530E-01 | -1.85 | :-.525E-01 | -1.85 | :0.520E-01 | -1.86 | :-.514E-01 |
| | | | | | | | | | | | |
| Current (mA) | / | 324.0000 | | 328.0000 | | 332.0000 | | 336.0000 | | 340.0000 | |
| Bunch length (cm) | / | 21.4771 | | 21.5652 | | 21.6525 | | 21.7391 | | 21.8250 | |
| Synchrotron tune | / | 0.0079 | | 0.0079 | | 0.0079 | | 0.0079 | | 0.0079 | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | | |
| | | 0.309 | :0.114E-10 | 0.307 | :0.523E-12 | 0.305 | :0.280E-11 | 0.303 | :0.957E-11 | 0.301 | :0.898E-11 |
| | | -2.60 | :0.194E-10 | -2.61 | :0.241E-09 | -2.62 | :0.733E-10 | -2.63 | :0.303E-10 | -2.63 | :-.655E-09 |
| | | -1.87 | :-.508E-01 | -1.88 | :0.501E-01 | -1.88 | :-.493E-01 | -1.89 | :0.485E-01 | -1.90 | :-.476E-01 |
| | | -1.87 | :0.508E-01 | -1.88 | :-.501E-01 | -1.88 | :0.493E-01 | -1.89 | :-.485E-01 | -1.90 | :0.476E-01 |
| | | | | | | | | | | | |
| Current (mA) | / | 344.0000 | | 348.0000 | | 352.0000 | | 356.0000 | | 360.0000 | |
| Bunch length (cm) | / | 21.9103 | | 21.9948 | | 22.0788 | | 22.1621 | | 22.2448 | |
| Synchrotron tune | / | 0.0079 | | 0.0079 | | 0.0079 | | 0.0079 | | 0.0079 | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | | |
| | | 0.299 | :0.856E-11 | 0.297 | :0.493E-11 | 0.295 | :-.251E-10 | 0.293 | :0.109E-11 | 0.291 | :0.308E-12 |
| | | -2.64 | :0.121E-10 | -2.65 | :0.116E-09 | -2.66 | :-.379E-11 | -2.67 | :0.653E-09 | -2.68 | :-.231E-10 |
| | | -1.90 | :0.466E-01 | -1.91 | :-.457E-01 | -1.92 | :0.446E-01 | -1.92 | :-.436E-01 | -1.93 | :0.425E-01 |
| | | -1.90 | :-.466E-01 | -1.91 | :0.457E-01 | -1.92 | :-.446E-01 | -1.92 | :0.436E-01 | -1.93 | :-.425E-01 |
| | | | | | | | | | | | |
| Current (mA) | / | 364.0000 | | 368.0000 | | 372.0000 | | 376.0000 | | 380.0000 | |
| Bunch length (cm) | / | 22.3269 | | 22.4084 | | 22.4893 | | 22.5696 | | 22.6494 | |
| Synchrotron tune | / | 0.0079 | | 0.0079 | | 0.0079 | | 0.0079 | | 0.0079 | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | | |
| | | 0.289 | :0.109E-10 | 0.287 | :0.785E-12 | 0.285 | :0.584E-11 | 0.284 | :0.293E-11 | 0.282 | :0.958E-11 |
| | | -2.68 | :0.638E-10 | -2.69 | :0.505E-10 | -2.70 | :0.700E-10 | -2.71 | :-.101E-09 | -2.72 | :-.119E-09 |
| | | -1.94 | :-.413E-01 | -1.94 | :0.401E-01 | -1.95 | :-.389E-01 | -1.95 | :0.376E-01 | -1.96 | :-.363E-01 |
| | | -1.94 | :0.413E-01 | -1.94 | :-.401E-01 | -1.95 | :0.389E-01 | -1.95 | :-.376E-01 | -1.96 | :0.363E-01 |
| | | | | | | | | | | | |
| Current (mA) | / | 384.0000 | | 388.0000 | | 392.0000 | | 396.0000 | | 400.0000 | |
| Bunch length (cm) | / | 22.7285 | | 22.8072 | | 22.8853 | | 22.9629 | | 23.0399 | |
| Synchrotron tune | / | 0.0079 | | 0.0079 | | 0.0079 | | 0.0079 | | 0.0079 | |
| (Nu-Nux)/Nus ... | | (REAL : IMAGINARY) | | | | | | | | | |
| | | 0.280 | :0.378E-10 | 0.278 | :0.967E-11 | 0.277 | :0.228E-11 | 0.275 | :0.112E-10 | 0.00 | : 0.00 |
| | | -2.73 | :-.448E-10 | -2.74 | :0.148E-09 | -2.74 | :0.346E-10 | -2.75 | :-.126E-09 | 0.00 | : 0.00 |
| | | -1.96 | :0.350E-01 | -1.97 | :-.336E-01 | -1.97 | :0.322E-01 | -1.98 | :-.307E-01 | 0.00 | : 0.00 |
| | | -1.96 | :-.350E-01 | -1.97 | :0.336E-01 | -1.97 | :-.322E-01 | -1.98 | :0.307E-01 | 0.00 | : 0.00 |

1PROBLEM = SAMPLE INPUT #2 DCI OF ORSAY WITH BETATRON TUNE SPREAD

30/ 8/ 5 14:27:59

(*) = Real part of $(\text{Nu}-\text{Nux})/\text{Nus}$ vs. the bunch current (mA)

1.00E+00

0.00E+00

-1.00E+00


-2.00E+00

-3.00E+00

0 0.00E+00 5.00E+01 1.00E+02 1.50E+02 2.00E+02 2.50E+02 3.00E+02 3.50E+02

3

NUS= 0.792E-02 ENGY/GeV= 0.800 SPRD= 0.00
 REVFRQ/MHz= 3.17 SGMZ/cm= -1.00 BETAC/m= 8.86
 FREQ/MHz= 0.130E+04 ALPHA= 0.788E-01 CHROM= 0.00
 LZOT=F RS/MOhm/m= 0.400 QV= 1.00
 LBIN=F MU= 0




1PROBLEM = SAMPLE INPUT #2 DCI OF ORSAY WITH BETATRON TUNE SPREAD

30/ 8/ 5 14:27:59 <<< DISPERSION INTEGRAL METHOD >>>

4
 NUS= 0.792E-02 ENG/GeV= 0.800 SPRD= 0.500E-03
 REVRQ/MHz= 3.17 SGMZ/cm= -1.00 BETAC/m= 8.86
 FREQ/MHz= 0.130E+04 ALPHA= 0.788E-01 CHROM= 0.00
 LZOT=F RS/MOhm/m= 0.400 QV= 1.00
 LBIN=F MU= 0

(*) = Real part of (Nu-Nux)/Nus vs. the bunch current (mA)



TOTAL CPU TIME USED: 2.14 (S)

5

```

      NUS= 0.792E-02
      REVFRQ/MHz= 3.17
      FREQ/MHz= 0.130E+04
      LZOT=F

```

```

ENG/GeV= 0.800
SGMZ/cm= -1.00
ALPHA= 0.788E-01
RS/MOhm/m= 0.400
LBIN=F


```

```

      SPRD= 0.00
      BETAC/m= 8.86
      CHROM= 0.00
      QV= 1.00
      MU= 0


```

(*) = Imaginary part of $(Nu - Nux)/Nus$ vs. the bunch current (mA)



6
 1PROBLEM = SAMPLE INPUT #2 DCI OF ORSAY WITH BETATRON TUNE SPREAD
 30/ 8/ 5 14:27:59 <<< DISPERSION INTEGRAL METHOD >>>
 (*) = Imaginary part of (Nu-Nux)/Nus vs. the bunch current (mA)

| | | |
|---------------------|------------------|-----------------|
| NUS= 0.792E-02 | ENG/GeV= 0.800 | SPRD= 0.500E-03 |
| REVFREQ/MHz= 3.17 | SGMZ/cm= -1.00 | BETAC/m= 8.86 |
| FREQ/MHz= 0.130E+04 | ALPHA= 0.788E-01 | CHROM= 0.00 |
| LZOT=F | RS/MOhm/m= 0.400 | QV= 1.00 |
| | LBIN=F | MU= 0 |




TOTAL CPU TIME USED: 2.14 (S)

– Real Part of $(\nu - \nu_x)/\nu_s$ –

MOSES -- SAMPLE INPUT #2 DCI OF ORSAY WITH BETATRON TUNE SPREAD


30/ 8/ 5 14:27:59 VERSION 4.0 CPU TIME USED: 2.14 (s)



– Real Part of $(\nu - \nu_x)/\nu_s$ –

MOSES -- SAMPLE INPUT #2 DCI OF ORSAY WITH BETATRON TUNE SPREAD

30/ 8/ 5 14:27:59 VERSION 4.0 CPU TIME USED: 2.14 (s)




SPRD = 0.500E-03
 NUS = 0.792E-02
 ENGY = 0.800 (GeV)
 SGMZ = -1.00 (cm)
 BETAC = 8.86 (m)
 REVFRQ = 3.17 (MHz)
 ALPHA = 0.788E-01
 CHORM = 0.00
 FREQ = 0.130E+04 (MHz)
 RS = 0.400 (Mhm/m)
 QV = 1.00
 LBIN = F
 MU = 0

– Imaginary Part of $(\nu - \nu_x)/\nu_s$ –

MOSES -- SAMPLE INPUT #2 DCI OF ORSAY WITH BETATRON TUNE SPREAD

30/ 8/ 5 14:27:59 VERSION 4.0 CPU TIME USED: 2.14 (s)



– Imaginary Part of $(\nu - \nu_x)/\nu_s$ –

MOSES -- SAMPLE INPUT #2 DCI OF ORSAY WITH BETATRON TUNE SPREAD

30/ 8/ 5 14:27:59 VERSION 4.0 CPU TIME USED: 2.14 (s)

